

Management Committee Meeting - October 26, 2016 + Revised

2 DEFINITIONS

The following definitions are applicable to the ISO Services Tariff:

2.1 Definitions - A

Actual Energy Injections: Energy injections which are measured using a revenue-quality real-time meter.

Actual Energy Withdrawals: Energy withdrawals which are either: (1) measured with a revenue-quality real-time meter; (2) assessed (in the case of Load Serving Entities ("LSEs") serving retail customers where withdrawals are not measured by revenue-quality real-time meters) on the basis provided for in a Transmission Owner's retail access program; or (3) calculated (in the case of wholesale customers where withdrawals are not measured by revenue-quality real-time meters), until such time as revenue - quality real-time metering is available on a basis agreed upon by the unmeasured wholesale customers.

Advance Reservation: (1) A reservation of transmission service over the Cross-Sound Scheduled Line that is obtained in accordance with the applicable terms of Schedule 18 and the Schedule 18 Implementation Rule of the ISO New England Inc. Transmission, Markets and Services Tariff, or in accordance with any successors thereto; or (2) A right to schedule transmission service over the Neptune Scheduled Line that is obtained in accordance with the rules and procedures established pursuant to Section 38 of the PJM Interconnection, L.L.C. Open Access Transmission Tariff and set forth in a separate service schedule under the PJM Interconnection, L.L.C. Open Access Transmission Tariff; or (3) A right to schedule transmission service over the Linden VFT Scheduled Line that is obtained in accordance with the rules and procedures established pursuant to Section 38 of the PJM Interconnection, L.L.C. Open Access Transmission Tariff and set forth in a separate service schedule under the PJM Interconnection, L.L.C. Open Access Transmission Tariff; or (4) A right to schedule transmission service over the HTP Scheduled Line that is obtained in accordance with the rules and procedures established pursuant to Section 38 of the PJM Interconnection, L.L.C. Open Access Transmission Tariff and set forth in a separate service schedule under the PJM Interconnection, L.L.C. Open Access Transmission Tariff.

Adverse Conditions: Those conditions of the natural or man-made environment that threaten the adequate reliability of the NYS Power System, including, but not limited to, thunderstorms, hurricanes, tornadoes, solar magnetic flares and terrorist activities.

Adjusted Actual Load: Actual Load adjusted to reflect: (i) Load relief measures such as voltage reduction and Load Shedding; (ii) Load reductions provided by Demand Side Resources; (iii) normalized design weather conditions; (iv) Station Power delivered that is not being self supplied pursuant to Section 4.7 of the ISO Services Tariff; and (v) adjustments for Special Case Resources and EDRP.

Affiliate: With respect to a person or entity, any individual, corporation, partnership, firm, joint venture, association, joint-stock company, trust or unincorporated organization, directly or indirectly controlling, controlled by, or under common control with, such person or entity. The term "Control" shall mean the possession, directly or indirectly, of the power to direct the management or policies of a person or an entity. A voting interest of ten percent or more shall create a rebuttable presumption of control.

Ancillary Services: Services necessary to support the transmission of Energy from Generators to Loads, while maintaining reliable operation of the NYS Power System in accordance with Good Utility Practice and Reliability Rules. Ancillary Services include Scheduling, System Control and Dispatch Service; Reactive Supply and Voltage Support Service (or “Voltage Support Service”); Regulation Service; Energy Imbalance Service; Operating Reserve Service (including Spinning Reserve, 10-Minute Non-Synchronized Reserves and 30-Minute Reserves); and Black Start Capability.

Application: A request to provide or receive service pursuant to the provisions of the ISO Services Tariff, that includes all information reasonably requested by the ISO.

Automatic Generation Control (“AGC”): The **automatic** regulation of the power output of electric Generators within a prescribed range in response to a change in system frequency, or tie-line loading, to maintain system frequency or scheduled interchange with other areas within predetermined limits.

Available Generating Capacity: Generating Capacity that is on line to serve Load and/or provide Ancillary Services, or is capable of initiating start-up for the purpose of serving Transmission Customers or providing Ancillary Services, within thirty (30) minutes.

Available Operating Capacity: For purposes of determining a Scarcity Reserve Requirement, the capability of all Suppliers that are eligible to provide Operating Reserves and have submitted Energy Bids in the Real-Time Market to provide Energy in greater than 30 minutes but less than or equal to 60 minutes; provided, however, that this value shall not include any quantity of Energy and Operating Reserves scheduled to be provided by all such Suppliers. The Available Operating Capacity value (in MW) shall be calculated by the RTD software for each normal RTD run. For purposes of calculating a Scarcity Reserve Requirement in accordance with Section 15.4.6.2 of Rate Schedule 4 of this ISO Services Tariff, each RTD run shall utilize the value of Available Operating Capacity calculated during the immediately preceding normal RTD run and each RTC run shall utilize the value of Available Operating Capacity calculated during the most recently-completed normal RTD run prior to the RTC run.

Availability: A measure of time that a Generator, transmission line or other facility is or was capable of providing service, whether or not it actually is in-service.

Average Coincident Load (“ACL”): The value in each Capability Period calculated for each Special Case Resource, except those that are eligible to report a Provisional Average Coincident Load, that is equal to the average of the SCR’s metered hourly Load that is supplied by the NYS Transmission System and/or the distribution system during the Capability Period SCR Load Zone Peak Hours applicable to such SCR, and computed and reported in accordance with Section 5.12.11.1.1 of this Services Tariff and ISO Procedures. Any Load supported by generation produced from a Local Generator, other behind-the-meter generator, or other supply source located behind the SCR’s meter operating during the Capability Period SCR Load Zone Peak Hours may not be included in the SCR’s metered Load values reported for the ACL.

Average Coincident Load of an SCR Aggregation: The value that is equal to the sum of the Average Coincident Loads and Provisional Average Coincident Loads for all Special Case

Resources in an SCR Aggregation, assigned by the Responsible Interface Party to an SCR Aggregation in a single Load Zone, computed and reported monthly in accordance with Section 5.12.11.1.4 of this Services Tariff and ISO Procedures.

2.2 Definitions - B

Back-Up Operation: The procedures for operating the NYCA in a safe and reliable manner when the ISO's normal communication or computer systems are not fully functional as set forth in Section 5.3 of this ISO Services Tariff and Article 2.12 of the ISO OATT.

Base Point Signals: Electronic signals sent from the ISO and ultimately received by Generators or Demand Side Resources specifying the scheduled MW output for the Generator. Real-Time Dispatch ("RTD") Base Point Signals are typically sent to Generators or Demand Side Resources on a nominal five (5) minute basis. AGC Base Point Signals are typically sent to Generators or Demand Side Resources on a nominal six (6) second basis.

Basis Amount: The amount owed to the ISO for purchases of Energy and Ancillary Services excluding External Transactions in the Basis Month, after applying the Price Adjustment, as further adjusted by the ISO to reflect material changes in the extent of the Customer's participation in the ISO-administered Energy and Ancillary Services markets.

Basis Month: The month during the Prior Equivalent Capability Period in which the amount owed by the Customer for purchases of Energy and Ancillary Services excluding External Transactions, after applying the Price Adjustment, was greatest.

Bid/Post System: An electronic information system used to allow the posting of proposed transmission schedules and Bids for Energy and Ancillary Services by Market Participants for use by the ISO and to allow the ISO to post LBMPs and schedules.

Bid: Offer to sell or bid to purchase Energy, Demand Reductions or Transmission Congestion Contracts and an offer to sell Ancillary Services at a specified price that is duly submitted to the ISO pursuant to ISO Procedures. Bid shall mean a mitigated Bid where appropriate.

Bid Price: The price at which the Customer offering the Bid is willing to provide the product or service, or is willing to pay to receive such product or service, as applicable. In the case of a CTS Interface Bid, the Bid Price is a dollar value that indicates the bidder's willingness to purchase Energy at a CTS Source and sell it at a CTS Sink across a CTS Enabled Interface if, at the time of scheduling, the forecasted CTS Sink Price minus the forecasted CTS Source Price is greater than, or equal to, the dollar value specified in the Bid.

Bid Production Cost: Total cost of the Generators required to meet Load and reliability Constraints based upon Bids corresponding to the usual measures of Generator production cost (e.g., running cost, Minimum Generation Bid, and Start-Up Bid).

Bidder: An entity that bids to purchase Unforced Capacity in an Installed Capacity auction.

Bidding Requirement: The credit requirement for bidding in certain ISO-administered auctions, calculated in accordance with Section 26.4.3 of Attachment K to this Services Tariff.

Bilateral Transaction: A Transaction between two or more parties for the purchase and/or sale of Capacity or Energy other than those in the ISO Administered Markets. A request to schedule

a Bilateral Transaction in the Energy Market shall be considered a request to schedule Point-to-Point Transmission Service.

Billing Period: The period of time designated in Sections 7.2.2.1, 7.2.3.1, or 7.2.3.2 of this ISO Services Tariff over which the ISO will aggregate and settle a charge or a payment for services furnished under this ISO Services Tariff or the ISO OATT.

2.3 Definitions - C

Capability Period: Six-month periods which are established as follows: (i) from May 1 through October 31 of each year (“Summer Capability Period”); and (ii) from November 1 of each year through April 30 of the following year (“Winter Capability Period”).

Capability Period Auction: An auction conducted no later than thirty (30) days prior to the start of each Capability Period in which Unforced Capacity may be purchased and sold in a six-month strip.

Capability Period SCR Load Zone Peak Hours: The top forty (40) coincident peak hours that, prior to the Summer 2014 Capability Period include hour beginning thirteen through hour beginning eighteen and beginning with the Summer 2014 Capability Period include hour beginning eleven through hour beginning nineteen. The Capability Period SCR Load Zone Peak Hours shall be determined by the NYISO from the Prior Equivalent Capability Period and shall be used by RIPs to report ACL values for the purpose of SCR enrollment. For a SCR enrolled with a Provisional ACL that requires verification data to be reported at the end of the Capability Period in which the SCR was enrolled, the Capability Period SCR Load Zone Peak Hours shall be determined from the Capability Period in which the SCR was enrolled. Such hours shall not include (i) hours in which Special Case Resources located in the specific Load Zone were called by the ISO to respond to a reliability event or test and (ii) hours for which the Emergency Demand Response Program resources were deployed by the ISO in each specific Load Zone. In addition, beginning with the Summer 2014 Capability Period, the NYISO shall not include, in descending rank order of NYCA Load up to a maximum of eight hours per Capability Period, a) the hour before the start time of a reliability event or performance test, in which SCRs located in the specific Load Zone were called by the ISO to respond to a reliability event or performance test, or b) the hour immediately following the end time of such reliability event or performance test.

Capability Year: A Summer Capability Period, followed by a Winter Capability Period (*i.e.*, May 1 through April 30).

Capacity: The capability to generate or transmit electrical power, or the ability to control demand at the direction of the ISO, measured in megawatts (“MW”).

Capacity Limited Resource: A Resource that is constrained in its ability to supply Energy above its Normal Upper Operating Limit by operational or plant configuration characteristics. Capacity Limited Resources must register their Capacity limiting characteristics with, and justify them to, the ISO consistent with ISO Procedures. Capacity Limited Resources may submit a schedule indicating that their Normal Upper Operating Limit is a function depending on one or more variables, such as temperature or pondage levels, in which case the Normal Upper Operating Limit applicable at any time shall be determined by reference to that schedule.

Capacity Reservation Cap: The maximum percentage of transmission Capacity from a Transmission Owner’s sets of ETCNL that may be converted into ETCNL TCCs or the maximum percentage of a Transmission Owner’s RCRRs that may be converted into RCRR

TCCs, as the case may be, as established by the ISO pursuant to Section 19.4.3 of Attachment M of the OATT.

CARL Data: Control Area Resource and Load (“CARL”) data submitted by Control Area System Resources to the ISO.

Centralized Transmission Congestion Contracts (“TCC”) Auction (“Auction”): The process by which TCCs are released for sale for the Centralized TCC Auction period, through a bidding process administered by the ISO or an auctioneer.

Code of Conduct: The rules, procedures and restrictions concerning the conduct of the ISO directors and employees, contained in Attachment F to the ISO Open Access Transmission Tariff.

Commission (“FERC”): The Federal Energy Regulatory Commission, or any successor agency.

Compensable Overgeneration: A quantity of Energy injected over a given RTD interval in which a Supplier has offered Energy that exceeds the Real-Time Scheduled Energy Injection established by the ISO for that Supplier and for which the Supplier may be paid pursuant to this Section and ISO Procedures.

For Suppliers not covered by other provisions of this Section and Intermittent Power Resources depending on wind as their fuel for which the ISO has imposed a Wind Output Limit in the given RTD interval, Compensable Overgeneration shall initially equal three percent (3%) of the Supplier’s Normal Upper Operating Limit which may be modified by the ISO if necessary to maintain good Control Performance.

For a Generator which is operating in Start-Up or Shutdown Periods, or Testing Periods, or which is an Intermittent Power Resource that depends on solar energy or landfill gas for its fuel and which has offered its Energy to the ISO in a given interval not using the ISO-committed Flexible or Self-Committed Flexible bid mode, Compensable Overgeneration shall mean all Energy actually injected by the Generator that exceeds the Real-Time Scheduled Energy Injection established by the ISO for that Generator. For a Generator operating in intervals when it has been designated as operating Out of Merit at the request of a Transmission Owner or the ISO, Compensable Overgeneration shall mean all Energy actually injected by the Generator that exceeds the Real-Time Scheduled Energy Injection up to the Energy level directed by the Transmission Owner or the ISO.

For Intermittent Power Resources that depend on wind as their fuel and Limited Control Run of River Hydro Resources not using the ISO-Committed Flexible or Self-Committed Flexible bid mode, that were in operation on or before November 18, 1999 within the NYCA, plus an additional 3,300 MW of such Resources, Compensable Overgeneration shall mean that quantity of Energy injected by a Generator, over a given RTD interval that exceeds the Real-Time Scheduled Energy Injection established by the ISO for that Generator and for which the Generator may be paid pursuant to ISO Procedures; provided however, this definition of Compensable Overgeneration shall not apply to an Intermittent Power Resource depending on wind as its fuel for any interval for which the ISO has imposed a Wind Output Limit.

For a Generator comprised of a group of generating units at a single location, which grouped generating units are separately committed and dispatched by the ISO, and for which Energy injections are measured at a single location, Compensable Overgeneration shall mean that quantity of Energy injected by the Generator, during the period when one of its grouped generating units is operating in a Start-Up or Shutdown Period, that exceeds the Real-Time Scheduled Energy Injection established by the ISO for that period, for that Generator, and for which the Generator may be paid pursuant to ISO Procedures.

Completed Application: An Application that satisfies all of the information and other requirements for service under the ISO Services Tariff.

Confidential Information: Information and/or data that has been designated by a Customer to be proprietary and confidential, provided that such designation is consistent with the ISO Procedures, the ISO Services Tariff, and the ISO Code of Conduct.

Congestion: A characteristic of the transmission system produced by a constraint on the optimum economic operation of the power system, such that the marginal price of Energy to serve the next increment of Load, exclusive of losses, at different locations on the transmission system is unequal.

Congestion Component: The component of the LBMP measured at a location or the Transmission Usage Charge between two locations that is attributable to the cost of transmission Congestion as is more completely defined in Attachment B of the Services Tariff.

Congestion Rent: The opportunity costs of transmission Constraints on the NYS Transmission System. Congestion Rents are collected by the ISO from Loads through its facilitation of LBMP Market Transactions and the collection of Transmission Usage Charges from Bilateral Transactions.

Congestion Rent Shortfall: A condition in which the Congestion Rent revenue collected by the ISO in the Day-Ahead Market for Energy is less than the amount of Congestion Rent revenue in the Day-Ahead Market for Energy that the ISO is obligated under the ISO OATT to pay out to the Primary Holders of TCCs.

Constraint: An upper or lower limit placed on a variable or set of variables that are used by the ISO in its SCUC, RTC, or RTD programs to control and/or facilitate the operation of the NYS Transmission System.

Contingency: An actual or potential unexpected failure or outage of a system component, such as a Generator, transmission line, circuit breaker, switch or other electrical element. A Contingency also may include multiple components, which are related by situations leading to simultaneous component outages.

Control Area: An electric system or combination of electric power systems to which a common Automatic Generation Control scheme is applied in order to: (1) match, at all times, the power output of the Generators within the electric power system(s) and Capacity and Energy purchased from entities outside the electric power system(s), with the Load within the electric power

system(s); (2) maintain scheduled interchange with other Control Areas, within the limits of Good Utility Practice; (3) maintain the frequency of the electric power system(s) within reasonable limits in accordance with Good Utility Practice; and (4) provide sufficient Capacity to maintain Operating Reserves in accordance with Good Utility Practice.

Control Area System Resource: A set of Resources owned or controlled by an entity within a Control Area that also is the operator of such Control Area. Entities supplying Unforced Capacity using Control Area System Resources will not designate particular Resources as the suppliers of Unforced Capacity.

Control Performance: A standard for measuring the degree to which a Control Area is providing Regulation Service in conformance with NERC requirements.

Controllable Transmission: Any Transmission facility over which power-flow can be directly controlled by power-flow control devices without having to re-dispatch generation.

Commenced Repair: A determination by the ISO that a Market Participant with a Generator i) has decided to pursue the repair of its Generator, and based on the ISO's technical/engineering evaluation ii) has a Repair Plan for the Generator that is consistent with a Credible Repair Plan, and iii) has made appropriate progress in pursuing the repair of its Generator when measured against the milestones of a Credible Repair Plan.

Credible Repair Plan: A Repair Plan that meets the requirements described in Section 5.18.1.4 of this Services Tariff and in ISO Procedures.

Credit Assessment: An assessment of a Customer's creditworthiness, conducted by the ISO in accordance with Section 26.5.3 of Attachment K to this Services Tariff.

Cross-Sound Scheduled Line: A transmission facility that interconnects the NYCA to the New England Control Area at Shoreham, New York and terminates near New Haven, Connecticut.

CTS Enabled Interface: An External Interface at which the ISO has authorized the use of Coordinated Transaction Scheduling ("CTS") market rules and which includes a CTS Enabled Proxy Generator Bus for New York and a CTS Enabled Proxy Generator Bus for the neighboring Control Area.

CTS Enabled Proxy Generator Bus: A Proxy Generator Bus at which the ISO either requires or permits the use of CTS Interface Bids for Import and Export Transactions in the Real-Time Market and requires the use of Decremental Bids for Wheels Through in the Real-Time Market. A CTS Enabled Proxy Generator Bus at which the ISO permits CTS Interface Bids will also permit Decremental and Sink Price Cap Bids.

CTS Interface Bid: A Real-Time Bid provided by an entity engaged in an External Transaction at a CTS Enabled Interface. CTS Interface Bids shall include a MW amount, a direction indicating whether the proposed Transaction is to Import Energy to, or Export Energy from, the New York Control Area, and a Bid Price.

CTS Sink: Representation of the location(s) within a Control Area where energy associated with a CTS Interface Bid is withdrawn. The NYCA CTS Sinks are Proxy Generator Buses.

CTS Sink Price: The price at a CTS Sink.

CTS Source: Representation of the location(s) within a Control Area where energy associated with a CTS Interface Bid is injected. The NYCA CTS Sources are Proxy Generator Buses.

CTS Source Price: The price at a CTS Source.

Curtailement or Curtail: A reduction in Transmission Service in response to a transmission Capacity shortage as a result of system reliability conditions.

Curtailement Customer Aggregator: A Curtailement Services Provider that produces real-time verified reductions in NYCA load of at least 100 kW through contracts with retail end-users. The procedure for qualifying as a Curtailement Customer Aggregator is set forth in ISO procedures.

Curtailement Initiation Cost: The fixed payment, separate from a variable Demand Reduction Bid, required by a qualified Demand Reduction Provider in order to cover the cost of reducing demand.

Curtailement Services Provider: A qualified entity that can produce real-time, verified reductions in NYCA Load of at least 100 kW in a single Load Zone, pursuant to the Emergency Demand Response Program and related ISO procedures. The procedure for qualifying as a Curtailement Services Provider is set forth in Section 3 below and in ISO Procedures.

Curtailement Services Provider Capacity: Capacity from a Demand Side Resource nominated by a Curtailement Services Provider for participation in the Emergency Demand Response Program.

Customer: An entity which has complied with the requirements contained in the ISO Services Tariff, including having signed a Service Agreement, and is qualified to utilize the Market Services and the Control Area Services provided by the ISO under the ISO Services Tariff; provided, however, that a party taking services under the Tariff pursuant to an unsigned Service Agreement filed with the Commission by the ISO shall be deemed a Customer.

2.4 Definitions - D

DADRP Component: The credit requirement for a Demand Reduction Provider to bid into the Day-Ahead Market, and a component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

Day-Ahead: Nominally, the twenty-four (24) hour period directly preceding the Dispatch Day, except when this period may be extended by the ISO to accommodate weekends and holidays.

Day-Ahead LBMP: The LBMPs calculated based upon the ISO's Day-Ahead Security Constrained Unit Commitment process.

Day-Ahead Margin: That portion of Day-Ahead LBMP, Operating Reserves settlement or Regulation Service settlement for an hour that represents the difference between the Supplier's accepted Day-Ahead offer price and the Day-Ahead LBMP, Operating Reserves settlement or Regulation Service settlement for that hour.

Day-Ahead Margin Assurance Payment: A supplemental payment made to an eligible Supplier that buys out of a Day-Ahead Energy, Regulation Service, or Operating Reserves schedule such that an hourly balancing payment obligation offsets its Day-Ahead Margin. Rules for calculating these payments, and for determining Suppliers' eligibility to receive them, are set forth in Attachment J to this ISO Services Tariff.

Day-Ahead Market: The ISO Administered Market in which Capacity, Energy and/or Ancillary Services are scheduled and sold Day-Ahead consisting of the Day-Ahead scheduling process, price calculations and Settlements.

Day-Ahead Reliability Unit: A Day-Ahead committed Resource which would not have been committed but for a request by a Transmission Owner that the unit be committed in the Day-Ahead Market in order to meet the reliability needs of the Transmission Owner's local system or as the result of the ISO's analysis indicating the unit was needed in order to meet the reliability requirements of the NYCA.

Decremental Bid: A monotonically increasing Bid curve provided by an entity engaged in a Bilateral Import, other than an entity submitting a CTS Interface Bid, or Internal Transaction to indicate the LBMP below which that entity is willing to reduce its Generator's output, and purchase Energy in the LBMP Markets, or by an entity engaged in a Wheel Through Transaction to indicate the Congestion Component cost at or below which that entity is willing to accept Transmission Service.

Demand Reduction: A quantity of reduced electricity demand from a Demand Side Resource that is bid, produced, purchased or sold over a period of time and measured or calculated in

Megawatt hours. Demand Reductions offered by a Demand Side Resource as Energy in the LBMP Markets may only be offered in the Day-Ahead Market, and shall be offered only by a Demand Reduction Provider. The same Demand Reduction may not be offered by a Demand Reduction Provider and by a customer as Operating Reserves or Regulation Service.

Demand Reduction Aggregator: A Demand Reduction Provider, qualified pursuant to ISO Procedures, that bids Demand Side Resources of at least 1 MW through contracts with Demand Side Resources and is not a Load Serving Entity.

Demand Reduction Incentive Payment: A payment to Demand Reduction Providers that are scheduled to make Day-Ahead Demand Reductions. The payment shall be equal to the product of: (a) the Day-Ahead hourly LBMP at the applicable Demand Reduction bus; and (b) the lesser of the actual hourly Demand Reduction or the Day-Ahead scheduled hourly Demand Reduction in MW.

Demand Reduction Provider: A Customer that is eligible, pursuant to the relevant ISO Procedures, to bid Demand Side Resources of at least 1 MW as Energy into the Day-Ahead Market. A Demand Reduction Provider can be (i) a Load Serving Entity or (ii) a Demand Reduction Aggregator.

Demand Side Ancillary Service Program (DSASP): An ISO program that allows qualified DSASP Resources to participate in the ISO's Day-Ahead and Real-Time Markets for Operating Reserves and Regulation Service in accordance with the ISO Services Tariff and ISO Procedures.

Demand Side Ancillary Service Program Resource (DSASP Resource): A Demand Side Resource or an aggregation of Demand Side Resources located in the NYCA with at least 1 MW of load reduction that is represented by a point identifier (PTID) and is assigned to a Load Zone or Subzone by the ISO and that is:

- i. Capable of controlling demand in a responsive, measurable and verifiable manner within time limits prescribed by the ISO; and
- ii. Qualified to participate in the ISO's Ancillary Services market as a Supplier of Operating Reserves or Regulation Service pursuant to the ISO Services Tariff and ISO Procedures.

Demand Side Ancillary Service Program Provider (DSASP Provider): A Customer that is eligible, pursuant to the ISO Tariff and ISO Procedures, to offer DSASP Resource(s) as Operating Reserves or Regulation Service in the Day-Ahead or Real-Time Market. A DSASP Provider is responsible for enrolling its DSASP Resource(s), and, when communicating directly with the ISO via telemetry, is responsible for dispatching its DSASP Resource(s).

Demand Side Resource: A Resource located in the NYCA that: (i) is capable of controlling demand by either curtailing its Load or by operating a Local Generator to reduce Load from the NYS Transmission System and/or the distribution system at the direction of the ISO, in a responsive, measurable and verifiable manner within time limits, and (ii) is qualified to participate in competitive Energy, Capacity, Operating Reserves or Regulation Service markets, or in the Emergency Demand Response Program pursuant to this ISO Services Tariff and the ISO Procedures.

Dennison Scheduled Line: A transmission facility that interconnects the NYCA to the Hydro Quebec Control Area at the Dennison substation, located near Massena, New York and extends through the province of Ontario, Canada (near the City of Cornwall) to the Cedars substation in Quebec, Canada.

Dependable Maximum Net Capability (“DMNC”): The sustained maximum net output of a Generator, as demonstrated by the performance of a test or through actual operation, averaged over a continuous time period as defined in the ISO Procedures.

Desired Net Interchange (“DNI”): A mechanism used to set and maintain the desired Energy interchange (or transfer) between two Control Areas; it is scheduled ahead of time and can be changed manually in real-time.

Direct Sale: The sale of TCCs directly to a buyer by the Primary Owner through a non-discriminatory auditable sale conducted on the ISO’s OASIS, in compliance with the requirements and restrictions set forth in Commission Order Nos. 888 et seq. and 889 et seq.

Dispatchable: A bidding mode in which Generators or Demand Side Resources indicate that they are willing to respond to real-time control from the ISO. Dispatchable Generators may be either ISO-Committed Flexible or Self-Committed Flexible. Dispatchable Demand Side Resources must be ISO-Committed Flexible. Dispatchable Resources that are not providing Regulation Service will follow five-minute RTD Base Point Signals. Dispatchable Resources that are providing Regulation Service will follow six-second AGC Base Point Signals.

Dispatch Day: The twenty-four (24) hour (or, if appropriate, the twenty-three (23) or twenty-five (25) hour) period commencing at the beginning of each day (0000 hour).

Dispute Resolution Administrator (“DRA”): An individual hired by the ISO to administer the Expedited Dispute Resolution Procedures in Section 5.17 of the ISO Services Tariff.

DMNC Test Period: The period within a Capability Period during which a Resource required to do so pursuant to ISO procedures shall conduct a DMNC test if that DMNC test is to be valid for purposes of determining the amount of Installed Capacity used to calculate the Unforced

Capacity that this Resource is permitted to supply to the NYCA. Such periods will be established pursuant to the ISO Procedures.

DSASP Baseline MW: The value of the Load level of a DSASP resource in the dispatch interval immediately preceding the interval with a non-zero Base Point Signal, where the status of the regulation flag is set to the off condition for either Operating Reserves or Regulation service.

DSASP Component: The credit requirement for a Demand Side Resource to offer Ancillary Services, and a component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

Dynamically Scheduled Proxy Generator Bus: A Proxy Generator Bus for which the ISO may schedule Transactions at 5 minute intervals in real time. Dynamically Scheduled Proxy Generator Buses are identified in Section 4.4.4 of the Services Tariff.

2.5 Definitions - E

East of Central-East: An electrical area comprised of Load Zones F, G, H, I, J, and K, as identified in the ISO Procedures.

East of Central-East Excluding Long Island: An electrical area comprised of Load Zones F, G, H, I, and J, as identified in the ISO Procedures.

East of Central-East Excluding New York City and Long Island: An electrical area comprised of Load Zones F, G, H, and I, as identified in the ISO Procedures.

Economic Operating Point: The megawatt quantity which is a function of: i) the real-time LBMP at the Resource bus; and ii) the Supplier's real-time eleven constant cost step Energy Bid, for the Resource, such that (a) the offer price associated with Energy offers below that megawatt quantity (if that megawatt quantity is not that Resource's minimum output level) must be less than or equal to the real-time LBMP at the Resource bus, and (b) the offer price associated with Energy offers above that megawatt quantity (if that megawatt quantity is not that Resource's maximum output level) must be greater than or equal to the real-time LBMP at the Resource bus. In cases where multiple megawatt values meet conditions (a) and (b), the Economic Operating Point is the megawatt value meeting these conditions that is closest to the Resource's real-time scheduled Energy injection. In cases where the Economic Operating Point would be less than the minimum output level, the Economic Operating Point will be set equal to the MW value of the first point on the Energy Bid curve and in cases where the Economic Operating Point would be greater than the maximum output level, the Economic Operating Point will be set equal to the MW value of the last point on the Energy Bid curve.

Emergency: Any abnormal system condition that requires immediate automatic or manual action to prevent or limit loss of transmission facilities or Generators that could adversely affect the reliability of an electric system.

Emergency Demand Response Program ("EDRP"): A program pursuant to which the ISO makes payments to Curtailment Service Providers that voluntarily take effective steps in real time, pursuant to ISO procedures, to reduce NYCA demand in Emergency conditions.

Emergency State: The state that the NYS Power System is in when an abnormal condition occurs that requires automatic or immediate, manual action to prevent or limit loss of the NYS Transmission System or Generators that could adversely affect the reliability of the NYS Power System.

Emergency Upper Operating Limit (UOL_E): The upper operating limit that a Generator indicates it expects to be able to reach, or the maximum amount of demand that a Demand Side Resource expects to be able to reduce, at the request of the ISO during extraordinary conditions. Each Generator or Demand Side Resource shall specify a UOL_E in its bids that shall be equal to or greater than its stated Normal Upper Operating Limit.

Energy ("MWh"): A quantity of electricity that is bid, produced, purchased, consumed, sold, or transmitted over a period of time, and measured or calculated in megawatt hours.

Energy and Ancillary Services Component: A component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

Energy Limited Resource: Capacity resources that, due to environmental restrictions on operations, cyclical requirements, such as the need to recharge or refill, or other non-economic reasons, are unable to operate continuously on a daily basis, but are able to operate for at least four consecutive hours each day. Energy Limited Resources must register their Energy limiting characteristics with, and justify them to, the ISO consistent with ISO Procedures.

Equivalent Demand Forced Outage Rate: The portion of time a unit is in demand, but is unavailable due to forced outages.

Equivalency Rating: A rating determined by the ISO, at a Customer's request, based on the ISO's financial evaluation of an Unrated Customer that shall serve as the starting point of the ISO's determination of an amount of Unsecured Credit to be granted to the Customer, if any, as provided in Table K-1 of Attachment K to this Services Tariff.

ETA Agent: A Customer of the ISO that has been appointed by a Load Serving Entity and approved by the ISO in accordance with ISO Procedures for the purpose of enabling that Customer to hold all of the rights and obligations associated with Fixed Price TCCs, as provided for in this Services Tariff.

ETCNL TCC: A TCC created when a Transmission Owner with ETCNL exercises its right to convert a megawatt of ETCNL into a TCC pursuant to Section 19.4.1 of Attachment M of the OATT.

Excess Amount: The difference, if any, between the dollar amounts charged to purchasers of Unforced Capacity in an ISO-administered Unforced Capacity auction and the dollar amounts paid to sellers of Unforced Capacity in that ISO-administered Installed Capacity auction.

Excess Congestion Rents: Congestion revenues in the Day-Ahead Market for Energy collected by the ISO that are in excess of its Day-Ahead payment obligations. Excess Congestion Rents may arise if Congestion occurs in the Day-Ahead Market for Energy and if the Day-Ahead Transfer Capability of the transmission system is not exhausted by the set of TCCs and Grandfathered Rights that have been allocated at the completion of the last Centralized TCC Auction.

Existing Transmission Capacity for Native Load ("ETCNL"): Transmission Capacity reserved on a Transmission Owner's transmission system to serve the Native Load Customers of the current Transmission Owners (as of the filing date of the original ISO Tariff - January 31, 1997). This includes transmission Capacity required: (1) to deliver the output from operating facilities located out of a Transmission Owner's Transmission District; (2) to deliver power purchased under power supply contracts; and (3) to deliver power purchased under third party agreements (*i.e.*, Non-Utility Generators). Existing Transmission Capacity for Native Load is listed in Attachment L of the ISO OATT.

Existing Transmission Agreement ("ETA"): An agreement between two or more Transmission Owners, or between a Transmission Owner and another entity, in existence at the time of ISO

start-up and providing for transmission service by a Transmission Owner to another Transmission Owner or another entity. Table 1A of Attachment L lists all ETAs. ETAs include Transmission Wheeling Agreements (including MWAs and Third Party TWAs) and Transmission Facility Agreements.

Expected EDRP/SCR MW: The aggregate Load reduction (in MW) expected to be realized from EDRP and/or SCRs during the real-time intervals that the ISO has called upon EDRP and/or SCRs to provide Load reduction in a Scarcity Reserve Region, as determined based on the ISO's calculation of the historical performance of EDRP and SCRs. There will be separate values for voluntary and mandatory Load reductions. When determining the historical performance of SCRs, provision of Load reduction shall be deemed mandatory if the ISO has satisfied the notification requirements set forth in Section 5.12.11.1 of this ISO Services Tariff as it relates to the SCRs in the applicable Load Zone, otherwise provision of such Load reduction shall be deemed voluntary. When determining the historical performance of the EDRP, provision of Load reduction by EDRP shall be deemed voluntary.

Expected Load Reduction: For purposes of determining the Real-Time Locational Based Marginal Price, the reduction in Load expected to be realized in real-time from activation of the Emergency Demand Response Program and from Load reductions requested from Special Case Resources, as established pursuant to ISO Procedures.

Expedited Dispute Resolution Procedures: The dispute resolution procedures applicable to disputes arising out of the Installed Capacity provisions of this ISO Services Tariff (as set forth in Section 5.17) and the Customer settlements provisions of this ISO Services Tariff (as set forth in Section 7.4.3).

Export: A Bilateral Transaction or purchase from the LBMP Market where the Energy is delivered to an NYCA Interconnection with another Control Area.

Export Credit Requirement: A component of the External Transaction Component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

External: An entity (e.g., Supplier, Transmission Customer) or facility (e.g., Generator, Interface) located outside the Control Area being referenced or between two or more Control Areas. Where a specific Control Area is not referenced, the NYCA is the intended reference.

External Transaction Component: A component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

External Transactions: Purchases, sales or exchanges of Energy, Capacity or Ancillary Services for which either the Point of Injection ("POI") or Point of Withdrawal ("POW") or both are located outside the NYCA (i.e., Exports, Imports or Wheels Through).

2.6 Definitions - F

Facility Flow-Based Methodology: The methodology, as described in Section 17.5.3.7 of Attachment B, used to allocate Net Auction Revenue among Transmission Owners.

Federal Power Act (“FPA”): The Federal Power Act, as may be amended from time-to-time (See 16 U.S.C. § 796 *et seq.*).

Firm Point-To-Point Transmission Service: Transmission Service under this Tariff that is scheduled between specified Points of Receipt and Delivery pursuant to the ISO OATT. Firm Point-To-Point Transmission Service is service for which the Transmission Customer has agreed to pay the Congestion associated with its service. A Transmission Customer may fix the price of Congestion associated with its Firm Point-To-Point Transmission Service by acquiring sufficient TCCs with the same Points of Receipt and Delivery as its Transmission Service.

Firm Transmission Service: Transmission service requested by a Transmission Customer willing to pay Congestion Rent.

First Settlement: The process of establishing binding financial commitments on the part of Customers participating in the Day-Ahead Market based on Day-Ahead LBMP.

Fixed Block Unit: A unit that, due to operational characteristics, can only be dispatched in one of two states: either turned completely off, or turned on and run at a fixed capacity level.

Fixed Price TCC: TCCs obtained pursuant to Sections 19.2.1 or 19.2.2 of Attachment M of the ISO OATT. If a TCC is obtained pursuant to Section 19.2.1 of Attachment M of the OATT, it is an Historic Fixed Price TCC. If a TCC is awarded to an LSE pursuant to the provisions of Section 19.2.2 of Attachment M of the OATT, it is a Non-Historic Fixed Price TCC.

Forced Outage: An unscheduled inability of a Market Participant’s Generator to produce Energy that does not meet the notification criteria to be classified as a scheduled outage or de-rate as established in ISO Procedures. If the Forced Outage of a Generator starts on or after May 1, 2015, the Forced Outage will expire at the end of the month which contains the 180th day of its Forced Outage but may be extended if the Market Participant has Commenced Repair of its Generator.

2.7 Definitions - G

GADS Data: Data submitted to the NERC for collection into the NERC's Generating Availability Data System ("GADS").

Gap Solution: This term shall have the meaning given in Attachment Y to the OATT.

Generator: A facility capable of supplying Energy, Capacity and/or Ancillary Services that is accessible to the NYCA. A Generator comprised of a group of generating units at a single location, which grouped generating units are separately committed and dispatched by the ISO, and for which Energy injections are measured at a single location, and each unit within that group, shall be considered a Generator.

G-J Locality: The Locality comprised of Load Zones G, H, I, and J collectively.

Good Utility Practice: Any of the practices, methods or acts engaged in or approved by a significant portion of the electric utility industry during the relevant time period, or any of the practices, methods or acts which, in the exercise of reasonable judgment in light of the facts known at the time the decision was made, could have been expected to accomplish the desired result at a reasonable cost consistent with good business practices, reliability, safety and expedition. Good Utility Practice is not intended to be limited to the optimum practice, method or act to the exclusion of all others, but rather to delineate acceptable practices, methods, or acts generally accepted in the region, including those practices required by Federal Power Act Section 215(a)(4).

Grandfathered Rights: The transmission rights associated with: (1) Modified Wheeling Agreements; (2) Transmission Facility Agreements; and (3) Third Party Transmission Wheeling Agreements where the party entitled to exercise the transmission rights associated with such Agreements has chosen, as provided in the Tariff, to retain those rights rather than to convert those rights to Grandfathered TCCs.

Grandfathered TCCs: The TCCs associated with: (1) Modified Wheeling Agreements; (2) Transmission Facility Agreements with transmission wheeling provisions; and (3) Third Party TWAs where the party entitled to exercise the transmission rights associated with such Agreements has chosen, as provided by the Tariff, to convert those rights to TCCs.

2.8 Definitions - H

HTP Scheduled Line: A transmission facility that interconnects the NYCA to the PJM Interconnection, L.L.C. Control Area at the West 49th Street Substation, New York, New York and terminates in Ridgefield, New Jersey.

2.9 Definitions - I

ICAP Demand Curve: A series of prices which decline until reaching zero as the amount of Installed Capacity increases.

ICAP Demand Curve Reset Filing Year: A calendar year in which the ISO files ICAP Demand Curves, in accordance with Section 5.14.1.2.1.11 or Section 5.14.1.2.2.4.11.

ICAP Ineligible Forced Outage: The outage state of a Market Participant's Generator after: i) the expiration or termination of its Forced Outage pursuant to the provisions in Section 5.18.1.6 of this Services Tariff, which Forced Outage started on or after May 1, 2015; ii) the Market Participant voluntarily reclassified its Forced Outage pursuant to the provisions in Section 5.18.2.1 of this Services Tariff, which Forced Outage started on or after May 1, 2015; or iii) substantial actions have been taken, such as dismantling or disabling essential equipment, which actions are inconsistent with an intention to return the Generator to operation and the Energy market. A Generator in an ICAP Ineligible Forced Outage is subject to the return-to-service provisions in Section 5.18.4 of this Services Tariff and is ineligible to participate in the Installed Capacity market.

ICAP Spot Market Auction: An auction conducted pursuant to Section 5.14.1.1 of this Tariff to procure and set LSE Unforced Capacity Obligations for the subsequent Obligation Procurement Period, pursuant to the Demand Curves applicable to each respective LSE and the supply that is offered.

[Import Constrained Locality: New York City and the G-J Locality.](#)

Import Credit Requirement: A component of the External Transaction Component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

Import Curtailment Guarantee Payment: A payment made in accordance with Section 4.5.3.2 and Attachment J of this ISO Services Tariff to compensate a Supplier whose Import is Curtailed by the ISO.

Imports: A Bilateral Transaction or sale to the LBMP Market where Energy is delivered to a NYCA Interconnection from another Control Area.

Imputed LBMP Revenue: Revenue developed for calculating a Generator or Import Bid Production Cost guarantee, for any interval, which equals the product of (i) the Bilateral Transaction scheduled MW in the Day-Ahead Market or real-time market, as appropriate, from the Generator bus or Proxy Generator Bus, as appropriate, for the interval, (ii) the LBMP, in units of \$/MWh, either Day-Ahead or real-time as appropriate, at the Generator or Proxy Generator Bus for that interval and (iii) the length of the interval, in units of hours.

Inactive Reserves: The outage state in which a Market Participant's Generator is unavailable to produce Energy for a limited period of time not to exceed six months, for reasons that are not equipment related, which state does not meet the criteria to be classified as any other outage

pursuant to the provisions of this Services Tariff or of ISO Procedures. A Generator in Inactive Reserves is ineligible to participate in the Installed Capacity market.

Inadvertent Energy Accounting: The accounting performed to track and reconcile the difference between net actual Energy interchange and scheduled Energy interchange of a Control Area with adjacent Control Areas.

In-City: Located electrically within the New York City Locality (LBMP Load Zone J).

Incremental Average Coincident Load (“Incremental ACL”): Beginning with the Summer 2014 Capability Period, the amount of qualifying Load that may be added to the Average Coincident Load of a Special Case Resource. In order to qualify to use Incremental ACL the SCR must enroll with an ACL and report an increase in the Load of the facility that is supplied by the NYS Transmission System and/or distribution system that meets or exceeds the SCR Load Change Reporting Threshold in accordance with this Services Tariff. The Incremental ACL reported in a Capability Period cannot exceed one-hundred percent (100%) of the ACL that has been calculated for the SCR when it first enrolls in the Capability Period. For resources reporting an Incremental ACL, the Net Average Coincident Load shall equal the enrolled ACL plus the reported Incremental ACL less any applicable SCR Change of Status. Each resource for which a RIP reports an Incremental ACL is subject to verification subsequent to the Capability Period pursuant to reporting requirements and calculations using the SCR’s metered Load values provided in Section 5.12.11.1.5 of this Services Tariff and ISO Procedures.

Incremental Energy Bid: A series of monotonically increasing constant cost incremental Energy steps that indicate the quantities of Energy for a given price that an entity is willing to supply to the ISO Administered Markets.

Incremental TCC: A set of point-to-point Transmission Congestion Contract(s) that is awarded pursuant to Section 19.2.2 of Attachment M to the ISO OATT.

Independent System Operator (“ISO”): The New York Independent System Operator, Inc., a not-for-profit corporation established pursuant to the ISO Agreement.

Independent System Operator Agreement (“ISO Agreement”): The agreement that establishes the New York ISO.

Independent System Operator/New York State Reliability Council (“ISO/NYSRC Agreement”): The agreement between the ISO and the New York State Reliability Council governing the relationship between the two organizations.

Independent System Operator-Transmission Owner Agreement (“ISO/TO Agreement”): The agreement that establishes the terms and conditions under which the Transmission Owners transferred to the ISO Operational Control over designated transmission facilities.

Indicative NCZ Locational Minimum Installed Capacity Requirement: The amount of capacity that must be electrically located within a New Capacity Zone, or possess an approved Unforced Capacity Deliverability Right, in order to ensure that sufficient Energy and Capacity are available in that NCZ and that appropriate reliability criteria are met.

Installed Capacity (“ICAP”): External or Internal Capacity, in increments of 100 kW, that is made-available pursuant to Tariff requirements and ISO Procedures.

Installed Capacity Equivalent: The Resource capability that corresponds to its Unforced Capacity, calculated in accordance with ISO Procedures.

Installed Capacity Marketer: An entity which has signed this Tariff and which purchases Unforced Capacity from qualified Installed Capacity Suppliers, or from LSEs with excess Unforced Capacity, either bilaterally or through an ISO-administered auction. Installed Capacity Marketers that purchase Unforced Capacity through an ISO-administered auction may only resell Unforced Capacity purchased in such auctions in the NYCA.

Installed Capacity Supplier: An Energy Limited Resource, Generator, Installed Capacity Marketer, Responsible Interface Party, Intermittent Power Resource, Limited Control Run of River Hydro Resource, municipally-owned generation, System Resource or Control Area System Resource that satisfies the ISO’s qualification requirements for supplying Unforced Capacity to the NYCA.

Interconnection or Interconnection Points (“IP”): The point(s) at which the NYCA connects with a distribution system or adjacent Control Area. The IP may be a single tie line or several tie lines that are operated in parallel.

Interface: A defined set of transmission facilities that separate Load Zones and that separate the NYCA from adjacent Control Areas.

Interface MW - Mile Methodology: The procedure used to allocate Original Residual TCCs determined prior to the first Centralized TCC Auction to Transmission Owners.

Intermittent Power Resource: A device for the production of electricity that is characterized by an energy source that: (1) is renewable; (2) cannot be stored by the facility owner or operator; and (3) has variability that is beyond the control of the facility owner or operator. In New York, resources that depend upon wind, solar energy or landfill gas for their fuel have been classified as Intermittent Power Resources. Each Intermittent Power Resource that depends on wind as its fuel shall include all turbines metered at a single scheduling point identifier (PTID).

Internal: An entity (e.g., Supplier, Transmission Customer) or facility (e.g., Generator, Interface) located within the Control Area being referenced. Where a specific Control Area is not referenced, internal means the NYCA.

Internal Transactions: Purchases, sales or exchanges of Energy, Capacity or Ancillary Services where the Generator and Load are located within the NYCA.

Investment Grade Customer: A Customer that meets the criteria set forth in Section 26.3 of Attachment K to this Services Tariff.

Investor-Owned Transmission Owners: At the present time these include: Central Hudson Gas & Electric Corporation, Consolidated Edison Company of New York, Inc., New York State

Electric & Gas Corporation, Niagara Mohawk Power Corporation, Orange and Rockland Utilities, Inc., and Rochester Gas and Electric Corporation.

ISO Administered Markets : The Day-Ahead Market and the Real-Time Market (collectively the "LBMP Markets") and any other market or auction administered by the ISO.

ISO-Committed Fixed: In the Day-Ahead Market, a bidding mode in which a Generator requests that the ISO commit and schedule it. In the Real-Time Market, a bidding mode in which a Generator, with ISO approval, requests that the ISO schedule it no more frequently than every 15 minutes. A Generator scheduled in the Day-Ahead Market as ISO-Committed Fixed will participate as a Self-Committed Fixed Generator in the Real-Time Market unless it changes bidding mode, with ISO approval, to participate as an ISO-Committed Fixed Generator.

ISO-Committed Flexible: A bidding mode in which a Dispatchable Generator or Demand Side Resource follows Base Point Signals and is committed by the ISO.

ISO Market Power Monitoring Program: The monitoring program approved by the Commission and administered by the ISO and the Market Monitoring Unit that is designed to monitor the possible exercise of market power in ISO Administered Markets.

ISO OATT: The ISO Open Access Transmission Tariff.

ISO Procedures: The procedures adopted by the ISO in order to fulfill its responsibilities under the ISO OATT, the ISO Services Tariff and the ISO Related Agreements.

ISO Related Agreements: Collectively, the ISO Agreement, the ISO/TO Agreement, the NYSRC Agreement, and the ISO/NYSRC Agreement.

ISO Services Tariff (the "Tariff"): The ISO Market Administration and Control Area Services Tariff.

ISO Tariffs: The ISO OATT and the ISO Services Tariff, collectively.

2.10 Definitions - J

2.11 Definitions - K

2.12 Definitions - L

LBMP Market(s): The Real-Time Market or the Day-Ahead Market or both.

Limited Control Run-of-River Hydro Resource: A Generator above 1 MW in size that has demonstrated to the satisfaction of the ISO that its Energy production depends directly on river flows over which it has limited control and that such dependence precludes accurate prediction of the facility's real-time output.

Limited Customer: An entity that is not a Customer but which qualifies to participate in the ISO's Emergency Demand Response Program by complying with Limited Customer requirements set forth in the ISO Procedures.

Limited Energy Storage Resource ("LESR"): A Generator authorized to offer Regulation Service only and characterized by limited Energy storage, that is, the inability to sustain continuous operation at maximum Energy withdrawal or maximum Energy injection for a minimum period of one hour. LESRs must bid as ISO-Committed Flexible Resources.

Limited Energy Storage Resource ("LESR") Energy Management: Real-time Energy injections or withdrawals scheduled by the ISO to manage the Energy storage capacity of a Limited Energy Storage Resource, pursuant to ISO Procedures, for the purpose of maximizing the Capacity bid as available for Regulation Service from such Resource.

Linden VFT Scheduled Line: A transmission facility that interconnects the NYCA to the PJM Interconnection, L.L.C. Control Area in Linden, New Jersey.

LIPA Tax Exempt Bonds: Obligations issued by the Long Island Power Authority, the interest on which is not included in gross income under the Internal Revenue Code.

Load : A term that refers to either a consumer of Energy or the amount of demand (MW) or Energy (MWh) consumed by certain consumers.

Load Serving Entity ("LSE"): Any entity, including a municipal electric system and an electric cooperative, authorized or required by law, regulatory authorization or requirement, agreement, or contractual obligation to supply Energy, Capacity and/or Ancillary Services to retail customers located within the NYCA, including an entity that takes service directly from the ISO to supply its own Load in the NYCA.

Load Shedding: The systematic reduction of system demand by disconnecting Load in response to a Transmission System or area Capacity shortage, system instability, or voltage control considerations under the ISO OATT.

Load Zone: One (1) of eleven (11) geographical areas located within the NYCA that is bounded by one (1) or more of the fourteen (14) New York State Interfaces.

Local Furnishing Bonds: Tax-exempt bonds issued by a Transmission Owner under an agreement between the Transmission Owner and the New York State Energy Research and

Development Authority (“NYSERDA”), or its successor, or by a Transmission Owner itself, and pursuant to Section 142(f) of the Internal Revenue Code, 26 U.S.C. § 142(f).

Local Generator: A resource operated by or on behalf of a Load that is either: (i) not synchronized to a local distribution system; or (ii) synchronized to a local distribution system solely in order to support a Load that is equal to or in excess of the resource’s Capacity. Local Generators supply Energy only to the Load they are being operated to serve and do not supply Energy to the distribution system.

Locality: A single LBMP Load Zone or set of adjacent LBMP Load Zones within which a minimum level of Installed Capacity must be maintained, and as specifically identified in this subsection to mean (1) Load Zone J; (2) Load Zone K; and (3) Load Zones G, H, I, and J collectively (*i.e.*, the G-J Locality).

Locality Exchange Factor: Except the G-J Locality to ISO-NE for June 2017 through May 2018, the percentage of Locational Export Capacity that the ISO determines annually in accordance with Section 5.11.4.1 of the Services Tariff. For the G-J Locality to ISO-NE for June 2017 through May 2018, eighty percent (80%).

Locality Exchange MW: The MW of Locational Export Capacity excluding the MW to be transmitted using UDRs, that the ISO determines in accordance with Section 5.11.4.1 of the Services Tariff.

Local Reliability Rule: A Reliability Rule established by a Transmission Owner, and adopted by the NYSRC, to meet specific reliability concerns in limited areas of the NYCA, including without limitation, special conditions and requirements applicable to nuclear plants and special requirements applicable to the New York City metropolitan area.

Locational Based Marginal Pricing (“LBMP”): The price of Energy at each location in the NYS Transmission System as calculated pursuant to Section 17 Attachment B of this Services Tariff.

Locational Export Capacity: The MW of a Generator electrically located in an Import Constrained Locality that (a) has Capacity Resource Interconnection Service, pursuant to the applicable provisions of Attachment X, Attachment S and Attachment Z to the ISO OATT, and (b) that meets the eligibility requirements set forth in Section 5.9.2.2 of the Services Tariff.

Locational Minimum Installed Capacity Requirement: The portion of the NYCA Minimum Installed Capacity Requirement provided by Capacity Resources that must be electrically located within a Locality (including those combined with a Unforced Capacity Deliverability Right except for rights returned in an annual election to the ISO in accordance with ISO Procedures) in order to ensure that sufficient Energy and Capacity are available in that Locality and that appropriate reliability criteria are met.

Locational Minimum Unforced Capacity Requirement: The Unforced Capacity equivalent of the Locational Minimum Installed Capacity Requirement.

Long Island (“L.I.”): An electrical area comprised of Load Zone K, as identified in the ISO Procedures.

Lost Opportunity Cost: The foregone profit associated with the provision of Ancillary Services, which is equal to the product of: (1) the difference between (a) the Energy that a Generator could have sold at the specific LBMP and (b) the Energy sold as a result of reducing the Generator’s output to provide an Ancillary Service under the directions of the ISO; and (2) the LBMP existing at the time the Generator was instructed to provide the Ancillary Service, less the Generator’s Energy bid for the same MW segment.

LSE Unforced Capacity Obligation: The amount of Unforced Capacity that each NYCA LSE must obtain for an Obligation Procurement Period as determined by the ICAP Demand Curve for the NYCA, the G-J Locality, New York City Locality, and/or the Long Island Locality, as applicable, for each ICAP Spot Market Auction. The amount includes, at a minimum, each LSE’s share of the NYCA Minimum Unforced Capacity Requirement and the Locational Minimum Unforced Capacity Requirement, as applicable.

2.13 Definitions - M

Major Emergency State: An Emergency accompanied by abnormal frequency, abnormal voltage and/or equipment overloads that create a serious risk that the reliability of the NYS Power System could be adversely affected.

Marginal Losses: The NYS Transmission System Real Power Losses associated with each additional MWh of consumption by Load, or each additional MWh transmitted under a Bilateral Transaction as measured at the Points of Withdrawal.

Marginal Losses Component: The component of LBMP at a bus that accounts for the Marginal Losses, as measured between that bus and the Reference Bus.

Market-Clearing Price: The price determined in an Installed Capacity auction for each ISO-defined Locality, the remainder of the NYCA and each adjacent External Control Area for which all offers to sell and bids to purchase Unforced Capacity are in equilibrium.

Market Mitigation and Analysis Department: A department, internal to the ISO, that is responsible for participating in the ISO's administration of its Tariffs. The Market Mitigation and Analysis Department's duties are described in Section 30.3 of the Market Monitoring Plan that is set forth in Attachment O to this Services Tariff.

Market Monitoring Unit: "Market Monitoring Unit" shall have the same meaning in this ISO Services Tariff as it has in the Market Monitoring Plan that is set forth in Attachment O to this Services Tariff.

Market Participant: An entity, excluding the ISO, that produces, transmits, sells, and/or purchase for resale Unforced Capacity, Energy or Ancillary Services in the Wholesale Market. Market Participants include: Transmission Customers under the ISO OATT, Customers under the ISO Services Tariff, Power Exchanges, Transmission Owners, Primary Holders, LSEs, Suppliers and their designated agents. Market Participants also include entities buying or selling TCCs.

Market Problem: An issue which requires notification to Market Participants, the Commission and the Market Monitoring Unit pursuant to Section 3.5.1 of this Services Tariff. It includes market design flaws, software implementation and modeling anomalies or errors, market data anomalies or errors, and economic inefficiencies that have a material effect on the ISO-administered markets or transmission service. The term does not include erroneous Energy or Ancillary Services prices (which are managed through procedures outlined in Attachment E to the Services Tariff) or erroneous customer settlements.

Market Services: Services provided by the ISO under the ISO Services Tariff related to the ISO Administered Markets for Energy, Capacity and Ancillary Services.

[MCZ Import Constrained Locality: A Mitigated Capacity Zone that is also an Import Constrained Locality.](#)

Member Systems: The eight Transmission Owners that comprise the membership of the New York Power Pool.

Minimum Generation Bid: A two-parameter Bid that identifies the minimum operating level a Supplier requires to operate a Generator, and the payment a Supplier requires to operate its Generator at that level, or the minimum quantity of Demand Reduction a Demand Side Resource requires to provide Demand Reduction and the payment the Supplier requires to provide that level of Demand Reduction.

Minimum Generation Level: For purposes of describing the eligibility of ten minute Resources to be committed by the Real Time Dispatch for pricing purposes pursuant to the Services Tariff, Section 4.4.3.3, an upper bound, established by the ISO, on the physical minimum generation limits specified by ten minute Resources. Ten minute Resources with physical minimum generation limits that exceed this upper bound will not be committed by the Real Time Dispatch for pricing purposes. The ISO shall establish a Minimum Generation Level based on its evaluation of the extent to which it is meeting its reliability criteria including Control Performance. The Minimum Generation Level, in megawatts, and the ISO's rationale for that level, shall be made available through the ISO's website or comparable means.

Minimum Payment Nomination: An offer, submitted by a Responsible Interface Party, in dollars per Megawatt-hour and not to exceed \$500 per Megawatt-hour, to reduce Load equal to the Installed Capacity Equivalent of the amount of Unforced Capacity a Special Case Resource is supplying to the NYCA.

Mitigated Capacity Zone: New York City and any Locality added to the definition of "Locality" accepted by the Commission on or after March 31, 2013.

Modified Wheeling Agreement ("MWA"): A Transmission Wheeling Agreement between Transmission Owners that was in existence at the time of ISO start-up, as amended and modified as described in Attachment K. Modified Wheeling Agreements are associated with Generators or power supply contracts existing at ISO start-up. All Modified Wheeling Agreements are listed in Attachment L, Table 1A, and are designated in the "Treatment" column of Table 1A, as "MWA".

Monthly Auction: An auction administered by the ISO pursuant to Section 5.13.3 of the ISO Services Tariff.

Monthly Average Coincident Load ("Monthly ACL"): Beginning with the Summer 2014 Capability Period, the Load value calculated for each month during a Capability Period applicable to a Special Case Resource with a reported Incremental Average Coincident Load. The Monthly ACL is an average of the SCR's metered hourly Load that is supplied by the NYS Transmission System and/or the distribution system and reported for the Monthly SCR Load Zone Peak Hours applicable to such SCR. The calculation and verification data reporting requirements are provided in Section 5.12.11.1.5 of this Services Tariff and ISO Procedures. Any Load supported by generation produced from a Local Generator, other behind-the-meter generator, or other supply source located behind the meter operating during the Monthly SCR

Zone Load Peak Hours may not be included in the metered Load values reported for the Monthly ACL.

Monthly SCR Load Zone Peak Hours: Beginning with the Summer 2014 Capability Period, the top forty (40) coincident peak hours for each month within a Capability Period that include hour beginning eleven through hour beginning nineteen as identified by the ISO for each Load Zone; provided, however, that such hours shall not include (i) hours in which Special Case Resources located in the specific Load Zone were called by the ISO to respond to a reliability event or test, (ii) hours for which the Emergency Demand Response Program resources were deployed by the ISO in each specific Load Zone and (iii) in descending rank order of NYCA Load up to a maximum of eight hours per month, a) the hour before the start time of a reliability event or performance test, in which SCRs located in the specific Load Zone were called by the ISO to respond to a reliability event or performance test, or b) the hour immediately following the end time of such reliability event or performance test.

Mothball Outage: The outage state in which a Market Participant's Generator is voluntarily removed from service on or after May 1, 2015, with applicable prior notice, for reasons not related to equipment failure. A Generator in Mothball Outage is subject to the return-to-service provisions in Section 5.18.4 of this Services Tariff and is ineligible to participate in the Installed Capacity market.

2.14 Definitions - N

Native Load Customers: The wholesale and retail power customers of the Transmission Owners on whose behalf the Transmission Owners, by statute, franchise, regulatory requirement, or contract, have undertaken an obligation to construct and operate the Transmission Owners' systems to meet the reliable electric needs of such customers.

NCZ Locational Minimum Installed Capacity Requirement: The amount of Capacity that must be electrically located within an NCZ, or possess an approved Unforced Capacity Deliverability Right, designed to ensure that sufficient Energy and Capacity are available in that NCZ and that appropriate reliability criteria are met.

NCZ Study Capability Period: The Summer Capability Period that begins five years from May 1 in a calendar year including an NCZ Study Start Date.

NCZ Study Start Date: September 1 or the next business day thereafter in the calendar year prior to an ICAP Demand Curve Reset Filing Year.

Neptune Scheduled Line: A transmission facility that interconnects the NYCA to the PJM Interconnection LLC Control Area at Levittown, Town of Hempstead, New York and terminates in Sayerville, New Jersey.

NERC: The North American Electric Reliability Council or, as applicable, the North American Electric Reliability Corporation.

Net Auction Revenue: The total amount, in dollars, as calculated pursuant to Section Part 17.5.3.1 of Attachment B, remaining after collection of all charges and allocation of all payments associated with a round of a Centralized TCC Auction or a Reconfiguration Auction. Net Auction Revenue takes into account: (i) revenues from and payments for the award of TCCs in a Centralized TCC Auction or Reconfiguration Auction, (ii) payments to Transmission Owners releasing ETCNL, (iii) payments or charges to Primary Holders selling TCCs, (iv) payments to Transmission Owners releasing Original Residual TCCs, (v) O/R-t-S Auction Revenue Surplus Payments and U/D Auction Revenue Surplus Payments, and (vi) O/R-t-S Auction Revenue Shortfall Charges and U/D Auction Revenue Shortfall Charges. Net Auction Revenue may be positive or negative.

Net Average Coincident Load (“Net ACL”): The effective Average Coincident Load calculated and used by the ISO for a Special Case Resource during a specific month in which a SCR Change of Status was reported for the resource or, beginning with the Summer 2014 Capability Period, an Incremental Average Coincident Load was reported for the resource.

Net Congestion Rent: The total amount, in dollars, as calculated pursuant to Section 17.5.2.1 of Attachment B, remaining after collection of all Congestion-related charges and allocation of all Congestion-related payments associated with the Day-Ahead Market. Net Congestion Rent takes into account: (i) charges and payments for Congestion Rents, (ii) settlements with TCC Primary Holders, (iii) O/R-t-S Congestion Rent Shortfall Charges and U/D Congestion Rent Shortfall Charges, and (iv) O/R-t-S Congestion Rent Surplus Payments and U/D Congestion Rent Surplus Payments. Net Congestion Rent may be positive or negative.

Network Integration Transmission Service: The Transmission Service provided under Part 4 of the ISO OATT.

New Capacity Zone (“NCZ”): A single Load Zone or group of Load Zones that is proposed as a new Locality, and for which the ISO shall establish a Demand Curve.

New York City: The electrical area comprised of Load Zone J, as identified in the ISO Procedures.

New York Control Area (“NYCA”): The Control Area that is under the control of the ISO which includes transmission facilities listed in the ISO/TO Agreement Appendices A-1 and A-2, as amended from time-to-time, and generation located outside the NYS Power System that is subject to protocols (e.g., telemetry signal biasing) which allow the ISO and other Control Area operator(s) to treat some or all of that generation as though it were part of the NYS Power System.

New York Power Pool (“NYPP”): An organization established by agreement (the “New York Power Pool Agreement”) made as of July 21, 1966, and amended as of July 16, 1991, by and among Central Hudson Gas & Electric Corporation, Consolidated Edison Company of New York, Inc., Long Island Lighting Company, New York State Electric & Gas Corporation, Niagara Mohawk Power Corporation, Orange and Rockland Utilities, Inc., Rochester Gas and Electric Corporation, and the Power Authority of the State of New York. LIPA became a Member of the NYPP on May 28, 1998 as a result of the acquisition of the Long Island Lighting Company by the Long Island Power Authority.

New York State Bulk Power Transmission Facility: This term shall have the meaning given in Attachment Y to the OATT.

New York State Power System (“NYS Power System”): All facilities of the NYS Transmission System, and all those Generators located within the NYCA or outside the NYCA, some of which may from time-to-time be subject to operational control by the ISO.

New York State Reliability Council (“NYSRC”): An organization established by agreement among the Member Systems to promote and maintain the reliability of the NYS Power System.

New York State Reliability Council Agreement (“NYSRC Agreement”): The agreement which established the NYSRC.

New York State Transmission System (“NYS Transmission System”): The entire New York State electric transmission system, which includes: (1) the Transmission Facilities Under ISO Operational Control; (2) the Transmission Facilities Requiring ISO Notification; and (3) all remaining transmission facilities within the NYCA.

Non-Competitive Proxy Generator Bus: A Proxy Generator Bus for an area outside of the New York Control Area that has been identified by the ISO as characterized by non-competitive Import or Export prices, and that has been approved by the Commission for designation as a Non-Competitive Proxy Generator Bus. Non-Competitive Proxy Generator Buses are identified in Section 4.4.4 of the Services Tariff., as set forth in Section 4.4.2.2 of the MST

Non-Firm-Point-To-Point Transmission Service: Point-To-Point Transmission Service for which a Transmission Customer is not willing to pay Congestion. Such service is not available in the markets that the NYISO administers.

Non-Investment Grade Customer: A Customer that does not meet the criteria necessary to be an Investment Grade Customer, as set forth in Section 26.3 of Attachment K to this Services Tariff.

Non-Utility Generator ("NUG," "Independent Power Producer" or "IPP"): Any entity that owns or operates an electric generating facility that is not included in an electric utility's rate base. This term includes, but is not limited to, cogenerators and small power producers and all other non-utility electricity producers, such as exempt wholesale Generators that sell electricity.

Normal State: The condition that the NYS Power System is in when the Transmission Facilities Under ISO Operational Control are operated within the parameters listed for Normal State in the Reliability Rules. These parameters include, but are not limited to, thermal, voltage, stability, frequency, operating reserve and Pool Control Error limitations.

Normal Upper Operating Limit (UOL_N): The upper operating limit that a Generator indicates it expects to be able to reach, or the maximum amount of demand that a Demand Side Resource expects to be able to reduce, during normal conditions. Each Resource will specify its UOL_N in its Bids which shall be reduced when the Resource requests that the ISO derate its Capacity or the ISO derates the Resource's Capacity. A Normal Upper Operating Limit may be submitted as a function depending on one or more variables, such as temperature or pondage levels, in which case the Normal Upper Operating Limit applicable at any time shall be determined by reference to that schedule.

Northport-Norwalk Scheduled Line: A transmission facility that originates at the Northport substation in New York and interconnects the NYCA to the ISO New England Control Area at the Norwalk Harbor substation in Connecticut.

Notice of Intent to Return: The notice a Supplier with a Generator that is in a Mothball Outage or ICAP Ineligible Forced Outage provides to the ISO, pursuant to ISO Procedures, that gives the date by which it intends to return to the Energy market, which proposed return date shall be no later than the expiration date of the Generator's Mothball Outage or ICAP Ineligible Forced Outage.

NPCC: The Northeast Power Coordinating Council.

NRC: The Nuclear Regulatory Commission or any successor thereto.

NYCA Installed Reserve Margin: The ratio of the amount of additional Installed Capacity required by the NYSRC in order for the NYCA to meet NPCC reliability criteria to the forecasted NYCA upcoming Capability Year peak Load, expressed as a decimal.

NYCA Minimum Installed Capacity Requirement: The requirement established for each Capability Year by multiplying the NYCA peak Load forecasted by the ISO by the quantity one plus the NYCA Installed Reserve Margin.

NYCA Minimum Unforced Capacity Requirement: The Unforced Capacity equivalent of the NYCA Minimum Installed Capacity Requirement.

NYPA: The Power Authority of the State of New York.

NYPA Tax-Exempt Bonds: Obligations of the New York Power Authority, the interest on which is not included in gross income under the Internal Revenue Code.

2.15 Definitions - O

Obligation Procurement Period: The period of time for which LSEs shall be required to satisfy their Unforced Capacity requirements. Starting with the 2001-2002 Winter Capability Period, Obligation Procurement Periods shall be one calendar month in duration and shall begin on the first day of each calendar month.

Off-Peak: The hours between 11 p.m. and 7 a.m., prevailing Eastern Time, Monday through Friday, and all day Saturday and Sunday, and NERC-defined holidays, or as otherwise decided by the ISO.

Offeror: An entity that offers to sell Unforced Capacity in an auction.

On-Peak: The hours between 7 a.m. and 11 p.m. inclusive, prevailing Eastern Time, Monday through Friday, except for NERC-defined holidays, or as otherwise decided by the ISO.

Open Access Same-Time Information System ("OASIS"): The information system and standards of conduct contained in Part 37 of the Commission's regulations and all additional requirements implemented by subsequent Commission orders dealing with OASIS.

Operating Capacity: Capacity that is readily converted to Energy and is measured in MW.

Operating Committee: A standing committee of the ISO created pursuant to the ISO Agreement, which coordinates operations, develops procedures, evaluates proposed system expansions and acts as a liaison to the NYSRC.

Operating Data: Pursuant to Section 5.12.5 of this Tariff, Operating Data shall mean GADS Data, data equivalent to GADS Data, CARL Data, metered Load data, or actual system failure occurrences data, all as described in the ISO Procedures.

Operating Requirement: The amount calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

Operating Reserves : Capacity that is available to supply Energy or reduce demand and that meets the requirements of the ISO. The ISO will administer Operating Reserves markets, in the manner described in this Article 4 and Rate Schedule 4 of this ISO Services Tariff, to satisfy the various Operating Reserves requirements, including locational requirements, established by the Reliability Rules and other applicable reliability standards. The basic Operating Reserves products that will be procured by the ISO on behalf of the market are classified as follows:

- (1) Spinning Reserve: Operating Reserves provided by Generators and Demand Side Resources that meet the eligibility criteria set forth in Rate Schedule 4 of this ISO Services Tariff that are already synchronized to the NYS Power System and can respond to instructions to change their output level, or reduce their Energy usage, within ten (10) minutes. Spinning Reserves may not be provided by Demand Side Resources that are Local Generators;

(2) 10-Minute Non-Synchronized Reserve: Operating Reserves provided by Generators, or Demand Side Resources, including Demand Side Resources using Local Generators, that meet the eligibility criteria set forth in Rate Schedule 4 of this ISO Services Tariff and that can be started, synchronized and can change their output level within ten (10) minutes; and

(3) 30-Minute Reserve: Synchronized Operating Reserves provided by Generators and Demand Side Resources that are not Local Generators; or non-synchronized Operating Reserves provided by Generators or Demand Side Resources that meet the eligibility criteria set forth in Rate Schedule 4 of this ISO Services Tariff and that can respond to instructions to change their output level within thirty (30) minutes, including starting and synchronizing to the NYS Power System.

Operating Reserve Demand Curve: A series of quantity/price points that defines the maximum Shadow Price for Operating Reserves meeting a particular Operating Reserve requirement corresponding to each possible quantity of Resources that the ISO's software may schedule to meet that requirement. A single Operating Reserve Demand Curve will apply to both the Day-Ahead Market and the Real-Time Market for each of the ISO's twelve Operating Reserve requirements.

Operating Study Power Flow: A Power Flow analysis that is performed at least once before each Capability Period that is used to determine each Interface Transfer Capability for the Capability Period (See Attachment M to the ISO OATT).

Operational Control: Directing the operation of the Transmission Facilities Under ISO Operational Control to maintain these facilities in a reliable state, as defined by the Reliability Rules. The ISO shall approve operational decisions concerning these facilities, made by each Transmission Owner before the Transmission Owner implements those decisions. In accordance with ISO Procedures, the ISO shall direct each Transmission Owner to take certain actions to restore the system to the Normal State. Operational Control includes security monitoring, adjustment of generation and transmission resources, coordination and approval of changes in transmission status for maintenance, determination of changes in transmission status for reliability, coordination with other Control Areas, voltage reductions and Load Shedding, except that each Transmission Owner continues to physically operate and maintain its facilities.

Optimal Power Flow ("OPF"): The Power Flow analysis that is performed during the administration of the Centralized TCC Auction to determine the most efficient simultaneously feasible allocation of TCCs to Bidders (See Attachment M to the ISO OATT).

Order Nos. 888 et seq.: The Final Rule entitled Promoting Wholesale Competition Through Open Access Non-discriminatory Transmission Services by Public Utilities; Recovery of Stranded Costs by Public Utilities and Transmitting Utilities, issued by the Commission on April 24, 1996, in Docket Nos. RM95-8-000 and RM94-7-001, as modified on rehearing, or upon appeal. (See FERC Stats. & Regs. [Regs. Preambles January 1991 - June 1996] ¶ 31,036 (1996) ("Order No. 888"), on reh'g, III FERC Stats. & Regs. ¶ 31,048 (1997) ("Order No. 888-A"), on reh'g, 81 FERC ¶ 61,248 (1997) ("Order No. 888-B"), order on reh'g, 82 FERC ¶ 61,046 (1998) ("Order No. 888-C").

Order Nos. 889 et seq.: The Final Rule entitled Open Access Same-Time Information System (formerly Real- Time Information Networks) and Standards of Conduct, issued by the Commission on April 24, 1996, in Docket No. RM95-9-000, as modified on rehearing, or upon appeal. (See FERC Stats. & Regs. [Regs. Preambles 1991-1996] ¶ 31,035 (1996) (“Order No. 889”), on reh’g, III FERC Stats. & Regs. ¶ 31,049 (1997) (“Order No. 889-A”), on reh’g, 81 FERC ¶ 61,253 (1997) (“Order No. 889-B”).

Original Residual TCC: A TCC converted from Residual Transmission Capacity estimated prior to the first Centralized TCC Auction and allocated among the Transmission Owners utilizing the Interface MW-Mile Methodology prior to the first Centralized TCC Auction.

Out-of-Merit: The designation of Resources committed and/or dispatched by the ISO at specified output limits for specified time periods to meet Load and/or reliability requirements that differ from or supplement the ISO’s security constrained economic commitment and/or dispatch.

2.16 Definitions - P

Performance Index: An index, described in ISO Procedures, that tracks a Generator's response to AGC signals from the ISO.

Performance Tracking System: A system designed to report metrics for Generators and Loads which include but are not limited to actual output and schedules. This system is used by the ISO to measure compliance with criteria associated with the provision of Energy and Ancillary Services.

Point-to-Point Transmission Service: The reservation and transmission of Capacity and Energy on a firm basis from the Point(s) of Receipt to the Point(s) of Delivery under the ISO Tariffs.

Point(s) of Delivery: Point(s) on the NYS Transmission System or Proxy Generator Buses where Energy transmitted by the ISO will be made available to the Transmission Customer under the OATT. The Point(s) of Delivery shall be specified pursuant to ISO Procedures.

Point(s) of Injection ("POI" or "Point of Receipt"): The point(s) on the NYS Transmission System or Proxy Generator Buses where Energy, Capacity and Ancillary Services will be made available to the ISO by the delivering party under the ISO OATT or the ISO Services Tariff. (May be referred to as "Point of Receipt" or similar in some Existing Transmission Agreements.)

Point(s) of Receipt: Point(s) of interconnection on the NYS Transmission System or Proxy Generator Buses where Energy will be made available to the ISO by the Transmission Customer under the OATT. The Point(s) of Receipt shall be specified pursuant to ISO Procedures.

Point(s) of Withdrawal ("POW" or "Point of Delivery"): The point(s) on the NYS Transmission System or Proxy Generator Buses where Energy, Capacity and Ancillary Services will be made available to the receiving party under the ISO OATT or the ISO Services Tariff. (May be referred to as "Point of Delivery" or similar in some Existing Transmission Agreements.)

Pool Control Error ("PCE"): The difference between the actual and scheduled interchange with other Control Areas, adjusted for frequency bias.

Post Contingency: Conditions existing on a system immediately following a Contingency.

Power Exchange ("PE"): A commercial entity meeting the requirements for service under the ISO OATT or the ISO Services Tariff that facilitates the purchase and/or sale of Energy, Unforced Capacity and/or Ancillary Services in a New York Wholesale Market. A PE may transact with the ISO on its own behalf or as an agent for others.

Power Factor: The ratio of real power to apparent power (the product of volts and amperes, expressed in megavolt-amperes, MVA).

Power Factor Criteria: Criteria to be established by the ISO to monitor a Load's use of Reactive Power.

Power Flow: A simulation which determines the Energy flows on the NYS Transmission System and adjacent transmission systems.

Price Adjustment: For each month in the Prior Equivalent Capability Period, the Price Adjustment equals the quotient of dividing (a) the Henry Hub futures gas price for the like month in the succeeding same-season Capability Period by (b) the average Henry Hub spot gas price for that month in the Prior Equivalent Capability Period.

Primary Holder: A Primary Holder of each TCC is the Primary Owner of that TCC or the party that purchased that TCC at the close of the Centralized TCC Auction. With respect to each TCC, a Primary Holder must be: (1) a Transmission Customer that has purchased the TCC in the Centralized TCC Auction, and that has not resold it in that same Auction; (2) a Transmission Customer that has purchased the TCC in a Direct Sale with another Transmission Customer; (3) the Primary Owner who has retained the TCC; or (4) Primary Owners of the TCC that allocated the TCC to certain customers or sold it in the Secondary Market or sold through a Direct Sale to an entity other than a Transmission Customer. The ISO settles Day-Ahead Congestion Rents pursuant to Attachments M and N to the ISO OATT with the Primary Holder of each TCC.

Primary Owner: The Primary Owner of each TCC is the Transmission Owner or other Transmission Customer that has acquired the TCC through conversion of rights under an Existing Transmission Agreement to Grandfathered TCCs (in accordance with Attachment K of the ISO OATT), or through the conversion of Existing Transmission Agreements upon their expiration (in accordance with Attachment B), or the Transmission Owner that acquired the TCC through the ISO's allocation of Original Residual TCCs or through the conversion of ETCNL or an RCRR.

Prior Equivalent Capability Period: The previous same-season Capability Period.

Provisional Average Coincident Load ("Provisional ACL"): Prior to the Summer 2014 Capability Period, the value that may be used in lieu of Average Coincident Load for an eligible Special Case Resource for a maximum duration no greater than three consecutive Capability Periods and only where the SCR (i) has not previously been enrolled with the ISO and (ii) never had interval metering Load data available from the Prior Equivalent Capability Period. Beginning with the Summer 2014 Capability Period, the value that may be used in lieu of ACL for an eligible SCR as provided in Section 5.12.11.1.2 of this Services Tariff. A SCR's Provisional ACL is verified subsequent to each eligible Capability Period pursuant to calculations using the SCR's metered Load values in accordance with Sections 5.12.11.1.1 and 5.12.11.1.2 of this Services Tariff and ISO Procedures. Any Load supported by generation produced from a Local Generator, other behind-the-meter generator, or other supply source located behind the SCR's meter operating during the applicable Capability Period SCR Load Zone Peak Hours may not be included in the SCR's metered Load values reported for the verification of its Provisional ACL.

Proxy Generator Bus: A proxy bus located outside the NYCA that is selected by the ISO to represent a typical bus in an adjacent Control Area and at which LBMP prices are calculated. The ISO may establish more than one Proxy Generator Bus at a particular Interface with a

neighboring Control Area to enable the NYISO to distinguish the bidding, treatment and pricing of products and services at the Interface.

PSC: The Public Service Commission of the State of New York or any successor agency thereto.

PSL: The New York Public Service Law, Public Service Law § 1 et seq. (McKinney 1989 & Supp. 1997-98).

Public Power Entity: An entity which is either (i) a public authority or corporate municipal instrumentality, including a subsidiary thereof, created by the State of New York that owns or operates generation or transmission and that is authorized to produce, transmit or distribute electricity for the benefit of the public, or (ii) a municipally owned electric system that owns or controls distribution facilities and provides electric service, or (iii) a cooperatively owned electric system that owns or controls distribution facilities and provides electric service.

2.17 Definitions - Q

Qualified Change of Load Condition: A Special Case Resource enrolled with an Average Coincident Load, Provisional Average Coincident Load, or Net Average Coincident Load, in accordance with this Services Tariff, meets a Qualified Change of Load Condition when: (i) the SCR is expected to have a reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that is expected to continue for a total period that is greater than seven (7) consecutive days, (ii) the SCR is experiencing a reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that is expected to continue for a total period that is greater than seven (7) consecutive days, or (iii) the SCR experienced an unanticipated reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold for a period greater than seven (7) consecutive days within any month in which the SCR sold capacity or adjoining months in which the SCR sold capacity in either month.

Qualified Change of Status Condition: A Special Case Resource enrolled with an Average Coincident Load, Provisional Average Coincident Load, or Net Average Coincident Load, in accordance with this Services Tariff meets a Qualified Change of Status Condition when: (i) the SCR is expected to have a reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that will extend for a period of greater than sixty (60) consecutive days, (ii) the SCR is experiencing a reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that is expected to continue for a total period that is greater than sixty (60) consecutive days, or (iii) the SCR has experienced an unanticipated reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that has existed for a period greater than sixty (60) consecutive days in which the SCR sold capacity.

Qualified Non-Generator Voltage Support Resource: A resource that is neither a Generator nor a synchronous condenser but that is capable of providing the ISO with Reactive Power on a dynamic basis, that is energized and under the operational control of the ISO, or a Transmission Owner, that meets the resource-specific technical and testing criteria specified in the ISO Procedures, and that is ineligible to receive Reactive Power compensation other than as a Qualified Non-Generator Voltage Support Resource. The Cross-Sound Scheduled Line shall be a Qualified Non-Generator Voltage Support Resource, provided that it meets the technical and testing criteria in the ISO Procedures.

Quick Start Mode: The setting of a block of generator units capable of remote start-up by a Transmission Owner so that it can synchronize and reach full output within fifteen (15) minutes.

Quick Start Reserves: Capacity of a block of generator units that is set to Quick Start Mode by request of a Transmission Owner.

2.18 Definitions - R

Ramp Capacity: The amount of change in the Desired Net Interchange that generation located in the NYCA can support at any given time. Ramp capacity may be calculated for all Interfaces between the NYCA and neighboring Control Areas as a whole or for any individual Interface between the NYCA and an adjoining Control Area.

RCRR TCC:: A zone-to-zone TCC created when a Transmission Owner with a RCRR exercises its right to convert the RCRR into a TCC pursuant to Section 19.5.4 of Attachment M of the ISO OATT.

Reactive Power (MVar): The product of voltage and the out-of-phase component of alternating current. Reactive Power, usually measured in MVar, is produced by capacitors (synchronous condensers), Qualified Non-Generator Voltage Support Resources, and over-excited Generators and absorbed by reactors or under-excited Generators and other inductive devices including the inductive portion of Loads.

Real Power Losses: The loss of Energy, resulting from transporting power over the NYS Transmission System, between the Point of Injection and Point of Withdrawal of that Energy.

Real-Time Bid: A Bid submitted into the Real-Time Commitment before the close of the Real-Time Scheduling Window. A Real-Time Bid shall also include a CTS Interface Bid.

Real-Time Commitment (“RTC”): A multi-period security constrained unit commitment and dispatch model that co-optimizes to solve simultaneously for Load, Operating Reserves and Regulation Service on a least as-bid production cost basis over a two hour and fifteen minute optimization period. The optimization evaluates the next ten points in time separated by fifteen minute intervals. Each RTC run within an hour shall have a designation indicating the time at which its results are posted; “RTC₀₀,” “RTC₁₅,” “RTC₃₀,” and “RTC₄₅” post on the hour, and at fifteen, thirty, and forty-five minutes after the hour, respectively. Each RTC run will produce binding commitment instructions for the periods beginning fifteen and thirty minutes after its scheduled posting time and will produce advisory commitment guidance for the remainder of the optimization period. RTC₁₅ will also establish hourly External Transaction schedules, while all RTC runs may establish 15 minute External Transaction schedules at Variably Scheduled Proxy Generator Buses. Additional information about RTC’s functions is provided in Section 4.4.2 of this ISO Services Tariff.

Real-Time Dispatch (“RTD”): A multi-period security constrained dispatch model that co-optimizes to solve simultaneously for Load, Operating Reserves, and Regulation Service on a least-as-bid production cost basis over a fifty, fifty-five or sixty-minute period (depending on when each RTD run occurs within an hour). The Real-Time Dispatch dispatches, but does not commit, Resources, except that RTD may commit, for pricing purposes, Resources meeting Minimum Generation Levels and capable of starting in ten minutes. RTD may also establish 5 minute External Transaction schedules at Dynamically Scheduled Proxy Generator Buses. Real-Time Dispatch runs will normally occur every five minutes. Additional information about RTD’s functions is provided in Section 4.4.3 of this ISO Services Tariff. Throughout this ISO

Services Tariff the term “RTD” will normally be used to refer to both the Real-Time Dispatch and to the specialized Real-Time Dispatch Corrective Action Mode software.

Real-Time Dispatch–Corrective Action Mode (“RTD-CAM”): A specialized version of the Real-Time Dispatch software that will be activated when it is needed to address unanticipated system conditions. RTD-CAM is described in Section 4.4.4 of this ISO Services Tariff.

Real-Time LBMP: The LBMPs established through the ISO Administered Real-Time Market.

Real-Time Market: The ISO Administered Markets for Energy and Ancillary Services resulting from the operation of the RTC and RTD.

Real-Time Minimum Run Qualified Gas Turbine: One or more gas turbines, offered in the Real-Time Market, which, because of their physical operating characteristics, may qualify for a minimum run time of two hours in the Real-Time Market. Characteristics that qualify gas turbines for this treatment are established by ISO Procedures and include using waste heat from the gas turbine-generated electricity to make steam for the generation of additional electricity via a steam turbine.

Real-Time Scheduled Energy: The quantity of Energy that a Supplier is directed to inject or withdraw in real-time by the ISO. Injections are indicated by positive Base Point Signals and withdrawals are indicated by negative Base Point Signals. Unless otherwise directed by the ISO, Dispatchable Supplier’s Real-Time Scheduled Energy is equal to its RTD Base Point Signal, or, if it is providing Regulation Service, to its AGC Base Point Signal, and an ISO Committed Fixed or Self-Committed Fixed Supplier’s Real-Time Scheduled Energy is equal to its bid output level in real-time.

Real-Time Scheduling Window: The period of time within which the ISO accepts offers and bids to sell and purchase Energy and Ancillary Services in the Real-Time Market for a given hour which period closes seventy-five (75) minutes before the start of that hour, or eighty-five (85) minutes before the start of that hour for Bids to schedule External Transactions at the Proxy Generator Buses associated with the Cross-Sound Scheduled Line, the Neptune Scheduled Line, the Linden VFT Scheduled Line, or the HTP Scheduled Line.

Reconfiguration Auction: The monthly auction administered by the ISO in which Market Participants may purchase and sell one-month TCCs.

Reference Bus: The location on the NYS Transmission System relative to which all mathematical quantities, including Shift Factors and penalty factors relating to physical operation, will be calculated. The NYPA Marcy 345 kV transmission substation is designated as the Reference Bus.

Regulation Capacity: The Energy or Demand Reduction capability, measured in MW, that a Regulation Service provider offers and/or which it is scheduled to provide for Regulation Service.

Regulation Capacity Market Price: The price for Regulation Capacity determined by the ISO pursuant to section 15.3 of this Services Tariff.

Regulation Capacity Response Rate: The Regulation Capacity a Resource is capable of providing over five minutes, measured in MW/minute which shall not exceed the lowest normal energy response rate provided for the Resource and which must be sufficient to permit that Resource to provide the Regulation Capacity (in MW) offered within a five-minute RTD interval. Reference to a Regulation response rate shall be a reference to the Regulation Capacity Response Rate.

Regulation Movement: The absolute value of the change in Energy or Demand Reduction over a six second interval, measured in MW, that a Regulation Service provider is instructed to deliver for the purpose of providing Regulation Service.

Regulation Movement Market Price: The price for Regulation Movement as determined by the ISO pursuant to section 15.3 of this Services Tariff.

Regulation Movement Multiplier: A factor with the value of thirteen (13), used with the Regulation Movement Bids, to schedule Regulation Service providers in both the Day-Ahead and Real-Time Energy markets. The ISO calculates the Regulation Movement Multiplier based on the historical relationship between the number of MW of Regulation Capacity that the ISO seeks to maintain in each hour and the number of Regulation Movement MW instructed by AGC in each hour.

Regulation Movement Response Rate: The amount of Regulation Movement a Regulation Service provider is capable of delivering in six seconds which shall not be less than, but can be equal to or greater than, the Regulation Capacity Response Rate equivalent.

Regulation Service: The Ancillary Service defined by the Commission as “frequency regulation” and that is instructed as Regulation Capacity in the Day-Ahead Market and as Regulation Capacity and Regulation Movement in the Real-Time Market as is further described in Section 15.3 of the Services Tariff. Day-Ahead and Real-Time Bids to provide Regulation Service shall include a Bid for Regulation Capacity and a Bid for Regulation Movement. The Regulation Service requirement or target level shall be for MW of Regulation Capacity.

Regulation Service Demand Curve: A series of quantity/price points that defines the maximum Shadow Price for Regulation Service corresponding to each possible quantity of Resources that the ISO’s software may schedule to satisfy the ISO’s Regulation Service constraint. A single Regulation Service Demand Curve will apply to both the Day-Ahead Market and the Real-Time Market for Regulation Service. The Shadow Price for Regulation Service shall be used to calculate Regulation Service payments under Rate Schedule 3 of this ISO Services Tariff.

Regulation Revenue Adjustment Charge (“RRAC”): A charge that will be assessed against certain Generators that are providing Regulation Service under Section 15.3.6 of Rate Schedule 3 to this ISO Services Tariff.

Regulation Revenue Adjustment Payment (“RRAP”): A payment that will be made to certain Generators that are providing Regulation Service under Section 15.3.6 of Rate Schedule 3 to this ISO Services Tariff.

Reliability Rules: Those rules, standards, procedures and protocols developed and promulgated by the NYSRC, including Local Reliability Rules, in accordance with NERC, NPCC, FERC, PSC and NRC standards, rules and regulations and other criteria and pursuant to the NYSRC Agreement.

Repair Plan: A work plan, set of actions, and time frame for such actions, that is necessary to repair a Generator and return it to service as described in Section 5.18.1 of this Services Tariff.

Required System Capability: Generation capability required to meet an LSE's peak Load plus Installed Capacity Reserve obligation as defined in the Reliability Rules.

Reserve Performance Index: An index created by the ISO for the purpose of calculating the Day Ahead Margin Assurance Payment pursuant to Attachment J of this Services Tariff made to Demand Side Resources scheduled to provide Operating Reserves in the Day-Ahead Market.

Residual Adjustment: The adjustment made to ISO costs that are recovered through Schedule 1 of the OATT. The Residual Adjustment is calculated pursuant to Schedule 1 of the OATT.

Residual Capacity Reservation Right ("RCRR"): A megawatt of transmission Capacity from one Load Zone to an electrically contiguous Load Zone, each of which is internal to the NYCA, that may be converted into an RCRR TCC by a Transmission Owner allocated the RCRR pursuant to Section 19.5 of Attachment M of the ISO OATT.

Residual Transmission Capacity: The transmission capacity determined by the ISO before, during and after the Centralized TCC Auction which is conceptually equal to the following:

Residual Transmission Capacity = TTC - TRM - CBM - GTR - GTCC - ETCNL

The TCCs associated with Residual Transmission Capacity cannot be accurately determined until the Centralized TCC Auction is conducted.

TTC is the Total Transfer Capability that can only be determined after the Residual Transmission Capacity is known.

GTR is the transmission capacity associated with Grandfathered Rights.

GTCC is the transmission capacity associated with Grandfathered TCCs.

ETCNL is the transmission capacity associated with Existing Transmission Capacity for Native Load.

TRM is the Transmission Reliability Margin.

CBM is the Capacity Benefit Margin.

Resource: An Energy Limited Resource, Generator, Installed Capacity Marketer, Special Case Resource, Intermittent Power Resource, Limited Control Run of River Hydro Resource, municipally-owned generation, System Resource, Demand Side Resource or Control Area System Resource.

Responsible Interface Party (“RIP”): A Customer that is authorized by the ISO to be the Installed Capacity Supplier for one or more Special Case Resources and that agrees to certain notification and other requirements as set forth in this Services Tariff and in the ISO Procedures.

Rest of State: The set of all non-Locality NYCA LBMP Load Zones. As of the 2014/2015 Capability Year, Rest of State includes all NYCA LBMP Load Zones other than LBMP Load Zones G, H, I, J and K.

Retired: A Generator that has permanently ceased operating on or after May 1, 2015 either: i) pursuant to applicable notice; or ii) as a result of the expiration of its Mothball Outage or of its ICAP Ineligible Forced Outage.

Rolling RTC: The RTC run that is used to schedule a given 15-minute External Transaction. The Rolling RTC may be an RTC00, RTC15, RTC30 or RTC45 run.

2.19 Definitions - S

Safe Operations: Actions which avoid placing personnel and equipment in peril with regard to the safety of life and equipment damage.

Scarcity Reserve Demand Curve: A series of quantity/price points that defines the maximum Shadow Price for Operating Reserves to meet a Scarcity Reserve Requirement for which the pricing rules established in Section 15.4.6.1.1(b) of Rate Schedule 4 of this ISO Services Tariff apply corresponding to each possible quantity of Resources that the ISO's software may schedule to satisfy that requirement. A single Scarcity Reserve Demand Curve will apply to the Real-Time Market for each such Scarcity Reserve Requirement.

Scarcity Reserve Region: A Load Zone or group of Load Zones containing EDRP and/or SCRs that have been called by the ISO to address the same reliability need, as such reliability need is determined by the ISO.

Scarcity Reserve Requirement: A 30-Minute Reserve requirement established by the ISO for a Scarcity Reserve Region in accordance with Rate Schedule 4 of this ISO Services Tariff.

Scheduled Energy Injections: As defined in the ISO OATT.

Scheduled Energy Withdrawals: As defined in the ISO OATT.

Scheduled Line: A transmission facility or set of transmission facilities: (a) that provide a distinct scheduling path interconnecting the ISO with an adjacent control area, (b) over which Customers are permitted to schedule External Transactions, (c) for which the ISO separately posts TTC and ATC, and (d) for which there is the capability to maintain the Scheduled Line actual interchange at the DNI, or within the tolerances dictated by Good Utility Practice. Each Scheduled Line is associated with a distinct Proxy Generator Bus. Transmission facilities shall only become Scheduled Lines after the Commission accepts for filing revisions to the NYISO's tariffs that identify a specific set or group of transmission facilities as a Scheduled Line. The transmission facilities that are Scheduled Lines are identified in Section 4.4.4 of the Services Tariff.

SCR Aggregation: One or more Special Case Resources registered by the Responsible Interface Party at a single PTID, with the Load of each Special Case Resource electrically located within the same single Load Zone and the total of all Loads at the PTID greater than or equal to 0.1 MW.

SCR Change of Load: A decrease in the Load of the SCR that meets the criteria of a Qualified Change of Load Condition and the SCR Load Change Reporting Threshold in accordance with this Services Tariff and results in a total Load reduction, within the range of hours that corresponds with the Capability Period SCR Load Zone Peak Hours, and the total Load reduction persists for more than seven (7) and less than or equal to sixty (60) continuous days from the first date of the reduction of the Load.

SCR Change of Status: The decrease to be treated as an adjustment to the applicable Average Coincident Load of a Special Case Resource when the SCR meets the criteria of a Qualified

Change of Status Condition and the SCR Load Change Reporting Threshold in accordance with this Services Tariff and results in a total Load reduction, within the range of hours that corresponds with the Capability Period SCR Load Zone Peak Hours, and the total Load reduction persists for more than sixty (60) continuous days from the first date of the reduction of the Load.

SCR Load Change Reporting Threshold: For a Special Case Resource with an applicable ACL greater than or equal to 500 kW, a reduction or increase in total Load not attributable to fluctuations in Load due to weather as described in ISO Procedures, that is equal to or greater than (i) thirty (30) percent of the applicable ACL for any month within the Capability Period, or (ii) five (5) MW in the NYC Locality or ten(10) MW if in any other Load Zone; whichever is less. For SCRs that elect to enroll with an Incremental ACL and do not increase the eligible Installed Capacity associated with the SCR, the RIP may enroll the SCR with a lower percentage change to its total Load increase as specified in Section 5.12.11.1.5 of this Services Tariff.

SCUC: Security Constrained Unit Commitment, described in Section 4.2.4 of this ISO Services Tariff.

Secondary Holders: Entities that: (1) purchase TCCs in the Secondary Market; (2) purchase TCCs in a Direct Sale from a Transmission Owner and have not been certified as a Primary Holder by the ISO; or (3) receive an allocation of Native Load TCCs from a Transmission Owner (See Attachment M). A Transmission Customer purchasing TCCs in a Direct Sale may qualify as a Primary Holder with respect to those TCCs purchased in that Direct Sale.

Second Settlement: The process of: (1) identifying differences between Energy production, Energy consumption or NYS Transmission System usage scheduled in a First Settlement and actual production, consumption, or usage during the Dispatch Day; and (2) assigning financial responsibility for those differences to the appropriate Customers and Market Participants. Charges for Energy supplied (to replace generation deficiencies or unscheduled consumption), and payments for Energy consumed (to absorb consumption deficiencies or excess Energy supply) or changes in transmission usage will be based on the Real-Time LBMPs.

Secondary Market: A market in which Primary and Secondary Holders sell TCCs by mechanisms other than through the Centralized TCC Auction or by Direct Sale. Buyers of TCCs in the Secondary Market shall neither pay nor receive Congestion Rents directly to or from the ISO.

Security Coordinator: An entity that provides the security assessment and Emergency operations coordination for a group of Control Areas. A Security Coordinator must not participate in the wholesale or retail merchant functions.

Self-Committed Fixed: A bidding mode in which a Generator is self-committed and opts not to be Dispatchable over any portion of its operating range.

Self-Committed Flexible: A bidding mode in which a Dispatchable Generator follows Base Point Signals within a portion of its operating range, but self-commits.

Self-Supply: The provision of certain Ancillary Services, or the provision of Energy to replace Marginal Losses by a Transmission Customer using either the Transmission Customer's own Generators or generation obtained from an entity other than the ISO.

Service Agreement: The agreement, in the form of Attachment A to the Tariff, and any amendments or supplements thereto entered into by a Customer and the ISO of service under the Tariff, or any unexecuted Service Agreement, amendments or supplements thereto, that the ISO unilaterally files with the Commission.

Service Commencement Date: The date that the ISO begins to provide service pursuant to the terms of a Service Agreement, or in accordance with the Tariff.

Settlement: The process of determining the charges to be paid to, or by, a Customer to satisfy its obligations.

Shadow Price: The marginal value of relieving a particular Constraint which is determined by the reduction in system cost that results from an incremental relaxation of that Constraint.

Shift Factor ("SF"): A ratio, calculated by the ISO, that compares the change in power flow through a transmission facility resulting from the incremental injection and withdrawal of power on the NYS Transmission System.

Shutdown Period: An ISO approved period of time immediately following a shutdown order, such as a zero base point, that has been designated by the Customer, during which unstable operation prevents the unit from accurately following its base points.

Sink Price Cap Bid: A monotonically increasing Bid curve provided by an entity engaged in an Export, other than an entity submitting a CTS Interface Bid, to indicate the relevant Proxy Generator Bus LBMP at or below which that entity is willing to either purchase Energy in the LBMP Markets or, in the case of Bilateral Transactions, to accept Transmission Service, where the MW amounts on the Bid curve represent the desired increments of Energy that the entity is willing to purchase at various price points.

Southeastern New York ("SENY"): An electrical area comprised of Load Zones G, H, I, J, and K, as identified in the ISO Procedures.

Special Case Resource ("SCR"): Demand Side Resources whose Load is capable of being interrupted upon demand at the direction of the ISO, and/or Demand Side Resources that have a Local Generator, which is not visible to the ISO's Market Information System and is rated 100 kW or higher, that can be operated to reduce Load from the NYS Transmission System or the distribution system at the direction of the ISO. Special Case Resources are subject to special rules, set forth in Section 5.12.11.1 of this ISO Services Tariff and related ISO Procedures, in order to facilitate their participation in the Installed Capacity market as Installed Capacity Suppliers. SCRs that do not use Local Generators may be offered as synchronized Operating Reserves and Regulation Service and Energy in the Day-Ahead Market. SCRs, using Local Generators rated 100 kW or higher, that are not visible to the ISO's Market Information System may also be offered as non-synchronized Operating Reserves.

Special Case Resource Capacity: The Installed Capacity Equivalent of the Unforced Capacity which has been sold by a Special Case Resource in the Installed Capacity market during the current Capability Period.

Start-Up Period: An ISO approved period of time immediately following synchronization to the Bulk power system, which has been designated by a Customer and bid into the Real-Time Market, during which unstable operation prevents the unit from accurately following its base points.

Station Power: Station Power shall mean the Energy used by a Generator:

1. for operating electric equipment located on the Generator site, or portions thereof, owned by the same entity that owns the Generator, which electrical equipment is used by the Generator exclusively for the production of Energy and any useful thermal energy associated with the production of Energy; and
2. for the incidental heating, lighting, air conditioning and office equipment needs of buildings, or portions thereof, that are: owned by the same entity that owns the Generator; located on the Generator site; and
3. used by the Generator exclusively in connection with the production of Energy and any useful thermal energy associated with the production of Energy.

Station Power does not include any Energy: (i) used to power synchronous condensers; (ii) used for pumping at a pumped storage facility or for charging a Limited Energy Storage Resource; or (iii) provided during a Black Start restoration by Generators that provide Black Start Capability Service.

Start-Up Bid: A Bid parameter that may vary hourly and that identifies the payment a Supplier requires to bring a Generator up to its specified minimum operating level from an offline state or a Demand Side Resource from a level of no Demand Reduction to its specified minimum level of Demand Reduction.

Start-Up Bids submitted for a Generator that is not able to complete its specified minimum run time (of up to a maximum of 24 hours) within the Dispatch Day are expected to include expected net costs related to the hour(s) that a Generator needs to run on the day following the Dispatch Day in order to complete its minimum run time. The component of the Start-Up Bid that incorporates costs that the Generator expects to incur on the day following the Dispatch Day is expected to reflect the operating costs that the Supplier does not expect to be able to recover through LBMP revenues while operating to meet the Generator's minimum run time, at the minimum operating level Bid for that Generator for the hour of the Dispatch Day in which the Generator is scheduled to start-up. Settlement rules addressing Start-Up Bids that incorporates costs related to the hours that a Generator needs to run on the day following the Dispatch Day on which the Generator is committed are set forth in Attachment C to this ISO Services Tariff.

Storm Watch: Actual or anticipated severe weather conditions under which region-specific portions of the NYS Transmission System are operated in a more conservative manner by reducing transmission transfer limits.

Strandable Costs: Prudent and verifiable expenditures and commitments made pursuant to a Transmission Owner's legal obligations that are currently recovered in the Transmission Owner's retail or wholesale rate that could become unrecoverable as a result of a restructuring of the electric utility industry and/or electricity market, or as a result of retail-turned-wholesale customers, or customers switching generation or Transmission Service suppliers.

Stranded Investment Recovery Charge: A charge established by a Transmission Owner to recover Strandable Costs.

Study Month: The calendar month for which the ISO calculates the Monthly Net Benefit Offer Floor, in accordance with Section 4.2.1.9 of the ISO Services Tariff and ISO Procedures.

Subzone: That portion of a Load Zone in a Transmission Owner's Transmission District.

Supplemental Event Interval: Any RTD interval in which there is a maximum generation pickup or a large event reserve pickup or which is one of the three RTD intervals following the termination of the maximum generation pickup or the large event reserve pickup.

Supplemental Resource Evaluation ("SRE"): A determination of the least cost selection of additional Generators, which are to be committed, to meet: (i) changed or local system conditions for the Dispatch Day that may cause the Day-Ahead schedules for the Dispatch Day to be inadequate to meet the reliability requirements of the Transmission Owner's local system or to meet Load or reliability requirements of the ISO; or (ii) forecast Load and reserve requirements over the six-day period that follows the Dispatch Day.

Supplier: A Party that is supplying the Capacity, Demand Reduction, Energy and/or associated Ancillary Services to be made available under the ISO OATT or the ISO Services Tariff, including Generators and Demand Side Resources that satisfy all applicable ISO requirements.

System Resource: A portfolio of Unforced Capacity provided by Resources located in a single ISO-defined Locality, the remainder of the NYCA, or any single External Control Area, that is owned by or under the control of a single entity, which is not the operator of the Control Area where such Resources are located, and that is made available, in whole or in part, to the ISO.

2.20 Definitions - T

Tangible Net Worth: The value, determined by the ISO, of all of a Customer's assets less both: (i) the amount of the Customer's liabilities and (ii) all of the Customer's intangible assets, including, but not limited to, patents, trademarks, franchises, intellectual property, and goodwill.

Testing Period: An ISO approved period of time during which a Generator is testing equipment and during which unstable operation prevents the unit from accurately following its base points.

Third Party Transmission Wheeling Agreements ("Third Party TWAs"): A Transmission Wheeling Agreement, as amended, between Transmission Owners or between a Transmission Owner and an entity that is not a Transmission Owner. Third Party TWAs are associated with the purchase (or sale) of Energy, Capacity, and/or Ancillary Services for the benefit of an entity that is not a Transmission Owner. All Third Party TWAs are listed in Table 1 A of Attachment L to the ISO OATT, and are designated in the "Treatment" column of Table 1A, as "Third Party TWA."

Total Transfer Capability ("TTC"): The amount of electric power that can be transferred over the interconnected transmission network in a reliable manner.

Trading Hub: A virtual location in a given Load Zone, modeled as a Generator bus and/or Load bus, for scheduling Bilateral Transactions in which both the POI and POW are located within the NYCA.

Trading Hub Energy Owner: A Customer who buys energy in a Bilateral Transaction in which the POW is a Trading Hub, or who sells energy in a Bilateral Transaction in which the POI is a Trading Hub.

Transaction: The purchase and/or sale of Energy or Capacity, or the sale of Ancillary Services. A Transaction bid into the Energy market to sell or purchase Energy or to schedule a Bilateral Transaction includes a Point of Injection and a Point of Withdrawal.

Transfer Capability: The measure of the ability of interconnected electrical systems to reliably move or transfer power from one area to another over all transmission facilities (or paths) between those areas under specified system conditions.

Transmission Congestion Contract Component ("TCC Component"): A component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

Transmission Congestion Contracts ("TCCs"): The right to collect or obligation to pay Congestion Rents in the Day-Ahead Market for Energy associated with a single MW of transmission between a specified POI and POW. TCCs are financial instruments that enable Energy buyers and sellers to hedge fluctuations in the price of transmission.

Transmission Customer: Any entity (or its designated agent) that requests or receives Transmission Service pursuant to a Service Agreement and the terms of the ISO OATT.

Transmission District: The geographic area served by the Investor-Owned Transmission Owners and LIPA, as well as the customers directly interconnected with the transmission facilities of the Power Authority of the State of New York.

Transmission Facilities Under ISO Operational Control: The transmission facilities of the Transmission Owners listed in Appendix A-1 of the ISO/TO Agreement, "Listing of Transmission Facilities Under ISO Operational Control," that are subject to the Operational Control of the ISO. This listing may be amended from time-to-time as specified in the ISO/TO Agreement.

Transmission Facilities Requiring ISO Notification: The transmission facilities of the Transmission Owners listed in Appendix A-2 of the ISO/TO Agreement, ("Listing of Transmission Facilities Requiring ISO Notification") whose status of operation must be provided to the ISO by the Transmission Owners (for the purposes stated in the ISO Tariffs and in accordance with the ISO Tariffs and ISO/TO Agreement) prior to the Transmission Owners making operational changes to the state of these facilities. This listing may be amended from time-to-time as specified in the ISO/TO Agreement.

Transmission Facility Agreement ("TFA"): Agreements governing the use of specific or designated transmission facilities charges to cover all, or a portion, of the costs to install, own, operate, or maintain transmission facilities, to the customer under the agreement and that have provisions to provide Transmission Service utilizing said transmission facilities. All Transmission Facility Agreements are listed in Attachment L. Table 1A, and are designated in the "Treatment" column as "Facility Agmt. – MWA."

Transmission Fund ("T-Fund"): The mechanism used under the current NYPP Agreement to compensate the Member Systems for providing Transmission Service for economy Energy Transactions over their transmission systems. Each Member System is allocated a share of the economy Energy savings in dollars assigned to the fund that is based on the ratio of their investment in transmission facilities to the sum of investments in transmission and generation facilities.

Transmission Owner: The public utility or authority (or its designated agent) that owns facilities used for the transmission of Energy in interstate commerce and provides Transmission Service under the Tariff.

Transmission Owner's Monthly Transmission System Peak: The maximum hourly firm usage as measured in megawatts ("MW") of the Transmission Owner's transmission system in a calendar month.

Transmission Reliability Margin ("TRM"): The amount of TTC reserved by the ISO to ensure the interconnected transmission network is secure under a reasonable range of uncertainties in system conditions.

Transmission Service: Point-To-Point Network Integration or Retail Access Transmission Service provided under the ISO OATT.

Transmission Service Charge (“TSC”): A charge designed to ensure recovery of the embedded cost of a Transmission Owner’s transmission system.

Transmission Shortage Cost: A series of quantity/price points that defines the maximum Shadow Price of a particular Constraint that will be used in calculating LBMP. The Transmission Shortage Costs are set at \$350/MWh for shortages above zero and less than or equal to 5MW, \$2350/MWh for shortages above 5MW and less than or equal to 20MW, and \$4000/MWh for shortages above 20MW.

Transmission System: The facilities operated by the ISO that are used to provide Transmission Services under the ISO OATT.

Transmission Usage Charge (“TUC”): Payments made by the Transmission Customer to cover the cost of Marginal Losses and, during periods of time when the transmission system is constrained, the marginal cost of Congestion. The TUC is equal to the product of: (1) the LBMP at the POW minus the LBMP at the POI (in \$/MWh); and (2) the scheduled or delivered Energy (in MWh).

Transmission Wheeling Agreement (“TWA”): The Agreements listed in Table 1A of Attachment L to the ISO OATT governing the use of specific or designated transmission facilities that are owned, controlled or operated by an entity for the transmission of Energy in interstate commerce. TWAs between Transmission Owners have been modified such that all TWAs between Transmission Owners are now MWAs.

2.21 Definitions - U

Unforced Capacity: The measure by which Installed Capacity Suppliers will be rated, in accordance with formulae set forth in the ISO Procedures, to quantify the extent of their contribution to satisfy the NYCA Installed Capacity Requirement, and which will be used to measure the portion of that NYCA Installed Capacity Requirement for which each LSE is responsible.

Unforced Capacity Deliverability Rights: Unforced Capacity Deliverability Rights (“UDRs”) are rights, as measured in MWs, associated with (i) new incremental controllable transmission projects, and (ii) new projects to increase the capability of existing controllable transmission projects that have UDRs, that provide a transmission interface to a Locality. When combined with Unforced Capacity which is located in an External Control Area or non-constrained NYCA region either by contract or ownership, and which is deliverable to the NYCA interface in the Locality in which the UDR transmission facility is electrically located, UDRs allow such Unforced Capacity to be treated as if it were located in the Locality, thereby contributing to an LSE’s Locational Minimum Installed Capacity Requirement. To the extent the NYCA interface is with an External Control Area the Unforced Capacity associated with UDRs must be deliverable to the Interconnection Point.

UCAP Component: A component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

Unrated Customer: A Customer that does not currently have a senior long-term unsecured debt rating or issuer rating from Standard & Poor’s, Moody’s, Fitch, or Dominion, and that has not received an ISO Equivalency Rating.

Unsecured Credit: A basis for satisfying part of a Customer’s Operating Requirement on the basis of the Customer’s creditworthiness. The amount of a Customer’s Unsecured Credit shall be determined in accordance with Section 26.5 of Attachment K to this Services Tariff.

2.22 Definitions - V

Variably Scheduled Proxy Generator Bus: A Proxy Generator Bus for which the ISO may schedule Transactions at 15 minute intervals in real time. Variably Scheduled Proxy Generator Buses are identified in Section 4.4.4 of the Services Tariff.

Verified Average Coincident Load (“Verified ACL”): The Average Coincident Load determined by the ISO with verification data provided by the RIP for SCRs enrolled with a Provisional Average Coincident Load, as calculated pursuant to Section 5.12.11.1.2 of this Services Tariff, or, beginning with the Summer 2014 Capability Period, for resources with a reported Incremental Average Coincident Load, as calculated pursuant to Section 5.12.11.1.5 of this Services Tariff. The Verified ACL shall be used to evaluate the SCR’s event responses for performance and in the calculation of the SCR’s performance factor and all associated performance factors, deficiencies and penalties.

Virtual Load: Any Bid to purchase Energy in the Day-Ahead Market submitted at a load bus specified for Virtual Transactions.

Virtual Supply: Any Bid to sell Energy in the Day-Ahead Market submitted at a load bus specified for Virtual Transactions.

Virtual Transaction: Any Bid to purchase or sell Energy in the Day-Ahead Market submitted at a load bus specified for Virtual Transactions.

Virtual Transaction Component: A component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

2.23 Definitions - W

West of Central-East (“West” or “Western”): An electrical area comprised of Load Zones A, B, C, D, and E, as identified in the ISO Procedures.

Wheels Through: Transmission Service, originating in another Control Area, that is wheeled through the NYCA to another Control Area.

Wheels Through Credit Requirement: A component of the External Transaction Component of the Operating Requirement, calculated in accordance with Section 26.4.2 of Attachment K to this Services Tariff.

Wholesale Market: The sum of purchases and sales of Energy and Capacity for resale along with Ancillary Services needed to maintain reliability and power quality at the transmission level coordinated together through the ISO and Power Exchanges. A party who purchases Energy, Capacity or Ancillary Services in the Wholesale Market to serve its own Load is considered to be a participant in the Wholesale Market.

Wholesale Transmission Services Charges (“WTSC”): Those charges calculated pursuant to Attachment H of the OATT, incurred or declared overdue by a Transmission Owner pursuant to Section 26.4.2 of Attachment K, after the effective date of these revisions; provided, however, that these provisions will not apply to pre-petition bankruptcy debts for a company that is currently in bankruptcy.

Wind Energy Forecast: The ISO’s forecast of Energy that is expected to be supplied over a specified interval of time by an Intermittent Power Resource that depends on wind as its fuel and which is used in ISO’s Energy market commitment and dispatch.

Wind Output Limit: A Base Point Signal calculated for an Intermittent Power Resource depending on wind as its fuel and which, when sent to the Intermittent Power Resource, shall include a separate flag indicating that the Base Point Signal directs the Intermittent Power Resource to reduce its output. All Intermittent Power Resources, other than those in commercial operation as of January 1, 2002 with name plate capacity of 12 MWs or fewer, shall be eligible to receive a Wind Output Limit.

WTSC Component: A component of the Operating Requirement, calculated in accordance with Section 26.4.2, of Attachment K to this Services Tariff.

2.24 Definitions - X

2.25 Definitions - Y

2.26 Definitions - Z

5 CONTROL AREA SERVICES: RIGHTS AND OBLIGATIONS

5.1 Control Area Services

The ISO will provide Control Area Services in accordance with the standards and criteria of NERC and NPCC, the Reliability Rules of the NYSRC, and Good Utility Practice. The Control Area Services provided by the ISO include, but are not limited to, the following:

- (a) Developing and implementing procedures to maintain the reliability of NYS Power System;
- (b) Coordinating operations with other Control Area operators;
- (c) Arranging for reserve sharing agreements with other ISOs and other Control Areas to enhance reliability during abnormal operating conditions;
- (d) Coordinating the outage schedules for generating units within the NYCA to maintain system reliability;
- (e) Committing adequate generation resources to ensure the reliability of the NYS Power System;
- (f) Taking command and control of the NYCA resources during Emergency conditions and coordinating operations with Transmission Owners;
- (g) Maintaining and Operating a central control center and performing the functions of the NERC security control center for the NYCA under Emergency operating conditions;
- (h) Defining the Installed Capacity requirements for LSEs, inclusive of individual customers taking services directly from the ISO, within the NYCA;
- (i) Determining Locational Installed Capacity requirements for LSEs to ensure the reliable operation of the NYCA;
- (j) Administering of an Installed Capacity Market;

- (k) Training the operating personnel of the ISO and Transmission Owner control rooms; and
- (l) Administering the mandatory NERC reliability compliance process.

5.1.1 Customer Compliance with Reliability Standards; Penalties

5.1.1.1 Customer Compliance with Reliability Standards:

In accordance with applicable requirements in this Tariff and the ISO Procedures, all Customers shall conform to all applicable reliability criteria, policies, standards, rules, regulations and other requirements of NERC, NPCC, NYSRC, any applicable regional council, or their successors, the ISO's specific reliability requirements and ISO Procedures, and applicable operating guidelines and all applicable requirements of federal and state regulatory authorities. Failure to conform to these requirements may subject a Customer to direct assignment of penalties assessed against the ISO by FERC, NERC, NPCC or any other federal or state regulatory authority as a result of such Customer's failure to conform.

5.1.1.2 Direct Assignment of Penalty Costs:

The ISO's compliance with applicable reliability criteria, policies, standards, rules, regulations and other requirements is sometimes dependent on timely, accurate and adequate information and/or action on the part of a Customer. If the ISO is found to be non-compliant with respect to any applicable reliability criteria, policies, standards, rules, regulations and other requirements as a result of a Customer's actions or failure to act in violation of an obligation imposed by the ISO Tariffs, ISO Procedures, or ISO Related Agreements, the ISO may seek to directly assign to the Customer the cost of a penalty imposed on the ISO as a consequence of its non-compliance. If the Customer is found to be non-compliant with respect to any applicable reliability criteria, policies, standards, rules, regulations and other requirements as a result of the

ISO's actions or failure to act in violation of an obligation imposed by the ISO Tariffs, ISO Procedures, or ISO Related Agreements, the Customer may seek to directly assign to the ISO the cost of a penalty imposed on the Customer as a consequence of the ISO's non-compliance. Any direct assignment of penalty costs must first be approved by FERC, as provided in Schedule 6.11 of the OATT.

5.1.1.3 ISO's Recovery of Penalty Costs Through Schedule 11:

If direct assignment to a particular Customer is not possible or if the ISO is directly responsible for a violation because of its own action or inaction, the ISO may seek to recover such penalty costs in Schedule 6.11 Section 6.11.3 of the ISO OATT. Any inclusion of penalty costs in Schedule 6.11 must first be approved by FERC on a case-by-case basis, as provided in Schedule 6.11 of the ISO OATT. Prior to seeking FERC authorization for recovery of a penalty in Schedule 6.11 Section 6.11.3 of the ISO OATT, the ISO shall consult with the Management Committee and any appropriate subcommittee or working groups designated by the Management Committee, regarding the recovery and allocation of such penalty before filing at FERC. Any recommendation by the Management Committee regarding a proposed penalty recovery shall be reported by the ISO to FERC in any ISO filing seeking penalty recovery.

5.1.2 Incorporation of Certain Business Practice Standards

- (a) Pursuant to Commission Order No. 676-H, the ISO incorporates by reference the following business practice standards developed by the North American Energy Standards Board's Wholesale Electric Quadrant:

WEQ-000, Abbreviations, Acronyms, and Definition of Terms, WEQ Version 003, July 31, 2012, as modified by NAESB final actions ratified on Oct. 4, 2012, Nov. 28, 2012 and Dec. 28, 2012 (with minor corrections applied Nov. 26, 2013);

WEQ-001, Open Access Same-Time Information Systems (OASIS), OASIS Version 2.0, WEQ Version 003, July 31, 2012 as modified by NAESB final actions ratified on Dec. 28, 2012 (with minor corrections applied November 26, 2013) excluding Standards WEQ-001-9.5, WEQ-001-10.5, WEQ-001-14.1.3, WEQ-001-15.1.2 and WEQ-001-106.2.5, except as provided below;

WEQ-004, Coordinate Interchange, WEQ Version 003, July 31, 2012 (with Final Action ratified on December 28, 2012), except as provided below;

WEQ-005, Area Control Error (ACE) Equation Special Cases, WEQ Version 003, July 31, 2012

WEQ-006, Manual Time Error Correction, WEQ Version 003, July 31, 2012;

WEQ-007, Inadvertent Interchange Payback, WEQ Version 003, July 31, 2012;

WEQ-008, Transmission Loading Relief - Eastern Interconnection, WEQ Version 003, July 31, 2012 (with minor corrections applied November 28, 2012);

WEQ-011, Gas/Electric Coordination, WEQ Version 003, July 31, 2012;

WEQ-012, Public Key Infrastructure (PKI), WEQ Version 003, July 31, 2012, (as modified by NAESB final actions ratified on Oct. 4, 2012), except as provided below (NYISO compliance to begin May 15, 2017, pursuant to *New York Independent System Operator, Inc.*, FERC Docket No. ER15-550-000, Notice Granting Extension (April 15, 2015));

WEQ-015, Measurement and Verification of Wholesale Electricity Demand Response, WEQ Version 003, July 31, 2012 (with minor corrections applied November 26, 2013); and

WEQ-021, Measurement and Verification of Energy Efficiency Products, WEQ Version 003, July 31, 2012.

- (b) The ISO is not required to comply with the following Standards:

WEQ-001, Open Access Same-Time Information Systems (OASIS), OASIS Version 2.0, WEQ Version 003, July 31, 2012 (with minor corrections applied November 26, 2013): Standards 001-2, 001-3, 001-4, 001-5, 001-6, 001-7, 001-8, 001-9, 001-10, 001-011, 001-012, 001-13.1.2, 001-13.1.3(b) and (c), 001-014, 001-015, 001-016, 001-017, 001-018, 001-019, 001-020, 001-021, 001-022, 001-23, 001-101 through 001-107.3.1, 001-Appendix A, 001-Appendix B, and 001-Appendix D, pursuant to *New York Independent System Operator, Inc.*, 151 FERC ¶ 61,157 (May 19, 2015);

WEQ-002, Open Access Same-Time Information Systems (OASIS) Business Practice Standards & Communication Protocols (S&CP), OASIS Version 2.0, WEQ Version 003, July 31, 2012, as modified by NAESB final actions ratified on Nov. 28, 2012 and Dec. 28, 2012(with minor corrections applied November 26, 2013), pursuant to *New York Independent System Operator, Inc.*, 151 FERC ¶ 61,157 (May 19, 2015);

WEQ-003, Open Access Same-Time Information Systems (OASIS) Data Dictionary Business Practice Standards, OASIS Version 2.0, WEQ Version 003, July 31, 2012, as modified by NAESB final actions ratified on Nov. 28, 2012 and Dec. 28, 2012 (with minor corrections applied November 26, 2013), pursuant to *New York Independent System Operator, Inc.*, 151 FERC ¶ 61,157 (May 19, 2015);

WEQ-004, Coordinate Interchange, WEQ Version 003, July 31, 2012 (with Final Action ratified on December 28, 2012): Standards 004-3, 004-18, and 004-Appendix A and 004-Appendix C, pursuant to *New York Independent System Operator, Inc.*, 151 FERC ¶ 61,157 (May 19, 2015); and

WEQ-013, Open Access Same-Time Information Systems (OASIS) Implementation Guide, OASIS Version 2.0, WEQ Version 003, July 31, 2012, as modified by NAESB final actions ratified on Dec. 28, 2012 (with minor corrections applied November 26, 2013), pursuant to *New York Independent System Operator, Inc.*, 151 FERC ¶ 61,157 (May 19, 2015).

5.2 Independent System Operator Authority

The ISO will act as the Control Area operator, as defined by NERC, for the NYCA. The ISO will provide all Control Area Services in the NYCA. Control Area Services provided by the ISO will be in accordance with the terms of the ISO Services Tariff, the Reliability Rules, the ISO Related Agreements and Good Utility Practice. The ISO will act with other Control Area operators as required to modify External Transactions pursuant to this Tariff and to ensure the effective and reliable coordination with the interconnected Control Areas. In acting as the Control Area operator, the ISO will be responsible for maintaining the safety and the short-term reliability of the NYCA and for the implementation of reliability standards promulgated by NERC and NPCC and for the Reliability Rules promulgated by the NYSRC. To be included within NYCA, a Market Participant must meet the requirements of Section 5.6. Each Market Participant that (1) withdraws Energy to supply Load within the NYCA; or (2) provides installed Capacity to an LSE serving Load within the NYCA, benefits from the Control Area Services provided by the ISO and from the reliability achieved as a result of ISO Control Area Services and therefore must take service as a Customer under the Tariff. To be included within NYCA, a Market Participant must meet the requirements of Section 5.6. A Market Participant that is not included within the NYCA may take service as a Customer under the Tariff, provided that it meets the requirements of Section 5.7.

5.2.1 Suspension of Virtual Transactions

The ISO may temporarily suspend Virtual Transactions if it determines that:

- 5.2.1.1 The financial exposure of customers engaged in Virtual Transactions cannot be determined with a reasonable degree of accuracy or to factors such as software or system failures;

5.2.1.2 A market aberration associated with Virtual Transactions substantially impairs the functioning of the ISO-administered markets; or

5.2.1.3 Virtual Transactions substantially impair the ability of the ISO to maintain the reliability of the electric system.

As soon as reasonably practicable, the ISO shall notify the Commission and Market Participants of the reason(s) for any suspension of Virtual Transactions, the action(s) necessary to restore Virtual Transactions, and the estimated time required to restore Virtual Transactions.

5.2.2 Suspension of the Ability of Generators to Increase Their Bids in Real-Time

The ISO may temporarily suspend the ability to submit Incremental Energy Bids in the real-time market that exceed the Incremental Energy Bids submitted in the Day-Ahead Market or the mitigated Day-Ahead Incremental Energy Bids where appropriate for the portions of Generators' Capacity that were scheduled in the Day-Ahead Market, if the ISO determines that:

5.2.2.1 a market aberration associated with Incremental Energy Bids submitted in the real-time market that exceed the Incremental Energy Bids submitted in the Day-Ahead Market for the portions of Generators' Capacity that were scheduled in the Day-Ahead Market substantially impairs the functioning of the ISO-administered markets; or

5.2.2.2 Permitting Incremental Energy Bids submitted in the real-time market to exceed the Incremental Energy Bids submitted in the Day-Ahead Market or the mitigated Day-Ahead Incremental Energy Bids where appropriate, for portions of Generators' Capacity that were scheduled in the Day-Ahead Market substantially impairs the ability of the ISO to maintain the reliability of the electric system.

As soon as reasonably practicable, the ISO shall notify the Commission and Market Participants of the reason(s) for any suspension of the ability for Incremental Energy Bids submitted in the real-time market to exceed the Incremental Energy Bids submitted in the Day-Ahead Market or the mitigated Day-Ahead Incremental Energy Bids where appropriate, for portions of Generators' Capacity that were scheduled in the Day-Ahead Market; the action(s) necessary to restore this feature to the ISO-Administered Markets; and the estimated time required to restore this feature to the ISO-Administered Markets.

5.3 Control Center Operation

The ISO will maintain and operate a control center in order to monitor the power flows on and across the NYCA, coordinate the flow of electricity within the NYCA, respond to Emergency situations, monitor power flows between the NYCA and neighboring Control Areas and maintain reliability.

5.3.1 Back-Up Operation

The ISO shall develop Back-Up Operation procedures that will carry out the intent and purposes of this ISO Services Tariff, to the extent practical, in circumstances under which the normal communications or computer systems of the ISO are not fully functional. Such procedures shall include testing requirements and training for the ISO staff, Transmission Owner staff, and Market Participants. If a communication or computer system malfunction results in the ISO's inability to operate the NYCA in accordance with ISO Procedures or under approved testing procedures, the ISO will direct the Transmission Owners to assume the responsibility to operate their respective systems in accordance with Good Utility Practice to facilitate the operation of the NYCA in a safe and reliable manner. The Transmission Owners will continue to operate their respective systems until such time that the ISO is ready to resume control. During Back-Up Operation, the Transmission Owner control centers will operate to maintain the Desired Net Interchange ("DNI") within each Transmission District. Generator Bid curves will be provided by the ISO to the individual Transmission Owners in order to permit dispatch by the Transmission Owners subject to the Transmission Owner code of conduct. Normal Day-Ahead Market and Real-Time Market operations may be halted, if required.

5.3.2 Market Participant and Customer Obligations

During Back-Up Operation, Customers and other Market Participants shall comply with any and all instructions and orders issued by the ISO or the Transmission Owners.

5.3.3 Billing and Settlement

In the event that Back-Up Operation is implemented, the billing and settlement procedures contained in Article 7 of this ISO Services Tariff shall apply only to the extent they can be implemented under the Back-Up Operation procedures. The ISO will follow specific billing and settlement procedures for use under these specific circumstances that required Back-Up Operation. The ISO shall gather necessary information, manually reconstruct the billing information as soon as practical, and submit invoices to Customers. The ISO shall be under no obligation to comply with the billing procedure time limits specified in Article 7. Neither the ISO nor the Transmission Owners shall be liable, under any circumstances, for any economic losses suffered by any Customer, Market Participant, or third party, resulting from the implementation by the ISO of Back-Up Operation, or from compliance with orders issued by the ISO or Transmission Owners that were necessary to operate the NYCA in a safe and reliable manner. Such orders may include, without limitation, instructions to generation facilities to increase or decrease output, and instructions to Load to reduce or interrupt service.

5.4 Operation Under Adverse Conditions

The ISO shall operate the NYS Power System during Adverse Conditions, including, but not limited to, thunder storms, hurricanes, tornadoes, solar magnetic flares and threat of terrorist activities, in accordance with the Reliability Rules, inclusive of Local Reliability Rules and related PSC orders. Consistent with such Reliability Rules, the ISO shall maintain reliability of the NYS Power System by directing the adjustment of the Generator output levels and controllable transmission devices in certain areas of the system to reduce power flows across transmission lines vulnerable to outages due to these Adverse Conditions, thereby reducing the likelihood of major power system disturbances.

The ISO shall have the sole authority to declare that Adverse Conditions are imminent or present and invoke the appropriate operating procedure(s) affecting the NYS Power System in response to those conditions. Activation of a procedure in compliance with a Local Reliability Rule shall involve a two (2) step process. The Transmission Owner directly involved with such Local Reliability Rule, such as Storm Watch, shall advise the ISO that Adverse Conditions are imminent or present and recommend to the ISO the activation of procedures in support of that Local Reliability Rule. Consistent with the Local Reliability Rule, the ISO shall declare the activation of the appropriate procedures.

The Transmission Owner and the ISO shall coordinate the implementation of the applicable procedures to the extent that Transmission Facilities under ISO Operational Control are impacted. Records pertaining to the activation of such procedures and the response in accordance with those procedures shall be maintained and made available upon request.

The Real-Time LBMPs shall be based on adjusted Generator levels set in response to activation of these procedures. Revenue shortfalls may occur if the redispatch of the system

Curtailed Energy scheduled Day-Ahead and more expensive Energy is dispatched subsequent to the Day-Ahead Settlement. These revenue shortfalls shall be recovered by the ISO through the Rate Schedule 1 charge under the ISO OATT.

5.5 Major Emergency State

In the event of, or in order to prevent, a Major Emergency State, Customers shall comply with all ISO Procedures and Reliability Rules applicable to a Major Emergency State.

5.6 Requirements For Inclusion Within The New York Control Area

To be included within the NYCA a Supplier or a Load must meet the following requirements:

- (a) Its facilities must be included within the NYCA.
- (b) It must accept and comply with NYCA standards with respect to system design, equipment ratings, operating practices and maintenance practices as set forth in the ISO Procedures so that sufficient electrical equipment control capability, information and communication are available to the ISO for planning and operation of the NYCA.
- (c) Its facilities must be able to respond to command and control instructions from the ISO.
- (d) It must have compatible operational communication mechanisms, maintained at its expense, to interact with the ISO and for Internal requirements.
- (e) It must ensure the continued compatibility of its local Energy management system, system monitoring and telecommunications systems to satisfy the technical requirements of interacting with the ISO as the ISO directs the operation of the NYCA.

5.7 Requirements For Entities Not Located Within The New York Control Area

In order for a Supplier or a Load that is not included within the NYCA to take services under the Tariff, it must be contained, in whole or in part, within a separate Control Area that meets all of the requirements for a Control Area defined by NERC, NPCC and any succeeding organizations. An entity that is contained in a Control Area other than the NYCA may take services under the ISO Services Tariff for the purpose of engaging in Control Area to Control Area Capacity and Energy Transactions with the ISO. In order for a Supplier or a Load not contained in the NYCA to take services under the ISO Services Tariff, an inter-Control Area agreement between the Control Area in which the entity is located and the ISO, that satisfies the reasonable requirements of both Control Area operators, must be in place.

5.8 Communication and Metering Requirements for Control Area Services

The ISO shall arrange for and maintain reliable communications and metering facilities between the ISO and the Transmission Owners in the NYCA and the Control Area operators of all neighboring interconnected Control Areas. Such facilities may consist of data circuits, voice lines, meters and other facilities deemed necessary by the ISO to maintain reliable communication links for the sole purpose of transmitting operations and reliability data and instructions. The ISO shall be responsible for the specification, installation and maintenance of the required facilities according to ISO Procedures. The costs incurred by the ISO to establish communications facilities between the ISO and a Security Coordinators of a neighboring Control Area shall be borne by the Control Area that requested the establishment of the communications facilities unless a different arrangement is agreed to by both Control Areas. The total cost of the communications facilities between the ISO and the Transmission Owners and the portion of the cost of inter-Control Area communication facilities assigned to the ISO shall be collected from all Customers in accordance with Rate Schedule 15.1 of the ISO Services Tariff. Transmission Owners with communications requirements which exceed those required by the ISO shall procure and maintain such additional facilities at their own expense.

Generators, Suppliers and Loads are required to exchange certain operating and reliability data with the ISO and the Transmission Owners' Control Centers in accordance with the ISO Agreement and the ISO/TO Agreement, applicable ISO operating and reliability requirements, and in conjunction with any requirements for interconnection with the Transmission Owner.

In addition, Suppliers wishing to submit Bids in the RTC for Energy or Regulation Service must make provision to receive command and control information from the ISO. Those Generators or Suppliers currently providing this capability via a Transmission Owner may

continue to do so. Those requiring installation of this capability must contract with the ISO or with the interconnected Transmission Owner and must comply with applicable ISO or Transmission Owner data and other technical requirements.

Suppliers with multiple units at a single location must maintain a consistent representation of the plant with the ISO with respect to aggregation of units for purposes of bidding. If an aggregate Bid is to be provided for a group of units and those units are bidding in the RTC, or providing Regulation Service, then the ISO shall model those units as a group for purposes of dispatch, control and security modeling. The ISO will provide a single aggregate Base Point Signal and unit control error. If, however, the Supplier wishes to dispatch units individually, then it must configure both its bidding and data interfaces accordingly. Each Supplier must initially specify the configuration of the plant for purposes of bidding aggregation and must then maintain bidding and data interfaces consistent with that configuration. Similar modeling, control and bidding Constraints apply to an LSE that bids Load that is dispatchable by the ISO.

5.8.1 Collection and Communication of Energy Forecasting Data by Intermittent Power Resources that Depend on Wind as Their Fuel

Pursuant to ISO Procedures, Intermittent Power Resources that depend on wind as their fuel shall maintain in good working order equipment to collect wind speed and wind direction data at their site and shall provide the ISO, or its agent, with wind speed, wind direction and maximum available megawatt data in the manner identified by the ISO, provided however this requirement shall not apply to any Intermittent Power Resource in commercial operation as of January 1, 2002 with nameplate capacity of 12 MWs or fewer. Maximum available megawatts shall be the sum of the individual nameplate capacities for all turbines that are online and currently capable of producing power (including those turbines that are not producing any power

due to low wind speeds); this value should exclude those turbines that are not producing power due to a fault condition or a network communication failure condition or that are offline for service. Each Intermittent Power Resource that depends on wind as its fuel shall be responsible for the cost of installing and maintaining such equipment at its site and shall share in funding the ISO's cost of wind forecasting function pursuant to this Services Tariff.

The ISO may impose financial sanctions for failure to provide wind speed and wind direction data pursuant to ISO Procedures.

Upon a determination of failure to provide wind speed and wind direction data pursuant to ISO Procedures, the ISO shall take the following actions. The ISO shall notify the Intermittent Power Resource that depends on wind as its fuel by written notice of its determination of failure to provide wind speed and wind direction data and that the ISO may impose financial sanctions if the failure is not corrected. The ISO shall offer a reasonable opportunity to correct the failure to provide wind speed and wind direction data pursuant to ISO Procedures. If, following such reasonable opportunity to cure, such failure is not cured, the ISO may impose daily sanctions of the greater of \$500 or \$20/MW of nameplate capacity until such failure is cured. The ISO shall offer the Intermittent Power Resource an opportunity to be heard by senior officers of the ISO prior to imposing sanctions.

5.9 Installed Capacity ~~–Implementation of Revised Installed Capacity Market Provisions and Locational Export Capacity~~

5.9.1 Sections 5.10 through 5.17 of this Tariff, implementing the Installed Capacity market design, shall govern LSE Unforced Capacity Obligations, the qualification of Installed Capacity Suppliers, and the ISO's administration of Installed Capacity auctions.

5.9.2 Provisions applicable to Locational Export Capacity. Nothing in this Section alters the requirements in the ISO Tariffs or ISO Procedures generally applicable to Installed Capacity Suppliers and Generators.

5.9.2.2 Eligibility. In order to be eligible to export capacity from an Import Constrained Locality for an Obligation Procurement Period, the Market Participant for a Generator must:

5.9.2.2.1 Notify the ISO on or before the first business day of the month prior to the month of the export, specify the quantity of MW in ICAP, and the Control Area that will be entitled to the exported capacity, such notice in accordance with ISO Procedures; and

5.9.2.2.2 Provide all data and other information to the ISO required in accordance with Services Tariff Section 23.4.5.

5.9.2.3 During any month a Generator has Locational Export Capacity, the Market Participant for it shall Bid the Locational Export Capacity into the in-day market when the ISO issues a Supplemental Resource Evaluation request (an SRE), unless the entity has a bid pending in the Real-Time Market when the SRE request is made or is unable to bid in response to the SRE request due to an outage as defined in the ISO Procedures, or due to other operational issues, or due to temperature related deratings.

5.10 NYCA Minimum Installed Capacity Requirement

The NYCA Minimum Installed Capacity Requirement is derived from the NYCA Installed Reserve Margin, which is established each year by the NYSRC. The NYCA Minimum Installed Capacity Requirement for the Capability Year beginning each May 1 will be established by multiplying the NYCA peak Load forecasted by the ISO by the quantity of one plus the NYCA Installed Reserve Margin. The ISO shall translate the NYCA Installed Reserve Margin, and thus the NYCA Minimum Installed Capacity Requirement, into a NYCA Minimum Unforced Capacity Requirement. For each Capability Period, the NYCA Minimum Unforced Capacity Requirement shall equal the product of the NYCA Minimum Installed Capacity Requirement and the ratio of (1) the total amount of Unforced Capacity that the specified Resources are qualified to provide during such Capability Period, as of the time the NYCA Minimum Unforced Capacity Requirement is determined as specified in ISO Procedures, to (2) the sum of the DMNCs used to determine the Unforced Capacities of such Resources for such Capability Period. The foregoing calculation shall be determined using the Resources in the NYCA in the most recent final version of the ISO's annual Load and Capacity Data Report, with the addition of Resources commencing commercial operation since completion of that report and the deletion of Resources with scheduled or planned retirement dates before or during such Capability Period.

The NYCA Minimum Unforced Capacity Requirement represents a minimum level of Unforced Capacity that must be secured by LSEs in the NYCA for each Obligation Procurement Period. Under the provisions of this Services Tariff and the ISO Procedures, each LSE will be obligated to procure its LSE Unforced Capacity Obligation. The LSE Unforced Capacity Obligation will be determined for each Obligation Procurement Period by the ICAP Spot Market

Auction, in accordance with ISO Procedures. Qualified Resources will have the opportunity to supply amounts of Unforced Capacity to meet the LSE Unforced Capacity Obligation as established by the ICAP Spot Market Auction.

The ISO will calculate a NYCA peak Load each year by applying regional Load growth factors to the prior calendar year's Adjusted Actual Peak Load. Regional Load growth factors shall be proposed by the Transmission Owners and reviewed by the ISO pursuant to procedures agreed to by Market Participants and described in the ISO Procedures. Disputes concerning the development of regional Load growth factors shall be resolved through the Expedited Dispute Resolution Procedures set forth in Section 5.17 of this Tariff.

The ISO shall determine the amount of Unforced Capacity that must be sited within the NYCA, and within each Locality, and the amount of Unforced Capacity that may be procured from areas External to the NYCA, in a manner consistent with the Reliability Rules. New Transmission projects to which the NYISO has granted UDRs will not affect the determination by the NYISO of the amount of Unforced Capacity that must be located within the NYCA or within each Locality of the NYCA.

5.11 Requirements Applicable to LSEs

5.11.1 Allocation of the NYCA Minimum Unforced Capacity Requirement

Each Transmission Owner and each municipal electric utility will submit to the ISO, for its review pursuant to mutually agreed upon procedures which shall be described in the ISO Procedures, the weather-adjusted Load within its Transmission District during the hour in which actual Load in the NYCA was highest (the “NYCA peak Load”) for the current Capability Year. (Municipal electric utilities may elect not to submit weather-adjusted data, in which case, weather adjustments shall be performed per ISO procedures. The ISO shall use these data to determine the Adjusted Actual Load at the time of the NYCA peak Load for each Transmission District and municipal electric utility pursuant to ISO Procedures, which shall ensure that transmission losses and the effects of demand reduction programs are treated in a consistent manner and that all weather normalization procedures meet a minimum criterion described in the ISO Procedures. Each Transmission District or municipal electric utility Load forecast coincident with the NYCA peak shall be the product of that Transmission District or municipal electric utility’s Adjusted Actual Load at the time of the NYCA peak Load multiplied by one plus the regional Load growth factor for that Transmission District or municipal electric utility developed pursuant to Section 5.10 of this Tariff. After calculating each Transmission District or municipal electric utility Load forecast, if the ISO determines that an Adjusted Actual Load determined for a Transmission District or municipal electric utility does not reflect reasonable expectations of what Load might reasonably have been expected to occur in that Transmission District or area served by that municipal electric utility in that Capability Year, after taking into consideration the adjustments to account for weather normalization, transmission losses and demand response programs that are described in the ISO Procedures, the ISO Procedures shall

also authorize the ISO to substitute its own measures of Adjusted Actual Load for that Transmission District or area serviced by that municipal electric utility in this calculation, subject to the outcome of dispute resolution procedures if invoked. The ISO's measure of Adjusted Actual Load shall be binding unless otherwise determined as the result of dispute resolution procedures that may be invoked. Each Transmission Owner must also submit aggregate Adjusted Load data, coincident with the NYCA peak hour, for all customers served by each LSE active within its Transmission District. The aggregate Load data may be derived from direct meters or Load profiles of the customers served. Each Transmission Owner shall be required to submit such forecasts and aggregate peak Load data in accordance with the ISO Procedures. Each municipal electric utility may choose to submit its peak Load forecast based on the Transmission District's peak Load forecast provided by a Transmission Owner or to provide its own. Any disputes arising out of the submittals required in this paragraph shall be resolved through the Expedited Dispute Resolution Procedures set forth in Section 5.17 of this Tariff.

All aggregate Load data submitted by a Transmission Owner must be accompanied by documentation indicating that each affected LSE has been provided the data regarding the assignment of customers to the affected LSE. Any disputes between LSEs and Transmission Owners regarding such data or assignments shall be resolved through the Expedited Dispute Resolution Procedures set forth in Section 5.17 of this Tariff, or the Transmission Owner's retail access procedures, as applicable.

The ISO shall allocate the NYCA Minimum Unforced Capacity Requirement among all LSEs serving Load in the NYCA prior to the beginning of each Capability Year. It shall then adjust the NYCA Minimum Unforced Capacity Requirement and reallocate it among LSEs before each Winter Capability Period as necessary to reflect changes in the factors used to

translate ICAP requirements into Unforced Capacity requirements. Each LSE's share of the NYCA Minimum Unforced Capacity Requirement will equal the product of: (i) the NYCA Minimum Installed Capacity Requirement as translated into a NYCA Minimum Unforced Capacity Requirement; and (ii) the ratio of the sum of the Load forecasts coincident with the NYCA peak Load for that LSE's customers in each Transmission District to the NYCA peak Load forecast.

Each LSE Unforced Capacity Obligation will equal the product of (i) the ratio of that LSE's share of the NYCA Minimum Unforced Capacity Requirement to the total NYCA Minimum Unforced Capacity Requirement and (ii) the total of all of the LSE Unforced Capacity Obligations for the NYCA established by the ICAP Spot Market Auction. The LSE Unforced Capacity Obligation will be determined in each Obligation Procurement Period by the ICAP Spot Market Auction, in accordance with the ISO Procedures. Each LSE will be responsible for acquiring sufficient Unforced Capacity to satisfy its LSE Unforced Capacity Obligations. LSEs with Load in more than one Locality will have an LSE Unforced Capacity Obligation for each Locality.

Prior to the beginning of each Capability Period, Transmission Owners shall submit the required Load-shifting information to the ISO and to each LSE affected by the Load-shifting, in accordance with the ISO Procedures. In the event that there is a pending dispute regarding a Transmission Owner's forecast, the ISO shall nevertheless establish each LSE's portion of the NYCA Minimum Unforced Capacity Requirement applicable at the beginning of each Capability Period in accordance with the schedule established in the ISO Procedures, subject to possible adjustments that may be required as a result of resolution of the dispute through the Expedited Dispute Resolution Procedures set forth in Section 5.17 of this Tariff.

Each month, as Transmission Owners report customers gained and lost by LSEs through Load-shifting, the ISO will adjust each LSE's portion of the NYCA Minimum Unforced Capacity Requirement such that (i) the total Transmission District Installed Capacity requirement remains constant and (ii) an individual LSE's allocated portion reflects the gains and losses. If an LSE loses a customer as a result of that customer leaving the Transmission District, the Load-losing LSE shall be relieved of its obligation to procure Unforced Capacity to cover the Load associated with the departing customer as of the date that the customer's departure is accepted by the ISO and shall be free to sell any excess Unforced Capacity. In addition, when a customer leaves the Transmission District, the ISO will adjust each LSE's portion of the NYCA Minimum Unforced Capacity Requirement so that the total Transmission District's share of the NYCA Minimum Unforced Capacity Requirement remains constant.

5.11.2 LSE Obligations

Each LSE must procure Unforced Capacity in an amount equal to its LSE Unforced Capacity Obligation from any Installed Capacity Supplier through Bilateral Transactions with purchases in ISO-administered Installed Capacity auctions, by self-supply from qualified sources, or by a combination of these methods. Each LSE must certify the amount of Unforced Capacity it has or has obtained prior to the beginning of each Obligation Procurement Period by submitting completed Installed Capacity certification forms to the ISO by the date specified in the ISO Procedures. The Installed Capacity certification forms submitted by the LSEs shall be in the format and include all the information prescribed by the ISO Procedures.

All LSEs shall participate in the ICAP Spot Market Auction pursuant to Section 5.14.1 of this Tariff.

5.11.3 Load-Shifting Adjustments

The ISO shall account for Load-shifting among LSEs each month using the best available information provided to it and the affected LSEs by the individual Transmission Owners. The ISO shall, upon notice of Load-shifting by a Transmission Owner and verification by the relevant Load-losing LSE, increase the Load-gaining LSE's LSE Unforced Capacity Obligation, as applicable, and decrease the Load-losing LSE's LSE Unforced Capacity Obligation, as applicable, to reflect the Load-shifting.

The Load-gaining LSE shall pay the Load-losing LSE an amount, pro-rated on a daily basis, based on the Market-Clearing Price of Unforced Capacity determined in the most recent previous applicable ICAP Spot Market Auction until the first day of the month after the nearest following Monthly Installed Capacity Auction is held. The amount paid by a Load-gaining LSE shall reflect any portion of the Load-losing LSE's LSE Unforced Capacity Obligation that is attributable to the shifting Load for the applicable Obligation Procurement Period, in accordance with the ISO Procedures. In addition, the amount paid by a Load-gaining LSE shall be reduced by the Load-losing LSE's share of any rebate associated with the lost Load paid pursuant to Section 5.15 of this Tariff.

Each Transmission Owner shall report to the ISO and to each LSE serving Load in its Transmission District the updated, aggregated LSE Loads with documentation in accordance with and by the date set forth in the ISO Procedures. The ISO shall reallocate a portion of the NYCA Minimum Unforced Capacity Requirement and the Locational Minimum Unforced Capacity Requirement, as applicable, to each LSE for the following Obligation Procurement Period, which shall reflect all documented Load-shifts as of the end of the current Obligation Procurement Period. Any disputes among Market Participants concerning Load-shifting shall be resolved through the Expedited Dispute Resolution Procedures set forth in Section 5.17 of this

Tariff, or the Transmission Owner's retail access procedures, as applicable. In the event of a pending dispute concerning a Load-shift, the ISO shall make its Obligation Procurement Period Installed Capacity adjustments as if the Load-shift reported by the Transmission Owners had occurred, or if the dispute pertains to the timing of a Load-shift, as if the Load-shift occurred on the effective date reported by the Transmission Owner, but will retroactively modify these allocations, as necessary, based on determinations made pursuant to the Expedited Dispute Resolution Procedures set forth in Section 5.17 of this Tariff, or the Transmission Owner's retail access procedures, as applicable.

5.11.4 LSE Locational Minimum Installed Capacity Requirements

The ISO will determine the Locational Minimum Installed Capacity Requirements, stated as a percentage of the Locality's forecasted Capability Year peak Load and expressed in Unforced Capacity terms, that shall be uniformly applicable to each LSE serving Load within a Locality. In establishing Locational Minimum Installed Capacity Requirements, the ISO will take into account all relevant considerations, including the total NYCA Minimum Installed Capacity Requirement, the NYS Power System transmission Interface Transfer Capability, the election by the holder of rights to UDRs that can provide Capacity from an External Control Area with a capability year start date that is different than the corresponding ISO Capability Year start date ("dissimilar capability year"), the Reliability Rules and any other FERC-approved Locational Minimum Installed Capacity Requirements.

The Installed Capacity Supplier holding rights to UDRs from an External Control Area with a dissimilar capability year shall have one opportunity for a Capability Year in which the Scheduled Line will first be used to offer Capacity associated with the UDRs, to elect that the ISO determine Locational Minimum Installed Capacity Requirements without a quantity of MW

from the UDRs for the first month in the Capability Year, and with the same quantity of MW as Unforced Capacity for the remaining months, in each case (a) consistent with and as demonstrated by a contractual arrangement to utilize the UDRs to import the quantity of MW of Capacity into a Locality, and (b) in accordance with ISO Procedures (a “capability year adjustment election”). If there is more than one Installed Capacity Supplier holding rights to UDRs concurrently, an Installed Capacity Supplier’s election pursuant to the preceding sentence (x) shall be binding on the entity to which the NYISO granted the UDRs up to the quantity of MW to which the Installed Capacity Supplier holds rights, and a subsequent assignment of these UDRs to another rights holder will not create the option for another one-time election by the new UDR rights holder, and (y) shall not affect the right another Installed Capacity Supplier may have to make an election. The right to make an election shall remain unless and until an election has been made by one or more holders of rights to the total quantity of MW corresponding to the UDRs. Absent this one-time election, the UDRs shall be modeled consistently for all months in each Capability Year as elected by the UDR rights holder in its notification to the ISO in accordance with ISO Procedures. Upon such an election, the ISO shall determine the Locational Minimum Unforced Capacity Requirement (i) for the first month of the Capability Year without the quantity of MW of Capacity associated with the UDRs, and (ii) for the remaining eleven months as Unforced Capacity. After the Installed Capacity Supplier has made its one-time election for a quantity of MW, the quantity of MW associated with the UDRs held by the Installed Capacity Supplier shall be modeled consistently for all months in any future Capability Period.

The Locational Minimum Unforced Capacity Requirement represents a minimum level of Unforced Capacity that must be secured by LSEs in each Locality in which it has Load for each

Obligation Procurement Period. The Locational Minimum Unforced Capacity Requirement for each Locality shall equal the product of the Locational Minimum Installed Capacity Requirement for a given Locality ([\(A\) with or without the UDRs if there is a capability year adjustment election by a rights holder and \(B\) without the Locality Exchange MW](#)) and the ratio of (1) the total amount of Unforced Capacity that the specified Resources are qualified to provide (with or without the UDRs associated with dissimilar capability periods, as so elected by the rights holder) during each month in the Capability Period, as of the time the Locational Minimum Unforced Capacity Requirement is determined as specified in ISO Procedures, to (2) the sum of the DMNCs used to determine the Unforced Capacities of such Resources for such Capability Period (with or without the DMNCs associated with the UDRs, as so elected by the rights holder).

–The foregoing calculation shall be determined using the Resources in the given Locality in the most recent final version of the ISO’s annual Load and Capacity Data Report, with the addition of Resources commencing commercial operation since completion of that report and the deletion of Resources with scheduled or planned retirement dates before or during such Capability Period. [The ISO will apply the Locality Exchange Factor for the applicable External Control Area to the MW of Locational Export Capacity that are the lesser of \(i\) the lesser of the Generator’s CRIS and its most recent DMNC, and \(ii\) the MW pursuant to the notice provided pursuant to Section 5.9.2.2.1 of this Services Tariff.](#)

Under the provisions of this Services Tariff and the ISO Procedures, each LSE will be obligated to procure its LSE Unforced Capacity Obligation. The LSE Unforced Capacity Obligation will be determined for each Obligation Procurement Period by the ICAP Spot Market Auction, in accordance with the ISO Procedures.

Qualified Resources will have the opportunity to supply amounts of Unforced Capacity to meet the LSE Unforced Capacity Obligation as established by the ICAP Spot Market Auction.

To be counted towards the locational component of the LSE Unforced Capacity Obligation, Unforced Capacity owned by the holder of UDRs or contractually combined with UDRs must be deliverable to the NYCA interface with the UDR transmission facility pursuant to NYISO requirements and consistent with the election of the holder of the rights to the UDRs set forth in this Section.

In addition, any Customer that purchases Unforced Capacity associated with any generation that is subject to capacity market mitigation measures in an ISO-administered auction may not resell that Unforced Capacity in a subsequent auction at a price greater than the annual mitigated price cap, as applied in accordance with the ISO Procedures in accordance with Sections 5.13.2, 5.13.3, and 5.14.1 of this Tariff. The ISO shall inform Customers that purchase Unforced Capacity in an ISO-administered auction of the amount of Unforced Capacity they have purchased that is subject to capacity market mitigation measures.

The ISO shall have the right to audit all executed Installed Capacity contracts and related documentation of arrangements by an LSE to use its own generation to meet its Locational Minimum Installed Capacity Requirement for an upcoming Obligation Procurement Period.

5.11.4.1 Determination of Locality Exchange Factor:

Except for the the Locality Exchange Factor from the G-J Locality to ISO-NE for June 2017 through May 2018, No later than January 31 each year, the ISO shall determine the Locality Exchange Factor for each Import Constrained Locality relative to each neighboring Control Area.

The ISO shall make each such determination by performing a power flow based analysis according to applicable transmission system planning practices for the determination of interface transfer limits used for the resource adequacy topology. Base case data from the most recent reliability planning process will be incorporated. The Locality Exchange Factor is the ratio of the shift factor on the applicable NYCA interface of a transfer from the Import Constrained Locality to the respective neighboring Control Area, to the shift factor of a transfer from Rest of State to the Import Constrained Locality, calculated in accordance with ISO Procedures. Only the AC circuits comprising the respective neighboring Control Area's interface with the NYCA will participate in the shift. The ISO shall post its Locality Exchange Factors on its website prior to the opening of the Summer Capability Period Auction, and notify the New York State Reliability Council.

5.12 Requirements Applicable to Installed Capacity Suppliers

5.12.1 Installed Capacity Supplier Qualification Requirements

In order to qualify as an Installed Capacity Supplier in the NYCA, each generator and merchant transmission facility interconnected to the New York State Transmission System must, commencing with the 2009 Summer Capability Period, have elected Capacity Resource Interconnection Service and been found deliverable, or must have been grandfathered as deliverable, pursuant to the applicable provisions of Attachment X, Attachment Z and Attachment S to the ISO OATT. Even if a Generator has otherwise satisfied the requirements to participate in the ISO's Installed Capacity market, a Generator in Inactive Reserves, an ICAP Ineligible Forced Outage, a Mothball Outage, or that is Retired is ineligible to participate in the ISO's Installed Capacity market. In addition, to qualify as an Installed Capacity Supplier in the NYCA, Energy Limited Resources, Generators, Installed Capacity Marketers, Intermittent Power Resources, Limited Control Run-of-River Hydro Resources and System Resources rated 1 MW or greater, other than External System Resources and Control Area System Resources which have agreed to certain Curtailment conditions as set forth in the last paragraph of Section 5.12.1 below, Responsible Interface Parties, existing municipally-owned generation, Energy Limited Resources, and Intermittent Power Resources, to the extent those entities are subject to the requirements of Section 5.12.11 of this Tariff, shall:

- 5.12.1.1 provide information reasonably requested by the ISO including the name and location of Generators, and System Resources;
- 5.12.1.2 in accordance with the ISO Procedures, perform DMNC tests and submit the results to the ISO, or provide to the ISO appropriate historical production data;
- 5.12.1.3 abide by the ISO Generator maintenance coordination procedures;

- 5.12.1.4 provide the expected return date from any outages (including partial outages) to the ISO;
- 5.12.1.5 in accordance with the ISO Procedures,
 - 5.12.1.5.1 provide documentation demonstrating that it will not use the same Unforced Capacity for more than one (1) buyer at the same time, and
 - 5.12.1.5.2 in the event that the Installed Capacity Supplier supplies more Unforced Capacity than it is qualified to supply in any specific month (*i.e.*, is short on Capacity), documentation that it has procured sufficient Unforced Capacity to cover this shortfall.
- 5.12.1.6 except for Installed Capacity Marketers and Intermittent Power Resources that depend upon wind or solar as their fuel, Bid into the Day-Ahead Market, unless the Energy Limited Resource, Generator, Limited Control Run-of-River Hydro Resource or System Resource is unable to do so due to an outage as defined in the ISO Procedures or due to temperature related de-ratings. Generators may also enter into the MIS an upper operating limit that would define the operating limit under normal system conditions. The circumstances under which the ISO will direct a Generator to exceed its upper operating limit are described in the ISO Procedures;
- 5.12.1.7 provide Operating Data in accordance with Section 5.12.5 of this Tariff;
- 5.12.1.8 provide notice to the ISO, prior to the commencement of the Annual Transmission Reliability Assessment on March 1, of any transfers of deliverability rights to be carried out pursuant to Sections 25.9.4 - 25.9.6 of Attachment S to the ISO OATT;

- 5.12.1.9 comply with the ISO Procedures;
- 5.12.1.10 when the ISO issues a Supplemental Resource Evaluation request (an SRE), Bid into the in-day market unless the entity has a bid pending in the Real-Time Market when the SRE request is made or is unable to bid in response to the SRE request due to an outage as defined in the ISO Procedures, or due to other operational issues, or due to temperature related deratings; and
- 5.12.1.11 Installed Capacity Suppliers located East of Central-East shall Bid in the Day-Ahead and Real-Time Markets all Capacity available for supplying 10-Minute Non-Synchronized Reserve (unless the Generator is unable to meet its commitment because of an outage as defined in the ISO Procedures), except for the Generators described in Subsections 5.12.1.11.1, 5.12.1.11.2 and 5.12.1.11.3 below:
- 5.12.1.11.1 Generators providing Energy under contracts executed and effective on or before November 18, 1999 (including PURPA contracts) in which the power purchasers do not control the operation of the supply source but would be responsible for penalties for being off-schedule, with the exception of Generators under must-take PURPA contracts executed and effective on or before November 18, 1999, who have not provided telemetering to their local TO and historically have not been eligible to participate in the NYPP market, which will continue to be treated as TO Load modifiers under the ISO-administered markets;
- 5.12.1.11.2 Existing topping turbine Generators and extraction turbine Generators producing Energy resulting from the supply of steam to the district steam system located in New York City (LBMP Zone J) in operation on or before November

18, 1999 and/or topping or extraction turbine Generators used in replacing or repowering steam supplies from such units (in accordance with good engineering and economic design) that cannot follow schedules, up to a maximum total of 523 MW of such units; and

5.12.1.11.3 Units that have demonstrated to the ISO that they are subject to environmental, contractual or other legal or physical requirements that would otherwise preclude them from providing 10-Minute NSR.

The ISO shall inform each potential Installed Capacity Supplier that is required to submit DMNC data of its approved DMNC ratings for the Summer Capability Period and the Winter Capability Period in accordance with the ISO Procedures.

Requirements to qualify as Installed Capacity Suppliers for External System Resources and Control Area System Resources located in External Control Areas that have agreed not to Curtail the Energy associated with such Installed Capacity or to afford it the same Curtailment priority that it affords its own Control Area Load shall be established in the ISO Procedures.

External Installed Capacity not associated with UDRs, including capacity associated with External CRIS Rights, Grandfathered External Installed Capacity Agreements listed in Attachment E of the ISO Installed Capacity Manual, the Existing Transmission Capacity for Native Load listed for New York State Electric & Gas Corporation in Table 3 of Attachment L to the ISO OATT, Import Rights, and External System Resources, is only qualified to satisfy a NYCA Minimum Unforced Capacity Requirement and is not eligible to satisfy a Locational Minimum Installed Capacity Requirement.

Not later than 30 days prior to each ICAP Spot Market Auction, each Market Participant that may make offers to sell Unforced Capacity in such auction shall submit information to the

ISO, in accordance with ISO Procedures and in the format specified by the ISO that identifies each Affiliated Entity, as that term is defined in Section 23.2.1 of Attachment H of the Services Tariff, of the Market Party or with which the Market Party is an Affiliated Entity. The names of entities that are Affiliated Entities shall not be treated as Confidential Information, but such treatment may be requested for the existence of an Affiliated Entity relationship. The information submitted to the ISO shall identify the nature of the Affiliated Entity relationship by the applicable category specified in the definition of “Affiliated Entity” in Section 23.2.1 of Attachment H of the Services Tariff.

5.12.2 Additional Provisions Applicable to External Installed Capacity Suppliers

Terms in this Section 5.12.2 not defined in the Services Tariff have the meaning set forth in the OATT.

5.12.2.1 Provisions Addressing the Applicable External Control Area

External Generators, External System Resources, and Control Area System Resources qualify as Installed Capacity Suppliers if they demonstrate to the satisfaction of the NYISO that the Installed Capacity Equivalent of their Unforced Capacity is deliverable to the NYCA or, in the case of an entity using a UDR to meet a Locational Minimum Installed Capacity Requirement, to the NYCA interface associated with that UDR transmission facility and will not be recalled or curtailed by an External Control Area to satisfy its own Control Area Loads, or, in the case of Control Area System Resources, if they demonstrate that the External Control Area will afford the NYCA Load the same curtailment priority that they afford their own Control Area Native Load Customers. The amount of Unforced Capacity that may be supplied by such entities qualifying pursuant to the alternative criteria may be reduced by the ISO, pursuant to ISO Procedures, to reflect the possibility of curtailment. External Installed Capacity associated with

Import Rights or UDRs is subject to the same deliverability requirements applied to Internal Installed Capacity Suppliers associated with UDRs.

5.12.2.2 Additional Provisions Addressing Internal Deliverability and Import Rights

In addition to the provisions contained in Section 5.12.2.1 above, External Installed Capacity not associated with UDRs or External CRIS Rights will be subject to the deliverability test in Section 25.7.8 and 25.7.9 of Attachment S to the ISO OATT. The deliverability of External Installed Capacity not associated with UDRs or External CRIS Rights will be evaluated annually as a part of the process that sets import rights for the upcoming Capability Year, to determine the amount of External Installed Capacity that can be imported to the New York Control Area across any individual External Interface and across all of those External Interfaces, taken together. The External Installed Capacity deliverability test will be performed using the ISO's forecast, for the upcoming Capability Year, of New York Control Area CRIS resources, transmission facilities, and load. Under this process (i) Grandfathered External Installed Capacity Agreements listed in Attachment E of the ISO Installed Capacity Manual, and (ii) the Existing Transmission Capacity for Native Load listed for New York State Electric & Gas Corporation in Table 3 of Attachment L to the ISO OATT, will be considered deliverable within the Rest of State. Additionally, 1090 MW of imports made over the Quebec (via Chateaugay) Interface will be considered to be deliverable until the end of the 2010 Summer Capability Period.

The import limit set for External Installed Capacity not associated with UDRs or External CRIS Rights will be set no higher than the amount of imports deliverable into Rest of State that (i) would not increase the LOLE as determined in the upcoming Capability Year IRM consistent with Section 2.7 of the NYISO Installed Capacity Manual, "Limitations on Unforced Capacity

Flow in External Control Areas,” (ii) are deliverable within the Rest of State Capacity Region when evaluated with the New York Control Area CRIS resources and External CRIS Rights forecast for the upcoming Capability Year, and (iii) would not degrade the transfer capability of any Other Interface by more than the threshold identified in Section 25.7.9 of Attachment S to the ISO OATT. Import limits set for External Installed Capacity will reflect the modeling of awarded External CRIS rights, but the awarded External CRIS rights will not be adjusted as part of import limit-setting process. Procedures for qualifying selling, and delivery of External Installed Capacity are detailed in the Installed Capacity Manual.

Until the grandfathered import rights over the Quebec (via Chateauguay) Interface expire at the end of the 2010 Summer Capability Period, the 1090 MW of grandfathered import rights will be made available on a first-come, first-served basis pursuant to ISO Procedures. Any of the grandfathered import rights over the Quebec (via Chateauguay) Interface not utilized for a Capability Period will be made available to other external resources for that Capability Period, pursuant to ISO Procedures, to the extent the unutilized amount is determined to be deliverable.

Additionally, any of the Existing Transmission Capacity for Native Load listed for New York State Electric & Gas Corporation not utilized by New York State Electric & Gas Corporation for a Capability Period will be made available to other external resources for that Capability Period, pursuant to ISO procedures, to the extent the unutilized amount is determined to be deliverable within the Rest of State Capacity Region.

LSEs with External Installed Capacity as of the effective date of this Tariff will be entitled to designate External Installed Capacity at the same NYCA Interface with another Control Area, in the same amounts in effect on the effective date of this Tariff. To the extent such External Installed Capacity corresponds to Existing Transmission Capacity for Native Load

as reflected in Table 3 of Attachment L to the ISO OATT, these External Installed Capacity rights will continue without term and shall be allocated to the LSE's retail access customers in accordance with the LSE's retail access program on file with the PSC and subject to any necessary filings with the Commission. External Installed Capacity rights existing as of September 17, 1999 that do not correspond to Table 3 of Attachment L to the ISO OATT shall survive for the term of the relevant External Installed Capacity contract or until the relevant External Generator is retired.

5.12.2.3 One-Time Conversion of Grandfathered Quebec (via Chateauguay) Interface Rights.

An entity can request to convert a specified number of MW, up to 1090 MW over the Quebec External Interface (via Chateauguay), into External CRIS Rights by making either a Contract Commitment or Non-Contract Commitment that satisfies the requirements of Section 25.7.11.1 of Attachment S to the ISO OATT. The converted number of MW will not be subject to further evaluation for deliverability within a Class Year Deliverability Study under Attachment S to the ISO OATT, as long as the External CRIS Rights are in effect.

5.12.2.3.1 The External CRIS Rights awarded under this conversion process will first become effective for the 2010-2011 Winter Capability Period.

5.12.2.3.2 Requests to convert these grandfathered rights must be received by the NYISO on or before 5:00 pm Eastern Time on February 1, 2010, with the following information: (a) a statement that the entity is electing to convert by satisfying the requirements of a Contract Commitment or a Non-Contract Commitment in accordance with Section 25.7.11.1 of Attachment S to the ISO OATT; (b) the length of the commitment in years; (c) for the Summer Capability Period, the requested number of MW; (d) for the Winter Capability Period, the

Specified Winter Months, if any, and the requested number of MW; and (e) a minimum number of MW the entity will accept if granted (“Specified Minimum”) for the Summer Capability Period and for all Specified Winter Months, if any.

5.12.2.3.3 An entity cannot submit one or more requests to convert in the aggregate more than 1090 MW in any single month.

5.12.2.3.4 If requests to convert that satisfy all other requirements stated herein are equal to or less than the 1090 MW limit, all requesting entities will be awarded the requested number of MW of External CRIS Rights. If conversion requests exceed the 1090 MW limit, the NYISO will prorate the allocation based on the weighted average of the requested MW times the length of the contract/commitment (*i.e.*, number of Summer Capability Periods) in accordance with the following formula:

$$\begin{aligned} & \text{Rights allocated to entity } i \\ & = 1090 \\ & \quad * (MW_i * \text{contract/commitment length}_i) \\ & \quad / \sum_j (MW_j * \text{contract/commitment length}_j) \end{aligned}$$

$j = 1, \dots, \#$ entities requesting import rights

In the formula, contract/commitment length means the lesser of the requested contract/commitment length and twenty (20) years. The NYISO will perform separate calculations for the Summer and Winter Capability Periods. The NYISO will determine whether the prorated allocated number of MW for any requesting entity is less than the entity’s Specified Minimum. If any allocation is less, the NYISO will remove such request(s) and recalculate the prorated allocations among the remaining requesting entities using the above formula. This process

will continue until the prorated allocation meets or exceeds the specified minimum for all remaining requests.

- 5.12.2.3.5 Any portion of the previously grandfathered 1090 MW not converted through this process will no longer be grandfathered from deliverability. Previously grandfathered rights converted to External CRIS Rights but then terminated will no longer be grandfathered from deliverability.

5.12.2.4 Offer Cap Applicable to Certain External CRIS Rights

Notwithstanding any other capacity mitigation measures or obligations that may apply, the offers of External Installed Capacity submitted pursuant to a Non-Contract Commitment, as described in Section 25.7.11.1.2 of Attachment S of the ISO OATT, will be subject to an offer cap in each month of the Summer Capability Period and for all Specified Winter Months. This offer cap will be determined as the higher of:

- 5.12.2.4.1 1.1 times the price corresponding to all available Unforced Capacity determined from the NYCA ICAP Demand Curve for that Period; and

- 5.12.2.4.2 The most recent auction clearing price (a) in the External market supplying the External Installed Capacity, if any, and if none, then the most recent auction clearing price in an External market to which the capacity may be wheeled, less (b) any transmission reservation costs in the External market associated with providing the Installed Capacity, in accordance with ISO Procedures.

5.12.3 Installed Capacity Supplier Outage Scheduling Requirements

All Installed Capacity Suppliers, except for Control Area System Resources and Responsible Interface Parties, that intend to supply Unforced Capacity to the NYCA shall submit

a confidential notification to the ISO of their proposed outage schedules in accordance with the ISO Procedures. Transmission Owners will be notified of these and subsequently revised outage schedules. Based upon a reliability assessment, if Operating Reserve deficiencies are projected to occur in certain weeks for the upcoming calendar year, the ISO will request voluntary rescheduling of outages. In the case of Generators actually supplying Unforced Capacity to the NYCA, if voluntary rescheduling is ineffective, the ISO will invoke forced rescheduling of their outages to ensure that projected Operating Reserves over the upcoming year are adequate.

A Generator that refuses a forced rescheduling of its outages for any unit shall be prevented from supplying Unforced Capacity in the NYCA with that unit during any month where it undertakes such outages. The rescheduling process is described in the ISO Procedures.

A Generator that intends to supply Unforced Capacity in a given month that did not qualify as an Installed Capacity Supplier prior to the beginning of the Capability Period must notify the ISO in accordance with the ISO Procedures so that it may be subject to forced rescheduling of its proposed outages in order to qualify as an Installed Capacity Supplier. A Supplier that refuses the ISO's forced rescheduling of its proposed outages shall not qualify as an Installed Capacity Supplier for that unit for any month during which it schedules or conducts an outage.

Outage schedules for External System Resources and Control Area System Resources shall be coordinated by the External Control Area and the ISO in accordance with the ISO Procedures.

5.12.4 Required Certification for Installed Capacity

- (a) Each Installed Capacity Supplier must confirm to the ISO, in accordance with ISO Procedures that the Unforced Capacity it has certified has not been sold for

use in an External Control Area.

- (b) Each Installed Capacity Supplier holding rights to UDRs from an External Control Area must confirm to the ISO, in accordance with ISO Procedures, that it will not use as self-supply or offer, and has not sold, Installed Capacity associated with the quantity of MW for which it has not made its one time capability adjustment year election pursuant to Section 5.11.4.

5.12.5 Operating Data Reporting Requirements

To qualify as Installed Capacity Suppliers in the NYCA, Resources shall submit to the ISO Operating Data in accordance with this Section 5.12.5 and the ISO Procedures. Resources that do not submit Operating Data in accordance with the following subsections and the ISO Procedures may be subject to the sanctions provided in Section 5.12.12.1 of this Tariff.

Resources that were not in operation on January 1, 2000 shall submit Operating Data to the ISO no later than one month after such Resources commence commercial operation, and in accordance with the ISO Procedures and the following subsections as applicable.

5.12.5.1 Generators, System Resources, Energy Limited Resources, Responsible Interface Parties, Intermittent Power Resources, Limited Control Run-of-River Hydro Resources and Municipally Owned Generation

To qualify as Installed Capacity Suppliers in the NYCA, Generators, External Generators, System Resources, External System Resources, Energy Limited Resources, Responsible Interface Parties, Intermittent Power Resources, Limited Control Run-of-River Hydro Resources and municipally owned generation or the purchasers of Unforced Capacity associated with those Resources shall submit GADS Data, data equivalent to GADS Data, or other Operating Data to the ISO in accordance with the ISO Procedures. Prior to the successful implementation of a software modification that allows gas turbines to submit multiple bid points,

these units shall not be considered to be forced out for any hours that the unit was available at its base load capability in accordance with the ISO Procedures. This section shall also apply to any Installed Capacity Supplier, External or Internal, using UDRs to meet Locational Minimum Installed Capacity Requirements.

5.12.5.2 Control Area System Resources

To qualify as Installed Capacity Suppliers in the NYCA, Control Area System Resources, or the purchasers of Unforced Capacity associated with those Resources, shall submit CARL Data and actual system failure occurrences data to the ISO each month in accordance with the ISO Procedures.

5.12.5.3 Transmission Projects Granted Unforced Capacity Deliverability Rights

An owner of a transmission project that receives UDRs must, among other obligations, submit outage data or other operational information in accordance with the ISO procedures to allow the ISO to determine the number of UDRs associated with the transmission facility.

5.12.6 Operating Data Default Value and Collection

5.12.6.1 UCAP Calculations

The ISO shall calculate for each Resource the amount of Unforced Capacity that each Installed Capacity Supplier is qualified to supply in the NYCA in accordance with formulae provided in the ISO Procedures.

The amount of Unforced Capacity that each Generator, System Resource, Energy Limited Resource, Special Case Resource, and municipally-owned generation is authorized to supply in the NYCA shall be based on the ISO's calculations of individual Equivalent Demand Forced Outage Rates. The amount of Unforced Capacity that each Control Area System

Resource is authorized to supply in the NYCA shall be based on the ISO's calculation of each Control Area System Resource's availability. The amount of Unforced Capacity that each Intermittent Power Resource is authorized to supply in the NYCA shall be based on the NYISO's calculation of the amount of capacity that the Intermittent Power Resource can reliably provide during system peak Load hours in accordance with ISO Procedures. Except as provided in Section 5.12.6.1.1 of this Services Tariff, this calculation shall not include hours in any month that the Intermittent Power Resource was in an outage state that started on or after May 1, 2015 and that precluded its eligibility to participate in the Installed Capacity market. The amount of Unforced Capacity that each Limited Control Run-of-River Hydro Resource is authorized to provide in the NYCA shall be determined separately for Summer and Winter Capability Periods as the rolling average of the hourly net Energy provided by each such Resource during the 20 highest NYCA integrated real-time load hours in each of the five previous Summer or Winter Capability Periods, as appropriate, stated in megawatts. Except as provided in Section 5.12.6.1.1 of this Services Tariff, for a Limited Control Run-of-River Hydro Resource in an outage state that started on or after May 1, 2015 and that precluded its eligibility to participate in the Installed Capacity market during one of the 20 highest NYCA integrated real-time load hours in any one of the five previous Summer or Winter Capability Periods, the ISO shall replace that Winter or Summer Capability Period, as appropriate, with the next most recent Winter or Summer Capability Period such that the rolling average of the hourly net Energy provided by each such Resource shall be calculated from the 20 highest NYCA integrated real-time load hours in the five most recent prior Summer or Winter Capability Periods in which the Resource was not in an outage state that precluded its eligibility to participate in the Installed Capacity market on one of the 20 highest NYCA integrated real-time load hours in that Capability Period.

The ISO shall calculate separate Summer and Winter Capability Period Unforced Capacity values for each Generator, System Resource, Special Case Resource, Energy Limited Resource, and municipally owned generation and update them periodically using a twelve-month calculation in accordance with formulae provided in the ISO Procedures; provided, however, except as provided in Section 5.12.6.1.1 of this Services Tariff, for a Generator in an outage state that started on or after May 1, 2015 and that precluded its eligibility to participate in the Installed Capacity market at any time during any month from which GADS or other operating data would otherwise be used to calculate an individual Equivalent Demand Forced Outage Rate, the ISO shall replace such month's GADS or other operating data with GADS or other operating data from the most recent prior month in which the Generator was not in an outage state that precluded its eligibility to participate in the Installed Capacity market.

The ISO shall calculate separate Summer and Winter Capability Period Unforced Capacity values for Intermittent Power Resources and update them seasonally as described in ISO Procedures.

5.12.6.1.1 Exceptions

A Generator returning to the Energy market after taking an outage that precluded its participation in the Installed Capacity market and which returns with modifications to its operating characteristics determined by the ISO to be material and which, therefore, requires the submission of a new Interconnection Request will receive, as the initial derating factor for calculation of the Generator's Unforced Capacity upon its return to service, the derating factor it would have received as a newly connecting unit in lieu of a derating factor developed from unit-specific data. A Generator returning to the Energy market after taking an outage that precluded its participation in the Installed Capacity market and which, upon its return, uses as its primary

fuel a fuel not previously used at the facility for any purpose other than for ignition purposes will receive, as the initial derating factor for calculation of the Generator's Unforced Capacity upon its return to service, the NERC class average derating factor in lieu of a derating factor developed from unit-specific data even if the modifications to allow use of a new primary fuel are not material and do not require the submission of a new Interconnection Request.

This Section 5.12.6.1.1 shall apply to a Generator returning to the Energy market after taking an outage that started on or after May 1, 2015 and that precluded its participation in the Installed Capacity market.

5.12.6.2 Default Unforced Capacity

In its calculation of Unforced Capacity, the ISO shall deem a Resource to be completely forced out for each month for which the Resource has not submitted its Operating Data in accordance with Section 5.12.5 of this Tariff and the ISO Procedures. A Resource that has been deemed completely forced out for a particular month may submit new Operating Data, for that month, to the ISO at any time. The ISO will use such new Operating Data when calculating, in a timely manner in accordance with the ISO Procedures, a Unforced Capacity value for the Resource.

Upon a showing of extraordinary circumstances, the ISO retains the discretion to accept at any time Operating Data which have not been submitted in a timely manner, or which do not fully conform with the ISO Procedures.

5.12.6.3 Exception for Certain Equipment Failures

When a Generator, Special Case Resource, Energy Limited Resource, or System Resource is forced into an outage by an equipment failure that involves equipment located on the high voltage side of the electric network beyond the step-up transformer, and including such

step-up transformer, the outage will not be counted for purposes of calculating that Resource's Equivalent Demand Forced Outage Rate.

5.12.7 Availability Requirements

Subsequent to qualifying, each Installed Capacity Supplier shall, except as noted in Section 5.12.11 of this Tariff, on a daily basis: (i) schedule a Bilateral Transaction; (ii) Bid Energy in each hour of the Day-Ahead Market in accordance with the applicable provisions of Section 5.12.1 of this Tariff; or (iii) notify the ISO of any outages. The total amount of Energy that an Installed Capacity Supplier schedules, bids, or declares to be unavailable on a given day must equal or exceed the Installed Capacity Equivalent of the Unforced Capacity it supplies.

5.12.8 Unforced Capacity Sales

Each Installed Capacity Supplier will, after satisfying the deliverability requirements set forth in the applicable provisions of Attachment X, Attachment Z and Attachment S to the ISO OATT, be authorized to supply an amount of Unforced Capacity during each Obligation Procurement Period, based on separate seasonal Unforced Capacity calculations performed by the ISO for the Summer and Winter Capability Periods. Unforced Capacity may be sold in six-month strips, or in monthly, or multi-monthly segments.

External Unforced Capacity (except External Installed Capacity associated with UDRs) may only be offered into Capability Period Auctions or Monthly Auctions for the Rest of State, and ICAP Spot Market Auctions for the NYCA, and may not be offered into a Locality for an ICAP Auction. Bilateral Transactions which certify External Unforced Capacity using Import Rights may not be used to satisfy a Locational Minimum Unforced Capacity Requirement.

If an Energy Limited Resource's, Generator's, System Resource's or Control Area System Resource's DMNC rating is determined to have increased during an Obligation

Procurement Period, pursuant to testing procedures described in the ISO Procedures, the amount of Unforced Capacity that it shall be authorized to supply in that or future Obligation

Procurement Periods shall also be increased on a prospective basis in accordance with the schedule set forth in the ISO Procedures provided that it first has satisfied the deliverability requirements set forth in the applicable provisions of Attachment X, Attachment Z and Attachment S to the ISO OATT.

New Generators and Generators that have increased their Capacity since the previous Summer Capability Period due to changes in their generating equipment may, after satisfying the deliverability requirements set forth in the applicable provisions of Attachment X, Attachment Z and Attachment S to the ISO OATT, qualify to supply Unforced Capacity on a foregoing basis during the Summer Capability Period based upon a DMNC test that is performed and reported to the ISO after March 1 and prior to the beginning of the Summer Capability Period DMNC Test Period. The Generator will be required to verify the claimed DMNC rating by performing an additional test during the Summer DMNC Test Period. Any shortfall between the amount of Unforced Capacity supplied by the Generator for the Summer Capability Period and the amount verified during the Summer DMNC Test Period will be subject to deficiency charges pursuant to Section 5.14.2 of this Tariff. The deficiency charges will be applied to no more than the difference between the Generator's previous Summer Capability Period Unforced Capacity and the amount of Unforced Capacity equivalent the Generator supplied for the Summer Capability Period.

New Generators and Generators that have increased their Capacity since the previous Winter Capability Period due to changes in their generating equipment may, after satisfying the deliverability requirements set forth in the applicable provisions of Attachment X, Attachment Z

and Attachment S to the ISO OATT, qualify to supply Unforced Capacity on a foregoing basis during the Winter Capability Period based upon a DMNC test that is performed and reported to the ISO after September 1 and prior to the beginning of the Winter Capability Period DMNC Test Period. The Generator will be required to verify the claimed DMNC rating by performing an additional test during the Winter Capability Period DMNC Test Period. Any shortfall between the amount of Unforced Capacity certified by the Generator for the Winter Capability Period and the amount verified during the Winter Capability Period DMNC Test Period will be subject to deficiency charges pursuant to Section 5.14.2 of this Tariff. The deficiency charges will be applied to no more than the difference between the Generator's previous Winter Capability Period Unforced Capacity and the amount of Unforced Capacity equivalent the Generator supplied for the Winter Capability Period.

Any Installed Capacity Supplier, except as noted in Section 5.12.11 of this ISO Services Tariff, which fails on a daily basis to schedule, Bid, or declare to be unavailable in the Day-Ahead Market an amount of Unforced Capacity, expressed in terms of Installed Capacity Equivalent, that it certified for that day, rounded down to the nearest whole MW, is subject to sanctions pursuant to Section 5.12.12.2 of this Tariff. If an entity other than the owner of an Energy Limited Resource, Generator, System Resource, or Control Area System Resource that is providing Unforced Capacity is responsible for fulfilling bidding, scheduling, and notification requirements, the owner and that entity must designate to the ISO which of them will be responsible for complying with the scheduling, bidding, and notification requirements. The designated bidding and scheduling entity shall be subject to sanctions pursuant to Section 5.12.12.2 of this ISO Services Tariff.

5.12.9 Sales of Unforced Capacity by System Resources

Installed Capacity Suppliers offering to supply Unforced Capacity associated with Internal System Resources shall submit for each of their Resources the Operating Data and DMNC testing data or historical data described in Sections 5.12.1 and 5.12.5 of this ISO Services Tariff in accordance with the ISO Procedures. Such Installed Capacity Suppliers will be allowed to supply the amount of Unforced Capacity that the ISO determines pursuant to the ISO Procedures to reflect the appropriate Equivalent Demand Forced Outage Rate. Installed Capacity Suppliers offering to sell the Unforced Capacity associated with System Resources may only aggregate Resources in accordance with the ISO Procedures.

5.12.10 Curtailment of External Transactions In-Hour

All Unforced Capacity that is not out of service, or scheduled to serve the Internal NYCA Load in the Day-Ahead Market may be scheduled to supply Energy for use in External Transactions provided, however, that such External Transactions shall be subject to Curtailment within the hour, consistent with ISO Procedures. Such Curtailment shall not exceed the Installed Capacity Equivalent committed to the NYCA.

5.12.11 Responsible Interface Parties, Municipally-Owned Generation, Energy Limited Resources and Intermittent Power Resources

5.12.11.1 Responsible Interface Parties

Responsible Interface Parties may qualify as Installed Capacity Suppliers, without having to comply with the daily bidding, scheduling, and notification requirements set forth in Section 5.12.7 of this Tariff, if their Special Case Resources are available to operate at the direction of the ISO in order to reduce Load from the NYS Transmission System and/or the distribution system for a minimum of four (4) consecutive hours each day, except for those

subject to operating limitations established by environmental permits, which will not be required to operate in excess of two (2) hours and which will be derated by the ISO pursuant to ISO Procedures to account for the Load serving equivalence of the hours actually available, following notice of the potential need to operate twenty-one (21) hours in advance if notification is provided by 3:00 P.M. ET, or twenty-four (24) hours in advance otherwise, and a notification to operate two (2) hours ahead. In order for a Responsible Interface Party to enroll an SCR that uses an eligible Local Generator, any amount of generation that can reduce Load from the NYS Transmission System and/or distribution system at the direction of the ISO that was produced by the Local Generator during the hour coincident with the NYCA or Locality peaks, upon which the LSE Unforced Capacity Obligation of the LSE that serves that SCR is based, must be accounted for when the LSE's Unforced Capacity Obligation for the upcoming Capability Year is established. Responsible Interface Parties must provide this generator data in accordance with ISO Procedures so that the ISO can adjust upwards the LSE Unforced Capacity Obligation to prevent double-counting.

Responsible Interface Parties supplying Unforced Capacity cannot offer the Demand Reduction associated with such Unforced Capacity in the Emergency Demand Response Program. A Resource with sufficient metering to distinguish MWs of Demand Reduction may participate as a Special Case Resource and in the Emergency Demand Response Program provided that the same MWs are not committed both as Unforced Capacity and to the Emergency Demand Response Program.

The ISO will have discretion, pursuant to ISO Procedures, to exempt Local Generators that are incapable of starting in two (2) hours from the requirement to operate on two (2) hours notification. Local Generators that can be operated to reduce Load from the NYS Transmission

System and/or distribution system at the direction of the ISO and Loads capable of being interrupted upon demand, that are not available on certain hours or days will be derated by the ISO, pursuant to ISO Procedures, to reflect the Load serving equivalence of the hours they are actually available.

Responsible Interface Parties must submit a Minimum Payment Nomination, in accordance with ISO Procedures. The ISO may request Special Case Resource performance from less than the total number of Special Case Resources within the NYCA or a Load Zone in accordance with ISO Procedures.

Local Generators that can be operated to reduce Load from the NYS Transmission System and/or distribution system at the direction of the ISO and Loads capable of being interrupted upon demand will be required to comply with verification and validation procedures set forth in the ISO Procedures. Such procedures will not require metering other than interval billing meters on customer Load or testing other than DMNC or sustained disconnect, as appropriate, unless agreed to by the customer, except that Special Case Resources not called to supply Energy in a Capability Period will be required to run a test once every Capability Period in accordance with the ISO Procedures.

Unforced Capacity supplied in a Bilateral Transaction by a Special Case Resource pursuant to this subsection may only be resold if the purchasing entity or the Installed Capacity Marketer has agreed to become a Responsible Interface Party and comply with the ISO notification requirements for Special Case Resources. LSEs and Installed Capacity Marketers may become Responsible Interface Parties and aggregate Special Case Resources and sell the Unforced Capacity associated with them in an ISO-administered auction if they comply with ISO notification requirements for Special Case Resources.

Responsible Interface Parties that were requested to reduce Load in any month shall submit performance data to the NYISO, within 75 days of each called event or test, in accordance with ISO Procedures. Failure by a Responsible Interface Party to submit performance data for any Special Case Resources required to respond to the event or test within the 75-day limit will result in zero performance attributed to those Special Case Resources for purposes of satisfying the Special Case Resource's capacity obligation as well as for determining energy payments. All performance data are subject to audit by the NYISO and its market monitoring unit. If the ISO determines that it has made an erroneous payment to a Responsible Interface Party, the ISO shall have the right to recover it either by reducing other payments to that Responsible Interface Parties or by resolving the issue pursuant to other provisions of this Services Tariff or other lawful means.

Provided the Responsible Interface Party supplies evidence of such reductions in 75 days, the ISO shall pay the Responsible Interface Party that, through their Special Case Resources, caused a verified Load reduction in response to (i) an ISO request to perform due to a forecast reserve shortage (ii) an ISO declared Major Emergency State, (iii) an ISO request to perform made in response to a request for assistance for Load relief purposes or as a result of a Local Reliability Rule, or (iv) a test called by the ISO, for such Load reduction, in accordance with ISO Procedures. Subject to performance evidence and verification, in the case of a response pursuant to clauses (i), (ii), of (iii) of this subsection, Suppliers that schedule Responsible Interface Parties shall be paid the zonal Real-Time LBMP for the period of requested performance or four (4) hours, whichever is greater, in accordance with ISO Procedures; provided, however, Special Case Resource Capacity shall settle Demand Reductions, in the interval and for the capacity for which Special Case Resource Capacity has been scheduled Day-Ahead to provide Operating

Reserves, Regulation Service or Energy, as being provided by a Supplier of Operating Reserves, Regulation Service or Energy.

In the event that a Responsible Interface Party's Minimum Payment Nomination for a Special Case Resource, for the number of hours of requested performance or the minimum four (4) hour period, whichever is greater, exceeds the LBMP revenue received, the Special Case Resource will be eligible for a Bid Production Cost Guarantee to make up the difference, in accordance with Section 4.23 of this Services Tariff and ISO Procedures; provided, however, the ISO shall set to zero the Minimum Payment Nomination for Special Case Resource Capacity in each interval in which such Capacity was scheduled Day-Ahead to provide Operating Reserves, Regulation Service or Energy. Subject to performance evidence and verification, in the case of a response pursuant to clause (iv) of this subsection, payment for participation in tests called by the ISO shall be equal to the zonal Real Time LBMP for the MWh of Energy reduced within the test period.

Transmission Owners that require assistance from enrolled Local Generators larger than 100 kW and Loads capable of being interrupted upon demand for Load relief purposes or as a result of a Local Reliability Rule, shall direct their requests for assistance to the ISO for implementation consistent with the terms of this section. Within Load Zone J, participation in response to an ISO request to perform made as a result of a request for assistance from a Transmission Owner for less than the total number of Special Case Resources, for Load relief purposes or as a result of a Local Reliability Rule, in accordance with ISO Procedures, shall be voluntary and the responsiveness of the Special Case Resource shall not be taken into account for performance measurement.

5.12.11.1.1 Special Case Resource Average Coincident Load

The ISO must receive from the Responsible Interface Party that enrolls a Special Case Resource, the applicable metered Load data required to calculate an ACL for that SCR as provided below and in accordance with ISO Procedures. The ACL shall be computed using the metered Load for the applicable Capability Period SCR Load Zone Peak Hours that indicates the Load consumed by each SCR that is supplied by the NYS Transmission System and/or distribution system and is exclusive of any generation produced by a Local Generator, other behind-the-meter generator, or other supply source located behind the SCR's meter, that served some of the SCR's Load.

Beginning with the Winter 2011-2012 Capability Period and thereafter, the ISO shall use the average of the highest twenty (20) one-hour peak Loads of the SCR taken from the Load data reported for the Capability Period SCR Load Zone Peak Hours during the Prior Equivalent Capability Period, and taking into account the resource's reported verified Load reduction in a Transmission Owner's demand response program in hours coincident with any of these hours, to create a SCR ACL baseline. In addition, beginning with the Summer 2014 Capability Period, the resource's verified Load reduction in either of the ISO's economic demand response programs (the Day Ahead Demand Response Program and the Demand Side Ancillary Services Program) in hours coincident with any of the applicable Capability Period SCR Load Zone Peak Hours will be taken into account when creating the SCR ACL. For the Day Ahead Demand Response Program, the verified Load reduction that occurred in response to a DADRP schedule shall be added to the Capability Period SCR Load Zone Peak Hour for which the reduction in response to a DADRP schedule occurred. For the Demand Side Ancillary Services Program, the Load value to be used in calculating the ACL for each hour during the Capability Period SCR Load Zone Peak Hours in which a non-zero Base Point Signal the ISO provides to the resource, shall be the

greater of (a) the DSASP Baseline MW value in the interval immediately preceding the first non-zero Base Point Signal in the Capability Period SCR Load Zone Peak Hour and (b) the metered Load of the resource as reported by the RIP for the Capability Period SCR Load Zone Peak Hour. When the non-zero Base Point Signal dispatch of a DSASP resource begins in one hour and continues into consecutive hours, and the consecutive hour is identified as being a Capability Period SCR Load Zone Peak Hour, the DSASP Baseline MW value in effect at the beginning of the dispatch of the non-zero Base Point Signal shall be the MW value used for purposes of determining the applicable Load value for that Capability Period SCR Load Zone Peak Hour, in accordance with the preceding sentence. The ISO will post to its website the Capability Period SCR Load Zone Peak Hours for each zone ninety (90) days prior to the beginning of the Capability Period for which the ACL will be in effect.

In the SCR enrollment file uploaded by the RIP each month within the Capability Period, among other required information, the RIP shall provide the SCR's metered Load values for the applicable Capability Period SCR Load Zone Peak Hours necessary to compute the ACL for each SCR.

The exception to this requirement to report the required metered Load data for the ACL, when enrolling a SCR prior to the Summer 2014 Capability Period, is if (i) the SCR has not previously been enrolled with the ISO and (ii) never had interval metering Load data for each month in the Prior Equivalent Capability Period needed to compute the SCR's ACL. Beginning with the Summer 2014 Capability Period, the exception to this requirement to report the required metered Load data for the ACL, is dependent upon one or more of the eligibility conditions for SCR enrollment with a Provisional ACL provided in Section 5.12.11.1.2 of this Services Tariff and ISO Procedures. For SCRs that meet the criteria to enroll with a Provisional ACL, the ISO

must receive from the RIP a Provisional ACL as provided in Section 5.12.11.1.2 of this Services Tariff and in accordance with ISO Procedures.

Beginning with the Summer 2014 Capability Period, in addition to the requirement for RIPs to report each SCR's metered Load values that occurred during the Capability Period SCR Load Zone Peak Hours, in accordance with this Services Tariff and ISO Procedures during the enrollment process, any qualifying increase in a SCR's Load that will be supplied by the NYS Transmission System and/or distribution system may be reported as an Incremental ACL, subject to the limitations and verification reporting requirements provided in Section 5.12.11.1.5 of this Services Tariff and in accordance with ISO Procedures. Incremental ACL values must be reported using the required enrollment file that may be uploaded by the RIP during each month's enrollment period. RIPs may not report Incremental ACL values for any SCRs that are enrolled in the Capability Period with a Provisional ACL.

A reduction in a SCR's Load that is supplied by the NYS Transmission System and/or distribution system and meets the criteria for a SCR Change of Status must be reported as a SCR Change of Status as provided by Section 5.12.11.1.3 of this Services Tariff and in accordance with ISO Procedures.

The ACL is the basis for the upper limit of ICAP, except in circumstances when the SCR has reported a SCR Change of Status or reported an Incremental ACL pursuant to Sections 5.12.11.1.3 and 5.12.11.1.5 of this Services Tariff. The basis for the upper limit of ICAP for a SCR that has experienced a SCR Change of Status or reported an Incremental ACL shall be the Net ACL.

5.12.11.1.2 Use of a Provisional Average Coincident Load

Prior to the Summer 2014 Capability Period, as provided in Section 5.12.11.1.1 of this

Services Tariff, if a new Special Case Resource has not previously been enrolled with the ISO and never had interval billing meter data from the Prior Equivalent Capability Period, its Installed Capacity value shall be its Provisional Average Coincident Load for the Capability Period for which the new SCR is enrolled. The Provisional ACL may be applicable to a new SCR for a maximum of three (3) consecutive Capability Periods, beginning with the Capability Period in which the SCR is first enrolled.

Beginning with the Summer 2014 Capability Period, a SCR may be enrolled using a Provisional ACL in lieu of an ACL when one of the following conditions has been determined by the ISO to apply: (i) the SCR has not previously been enrolled with the ISO for the seasonal Capability Period for which the SCR enrollment with a Provisional ACL is intended, (ii) the SCR was enrolled with a Provisional ACL in the Prior Equivalent Capability Period and was required to report fewer than twenty (20) hours of metered Load verification data that correspond with the Capability Period SCR Load Zone Peak Hours based on the meter installation date of the SCR, (iii) the RIP attempting to enroll the SCR with a Provisional ACL is not the same RIP that enrolled the SCR in the Prior Equivalent Capability Period and interval billing meter data for the SCR from the Prior Equivalent Capability Period is not obtainable by the enrolling RIP and not available to be provided to the enrolling RIP by the ISO. The Provisional ACL may be applicable to a SCR for a maximum of three (3) consecutive Capability Periods when enrolled with the same RIP, beginning with the Capability Period in which the SCR is first enrolled by the RIP.

A SCR enrolled in the Capability Period with a Provisional ACL may not be enrolled by another RIP for the remainder of the Capability Period and the Provisional ACL value shall apply to the resource for the entire Capability Period for which the value is established.

The Provisional ACL is the RIP's forecast of the SCR's ACL and shall be the basis for the upper limit of ICAP for which the RIP may enroll the SCR during the Capability Period.

Any SCR enrolled with a Provisional ACL shall be subject to actual in-period verification. A Verified ACL shall be calculated by the ISO using the top twenty (20) one-hour peak Loads reported for the SCR from the Capability Period SCR Load Zone Peak Hours that are applicable to verify the Provisional ACL in accordance with ISO Procedures and taking into account the resource's reported verified Load reductions in a Transmission Owner's demand response program that are coincident with any of the applicable Capability Period SCR Load Zone Peak Hours. In addition, beginning with the Summer 2014 Capability Period, the resource's verified Load reduction in either of the ISO's economic demand response programs (the Day Ahead Demand Response Program and the Demand Side Ancillary Services Program) in hours coincident with any of the applicable Capability Period SCR Load Zone Peak Hours will be taken into account when creating the SCR Verified ACL. For the Day Ahead Demand Response Program, the verified Load reduction that occurred in response to a DADRP schedule shall be added to the Capability Period SCR Load Zone Peak Hour for which the reduction in response to a DADRP schedule occurred. For the Demand Side Ancillary Services Program, the Load value to be used in calculating the Verified ACL for each hour during the Capability Period SCR Load Zone Peak Hours in which a non-zero Base Point Signal the ISO provides to the resource, shall be the greater of (a) the DSASP Baseline MW value in the interval immediately preceding the first non-zero Base Point Signal in the Capability Period SCR Load Zone Peak Hour and (b) the metered Load of the resource as reported by the RIP for the Capability Period SCR Load Zone Peak Hour. When the non-zero Base Point Signal dispatch of a DSASP resource begins in one hour and continues into consecutive hours, and the consecutive hour is

identified as being a Capability Period SCR Load Zone Peak Hour, the DSASP Baseline MW value in effect at the beginning of the dispatch of the non-zero Base Point Signal shall be the MW value used for purposes of determining the applicable Load value for that Capability Period SCR Load Zone Peak Hour, in accordance with the preceding sentence.

Following the Capability Period for which a resource with a Provisional ACL was enrolled, the RIP shall provide to the ISO the metered Load data required to compute the Verified ACL of the resource. The ISO shall compare the Provisional ACL to the Verified ACL to determine, after applying the applicable performance factor, whether the UCAP of the SCR had been oversold and whether a shortfall has occurred as provided under Section 5.14.2 of this Services Tariff. If the RIP fails to provide verification data required to compute the Verified ACL of the resource enrolled with a Provisional ACL by the deadline: (a) the Verified ACL of the resource shall be set to zero for each Capability Period in which the resource with a Provisional ACL was enrolled and verification data was not reported, and (b) the RIP may be subject to penalties in accordance with this Services Tariff.

5.12.11.1.3 Reporting a SCR Change of Load or SCR Change of Status

5.12.11.1.3.1 SCR Change of Load

The Responsible Interface Party shall report any SCR Change of Load in accordance with ISO Procedures. The RIP is required to document the SCR Change of Load and when the total Load reduction for SCRs that have a SCR Change of Load within the same Load Zone is greater than or equal to 5 MWs, the RIP shall report the SCR Change of Load for each SCR in accordance with ISO Procedures.

5.12.11.1.3.2 SCR Change of Status

The Responsible Interface Party shall report any SCR Change of Status in accordance

with ISO Procedures. The ISO shall adjust the reported ACL of the SCR for a reported SCR Change of Status to the Net ACL, for all prospective months to which the SCR Change of Status is applicable. When a SCR Change of Status is reported under clause (i), (ii) or (iii) within the definition of a Qualified Change of Status Condition and the SCR has sold capacity, the SCR shall be evaluated for a potential shortfall under Section 5.14.2 of this Services Tariff. Failure by the RIP to report a SCR Change of Status shall be evaluated as a potential shortfall under Section 5.14.2 of this Service Tariff and evaluated for failure to report under Section 5.12.12.2 of this Services Tariff.

Beginning with the Summer 2014 Capability Period, SCRs that were required to perform in the first performance test in the Capability Period in accordance with ISO Procedures and that subsequently report or change a reported SCR Change of Status value after the first performance test in the Capability Period shall be required to demonstrate the performance of the resource against the Net ACL value in the second performance test in the Capability Period. The exceptions to this provision occur when a SCR's eligible Installed Capacity is set to zero throughout the period of the SCR Change of Status, when a SCR's eligible Installed Capacity is decreased by at least the same kW value as the reported SCR Change of Status, or if a SCR Change of Status is reported, and prior to the second performance test, the SCR returns to the full applicable ACL enrolled prior to the SCR Change of Status. Performance in both performance tests shall be used in calculation of the resource's performance factors and all associated performance factors, deficiencies and penalties. If the RIP fails to report the performance for a resource that was required to perform in the second performance test in the Capability Period: (a) the resource will be assigned a performance of zero (0) for the test hour, and (b) the RIP shall be evaluated for failure to report under Section 5.12.12.2 of this Services Tariff.

5.12.11.1.4 Average Coincident Load of an SCR Aggregation

The ISO shall compute the Average Coincident Load of an SCR Aggregation each month in accordance with ISO Procedures.

5.12.11.1.5 Use of an Incremental Average Coincident Load

Beginning with the Summer 2014 Capability Period, a Responsible Interface Party may report any qualifying increase to a Special Case Resource's Average Coincident Load as Incremental Average Coincident Load in the RIP enrollment file upload and in accordance with this Services Tariff and ISO Procedures.

For SCRs with a total Load increase equal to or greater than twenty (20) percent and less than thirty (30) percent of the applicable ACL, the RIP may enroll the SCR with an Incremental ACL provided that the eligible Installed Capacity does not increase from the prior enrollment months within the same Capability Period and prior to enrollment with an Incremental ACL. If the SCR is enrolled with an Incremental ACL and it is the first month of the SCR's enrollment in the applicable Capability Period, the enrolled eligible Installed Capacity value shall not exceed the maximum eligible Installed Capacity of the SCR from the Prior Equivalent Capability Period. When no enrollment exists for the SCR in the Prior Equivalent Capability Period and it is the first month of the SCR's enrollment in the applicable Capability Period, the enrolled eligible Installed Capacity of the SCR shall not exceed the ACL calculated from the Capability Period SCR Load Zone Peak Hours. For SCRs with a total Load increase equal to or greater than thirty (30) percent of the applicable ACL, the RIP may enroll the SCR with an Incremental ACL and an increase to the SCR's eligible Installed Capacity and is required to test as described in this section of the Service Tariff.

The ISO shall adjust the ACL of the SCR for an Incremental ACL for all months for

which the Incremental ACL is reported by the RIP. For resources reporting an Incremental ACL, the Net ACL shall equal the enrolled ACL plus the reported Incremental ACL less any applicable SCR Change of Status and shall be the basis for the upper limit of ICAP for which the RIP may enroll the SCR during the Capability Period.

An Incremental ACL is a discrete change to the SCR operations that is expected to result in an increase to the Load that the SCR will consume from the NYS Transmission System and/or distribution system. It is not available to account for random fluctuations in Load, such as those caused by weather or other seasonal Load variations. Therefore, the ACL of a SCR may only be increased once per Capability Period and the amount of the increase enrolled must remain the same for all months for which the Incremental ACL is reported. A SCR enrolled in the Capability Period with an Incremental ACL may not be enrolled by another RIP for the remainder of the Capability Period. A SCR enrolled in the Capability Period with a Provisional ACL is not eligible to enroll with an Incremental ACL.

Following the Capability Period for which a SCR has been enrolled with an Incremental ACL, the RIP shall provide the hourly metered Load verification data that corresponds to the Monthly SCR Load Zone Peak Hours identified by the ISO for all months in which an Incremental ACL value was reported for the SCR. For each month for which verification data was required to be reported, the ISO shall calculate a Monthly ACL that will be used in the calculation of a Verified ACL. The Monthly ACL shall equal the average of the SCR's top twenty (20) one-hour metered Load values that correspond with the applicable Monthly SCR Load Zone Peak Hours, and taking into account (i) the resource's reported verified Load reduction in a Transmission Owner's demand response program in hours coincident with any of these hours and (ii) the resource's verified Load reduction in either of the ISO's economic

demand response programs (the Day Ahead Demand Response Program and the Demand Side Ancillary Services Program) in hours coincident with any of these hours. For the Day Ahead Demand Response Program, the verified Load reduction that occurred in response to a DADRP schedule shall be added to the Monthly SCR Load Zone Peak Hour for which the reduction in response to a DADRP schedule occurred. For the Demand Side Ancillary Services Program, the Load value to be used in calculating the Monthly ACL for each hour during the Monthly SCR Load Zone Peak Hours in which a non-zero Base Point Signal the ISO provides to the resource, shall be the greater of (a) the DSASP Baseline MW value in the interval immediately preceding the first non-zero Base Point Signal in the Monthly SCR Load Zone Peak Hour and (b) the metered Load of the resource as reported by the RIP for the Monthly SCR Load Zone Peak Hour. When the non-zero Base Point Signal dispatch of a DSASP resource begins in one hour and continues into consecutive hours, and the consecutive hour is identified as being a Monthly SCR Load Zone Peak Hour, the DSASP Baseline MW value in effect at the beginning of the dispatch of the non-zero Base Point Signal shall be the MW value used for purposes of determining the applicable Load value for that Monthly SCR Load Zone Peak Hour, in accordance with the preceding sentence. The Verified ACL shall be the average of the two (2) highest Monthly ACLs during the Capability Period in which the SCR was enrolled with an Incremental ACL within the same Capability Period.

For any month in which verification data for the Incremental ACL is required but not timely submitted to the ISO in accordance with ISO procedures, the ISO shall set the metered Load values to zero. When a Monthly ACL is set to zero, the Verified ACL will be calculated as the average of: a) the two (2) highest Monthly ACLs during the Capability Period in which the SCR was enrolled with an Incremental ACL within the same Capability Period; plus b) the

Monthly ACLs for all months in which the SCR was enrolled within the same Capability Period with an Incremental ACL in the Capability Period in which the RIP failed to provide the minimum verification data required. In addition, a RIP may be subject to a penalty for each month for which verification data was required and not reported in accordance with this Services Tariff.

For each SCR that is enrolled with an Incremental ACL, the ISO shall compare the Net ACL calculated from the resource enrollment (ACL plus Incremental ACL less any applicable SCR Change of Status) to the Verified ACL calculated for the SCR to determine if the RIP's use of an Incremental ACL may have resulted in a shortfall pursuant to Section 5.14.2.

A Special Case Resource that was required to perform in the first performance test in the Capability Period in accordance with ISO Procedures and was subsequently enrolled using an Incremental ACL and an increase in the amount of Installed Capacity that the SCR is eligible to sell, shall be required to demonstrate performance against the maximum amount of eligible Installed Capacity reported for the SCR in the second performance test in the Capability Period. Performance in this test shall be measured from the Net ACL. Performance in both performance tests shall be used in calculation of the resource's performance factor and all associated performance factors, deficiencies and penalties. If the RIP fails to report the performance for a resource that was required to perform in the second performance test in the Capability Period: (a) the resource will be assigned a performance of zero (0) for the test hour, and (b) the RIP shall be evaluated for failure to report under Section 5.12.12.2 of this Services Tariff.

5.12.11.2 Existing Municipally-Owned Generation

A municipal utility that owns existing generation in excess of its Unforced Capacity requirement, net of NYPA-provided Capacity may, consistent with the deliverability

requirements set forth in Attachment X and Attachment S to the ISO OATT, offer the excess Capacity for sale as Installed Capacity provided that it is willing to operate the generation at the ISO's request, and provided that the Energy produced is deliverable to the New York State Power System. Such a municipal utility shall not be required to comply with the requirement of Section 5.12.7 of this Tariff that an Installed Capacity Supplier bid into the Energy market or enter into Bilateral Transactions. Municipal utilities shall, however, be required to submit their typical physical operating parameters, such as their start-up times, to the ISO. This subsection is only applicable to municipally-owned generation in service or under construction as of December 31, 1999.

5.12.11.3 Energy Limited Resources

An Energy Limited Resource may, consistent with the deliverability requirements set forth in Attachment X and Attachment S to the ISO OATT, qualify as an Installed Capacity Supplier if it Bids its Installed Capacity Equivalent into the Day-Ahead Market each day and if it is able to provide the Energy equivalent of the Unforced Capacity for at least four (4) consecutive hours each day. Energy Limited Resources shall also Bid a Normal Upper Operating Limit or Emergency Upper Operating Limit, as applicable, designating their desired operating limits. Energy Limited Resources that are not scheduled in the Day-Ahead Market to operate at a level above their bid-in upper operating limit, may be scheduled in the RTC, or may be called in real-time pursuant to a manual intervention by ISO dispatchers, who will account for the fact that Energy Limited Resource may not be capable of responding.

5.12.11.4 Intermittent Power Resources

Intermittent Power Resources that depend upon wind or solar as their fuel may qualify as Installed Capacity Suppliers, without having to comply with the daily bidding and scheduling

requirements set forth in Section 5.12.7 of this Tariff, and may, consistent with the deliverability requirements set forth in Attachment X and Attachment S to the ISO OATT, claim up to their nameplate Capacity as Installed Capacity. To qualify as Installed Capacity Suppliers, such Intermittent Power Resources shall comply with the requirements of Section 5.12.1 and the outage notification requirements of 5.12.7 of this Tariff.

5.12.12 Sanctions Applicable to Installed Capacity Suppliers and Transmission Owners

Pursuant to this section, the ISO may impose financial sanctions on Installed Capacity Suppliers and Transmission Owners that fail to comply with certain provisions of this Tariff. The ISO shall notify Installed Capacity Suppliers and Transmission Owners prior to imposing any sanction and shall afford them a reasonable opportunity to demonstrate that they should not be sanctioned and/or to offer mitigating reasons why they should be subject to a lesser sanction. The ISO may impose a sanction lower than the maximum amounts allowed by this section at its sole discretion. Installed Capacity Suppliers and Transmission Owners may challenge any sanction imposed by the ISO pursuant to the ISO Dispute Resolution Procedures.

Any sanctions collected by the ISO pursuant to this section will be applied to reduce the Rate Schedule 1 charge under this Tariff.

5.12.12.1 Sanctions for Failing to Provide Required Information

If (i) an Installed Capacity Supplier fails to provide the information required by Sections 5.12.1.1, 5.12.1.2, 5.12.1.3, 5.12.1.4, 5.12.1.7 or 5.12.1.8 of this Tariff in a timely fashion, or (ii) a Supplier of Unforced Capacity from External System Resources located in an External Control Area or from a Control Area System Resource that has agreed not to Curtail the Energy associated with such Installed Capacity, or to afford it the same Curtailment priority that it

affords its own Control Area Load, fails to provide the information required for certification as an Installed Capacity Supplier established in the ISO Procedures, the ISO may take the following actions: On the first day that required information is late, the ISO shall notify the Installed Capacity Supplier that required information is past due and that it reserves the right to impose financial sanctions if the information is not provided by the end of the following day. Starting on the third day that the required information is late, the ISO may impose a daily financial sanction of up to the higher of \$500 or \$5 per MW of Installed Capacity that the Generator, System Resource, or Control Area System Resource in question is capable of providing. Starting on the tenth day that the required information is late, the ISO may impose a daily financial sanction of up to the higher of \$1000 or \$10 per MW of Installed Capacity that the Generator, System Resource, or Control Area System Resource in question is capable of providing.

If an Installed Capacity Supplier fails to provide the information required by Subsection 5.12.1.5 of this Tariff in a timely fashion, the ISO may take the following actions: On the first calendar day that required information is late, the ISO shall notify the Installed Capacity Supplier that required information is past due and that it reserves the right to impose financial sanctions if the information is not provided by the end of that first calendar day. Starting on the second calendar day that the required information is late, the ISO may impose a daily financial sanction up to the higher of \$500 or \$5 per MW of Installed Capacity that the Generator, System Resource, or Control Area System Resource in question is capable of providing.

If a TO fails to provide the information required by Subsection 5.11.3 of this Tariff in a timely fashion, the ISO may take the following actions: On the first day that required information is late, the ISO shall notify the TO that required information is past due and that it reserves the right to impose financial sanctions if the information is not provided by the end of

the following day. Starting on the third day that the required information is late, the ISO may impose a daily financial sanction up to \$5,000 a day. Starting on the tenth day that required information is late, the ISO may impose a daily financial sanction up to \$10,000.

5.12.12.2 Sanctions for Failing to Comply with Scheduling, Bidding, and Notification Requirements

On any day in which an Installed Capacity Supplier fails to comply with the scheduling, bidding, or notification requirements of Sections 5.12.1.6 or 5.12.1.10, or with Section 5.12.7 of this Tariff, or in which a Supplier of Installed Capacity from External System Resources or Control Area System Resources located in an External Control Area that has agreed not to Curtail the Energy associated with such Installed Capacity, or to afford it the same Curtailment priority that it affords its own Control Area Load, fails to comply with scheduling, bidding, or notification requirements for certification as an Installed Capacity Supplier established in the ISO Procedures, the ISO may impose a financial sanction up to the product of a deficiency charge (pro-rated on a daily basis) and the maximum number of MWs that the Installed Capacity Supplier failed to schedule or Bid in any hour in that day provided, however, that no financial sanction shall apply to any Installed Capacity Supplier who demonstrates that the Energy it schedules, bids, or declares to be unavailable on any day is not less than the Installed Capacity that it supplies for that day rounded down to the nearest whole MW. The deficiency charge may be up to one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction corresponding to where the Installed Capacity Supplier's capacity cleared, and for each month in which the Installed Capacity Supplier is determined not to have complied with the foregoing requirements.

In addition, if an Installed Capacity Supplier fails to comply with the scheduling, bidding, or notification requirements of Sections 5.12.1.6 or 5.12.1.10, or with Section 5.12.7 of this

Tariff, or if an Installed Capacity Supplier of Unforced Capacity from External System Resources or from a Control Area System Resource located in an External Control Area that has agreed not to curtail the Energy associated with such Unforced Capacity, or to afford it the same curtailment priority that it affords its own Control Area Load, fails to comply with the scheduling, bidding, or notification requirements for certification as an Installed Capacity Supplier established in the ISO Procedures during an hour in which the ISO curtails Transactions associated with NYCA Installed Capacity Suppliers, the ISO may impose an additional financial sanction equal to the product of the number of MWs the Installed Capacity Supplier failed to schedule during that hour and the corresponding Real-Time LBMP at the applicable Proxy Generator Bus.

If the Installed Capacity Supplier is a Responsible Interface Party that enrolled a SCR with an Incremental ACL in accordance with this Services Tariff, and also reported an increase to the Installed Capacity the SCR has eligible to sell after the first performance test in the Capability Period, the ISO may impose an additional financial sanction due to the failure of the RIP to report the required performance of the SCR against the Net ACL value in the second performance test in the Capability Period. This sanction shall be the value of the reported increase in the eligible Installed Capacity associated with the SCR that was sold by the RIP in each month of the Capability Period, during which the reported increase was in effect, multiplied by up to one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction for each such month.

If the Installed Capacity Supplier is a Responsible Interface Party, and the Average Coincident Load of the Special Case Resource has been decreased after the first performance test in the Capability Period, due to a SCR Change of Status in accordance with this Services Tariff

and ISO Procedures, the ISO may impose an additional financial sanction resulting from the failure of the RIP to report the required performance of the SCR against the Net ACL value of the SCR when the SCR was required to perform in the second performance test in the Capability Period in accordance with Section 5.12.11.1.3.2 of this Services Tariff. This sanction shall be the value of the Unforced Capacity equivalent of the SCR Change of Status MW reported for the SCR during the months for which the SCR was enrolled with a SCR Change of Status and was required to demonstrate in the second performance test as specified in Section 5.12.11.1.3.2 of this Services Tariff, multiplied by up to one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction for each such month.

If a RIP fails to provide the information required by Section 5.12.11.1.3 of this Services Tariff in accordance with the ISO Procedures for reporting a Qualified Change of Status Condition, and the ISO determines that a SCR Change of Status occurred within a Capability Period, the ISO may impose a financial sanction equal to the difference, if positive, between the enrolled ACL and the maximum one hour metered Load for the month multiplied by up to one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction for each month the Installed Capacity Supplier is deemed to have a shortfall in addition to the corresponding shortfall penalty as provided in Section 5.14.2.

For each month in which a RIP fails to report required verification data and the applicable ACL value is set to zero in accordance with Section 5.12.11 of this Services Tariff, the ISO shall have the right to recover any energy payments made to the RIP for performance of the SCR by reducing other payments or other lawful means.

5.13 Installed Capacity Auctions

5.13.1 General Auction Requirements

The ISO will administer Installed Capacity auctions to accommodate LSEs' and Installed Capacity Suppliers' efforts to enter into Unforced Capacity Transactions and to give LSEs an opportunity to acquire sufficient ~~their~~ Unforced Capacity to meet their respective LSE Unforced Capacity Obligations. The ISO shall conduct regular auctions, at the request of an LSE, at the times specified in this section and the ISO Procedures, and may conduct additional auction as necessary.

Installed Capacity Suppliers, LSEs and Installed Capacity Marketers that are Customers under this Tariff will be allowed to participate in Installed Capacity auctions, provided that they satisfy the creditworthiness requirements set forth in Attachment K of the ISO OATT. Unforced Capacity purchased in Installed Capacity auctions may not be sold for the purposes of meeting Installed Capacity requirements imposed by operators of External Control Areas. Offers to sell and bids to purchase Unforced Capacity shall be made in \$/kW for the time period appropriate to the auction. The ISO shall impose no limits on Bids or offers in any auction, except to the extent required by any applicable capacity market mitigation measures.

Installed Capacity Suppliers that wish to participate in an ISO-administered auction must submit completed certification forms to the ISO in accordance with the ISO ~~P~~ procedures, demonstrating that their Unforced Capacity has not been committed to a Bilateral Transaction.

The ISO Procedures shall specify the dates by which the ISO will post the results of Installed Capacity auctions. The ISO Procedures shall ensure that there are at least four business days between the time that auction results from monthly auctions are posted and the dates that LSEs are required to demonstrate the quantity of Unforced Capacity that has been obtained for

the upcoming Obligation Procurement Period, pursuant to Section 5.11.2 of this Tariff. LSEs holding Unforced Capacity which they want credited against their LSE Unforced Capacity Obligations must certify such Unforced Capacity when submitting their Installed Capacity certifications.

5.13.2 Capability Period Auction

A Capability Period Auction will be conducted no later than thirty (30) days prior to the start of each Capability Period in which Unforced Capacity will be purchased and sold for the entire duration of the Capability Period. The exact date of the Capability Period Auction shall be established in the ISO Procedures. The Capability Period Auction is intended to facilitate long-term Unforced Capacity transactions between Market Participants.

The Capability Period Auction will be conducted and solved simultaneously to purchase Unforced Capacity which may be used by an LSE toward all components of its LSE Unforced Capacity Obligation for each Obligation Procurement Period. Participation shall consist of: (i) LSEs seeking to purchase Unforced Capacity; (ii) any other entity seeking to purchase Unforced Capacity; (iii) qualified Installed Capacity Suppliers; and (iv) any other entity that owns excess Unforced Capacity.

Buyers that are awarded Unforced Capacity shall pay the applicable Market-Clearing Price of Unforced Capacity in the Capability Period Auction. Sellers that are selected to provide Unforced Capacity shall receive the applicable Market-Clearing Price of Unforced Capacity in the Capability Period Auction.

The results of the Capability Period Auction will be made available to Market Participants at the time specified in the ISO Procedures, which shall be prior to the start of the Monthly Auction held prior to the beginning of each Capability Period.

5.13.3 Monthly Auctions

Monthly Auctions will be held during which Unforced Capacity may be purchased and sold for the forthcoming Obligation Procurement Period, and any other month or months remaining in the Capability Period, as specified in the ISO Procedures. The exact dates of each Monthly Auction shall be established in the ISO Procedures. Each Monthly Auction is intended to facilitate Unforced Capacity transactions between Market Participants.

Each Monthly Auction will be conducted and solved simultaneously to purchase Unforced Capacity which may be used by an LSE toward all components of its LSE Unforced Capacity Obligation for each Obligation Period. Participation shall consist of: (i) LSEs seeking to purchase Unforced Capacity; (ii) any other entity seeking to purchase Unforced Capacity; (iii) qualified Installed Capacity Suppliers; and (iv) any other entity that owns excess Unforced Capacity.

Buyers that are awarded Unforced Capacity shall pay the applicable Market-Clearing Price of Unforced Capacity in the Monthly Auction. Sellers that are selected to provide Unforced Capacity shall receive the applicable Market-Clearing Price.

The results of each Monthly Auction will be made available to Market Participants in accordance with the ISO Procedures.

5.13.4 Detailed Installed Capacity Auction Description

Additional detail concerning the ISO's Installed Capacity auction procedures are provided in the ISO Procedures.

5.14 Installed Capacity Spot Market Auction and Installed Capacity Supplier Deficiencies

5.14.1 LSE Participation in the ICAP Spot Market Auction

5.14.1.1 ICAP Spot Market Auction

When the ISO conducts each ICAP Spot Market Auction it will account for all Unforced Capacity that each NYCA LSE has certified for use in the NYCA to meet its NYCA Minimum ~~Unforced~~ ~~Installed~~ Capacity Requirement or Locational Minimum ~~Installed~~ ~~Unforced~~ Capacity Requirement, as applicable, whether purchased through Bilateral Transactions or in prior auctions. The ISO shall receive offers of Unforced Capacity that has not previously been purchased through Bilateral Transactions or in prior auctions from qualified Installed Capacity Suppliers for the ICAP Spot Market Auction. The ISO shall also receive offers of Unforced Capacity from any LSE for any amount of Unforced Capacity that the LSE has in excess of its NYCA Minimum Unforced Capacity Requirement or Locational Minimum Unforced Capacity Requirement, as applicable. Unforced Capacity that will be exported from the New York Control Area during the month for which Unforced ~~C~~capacity is sold in an ICAP Spot Market Auction shall be certified to the NYISO by the certification deadline for that auction.

The ISO shall conduct an ICAP Spot Market Auction to purchase Unforced Capacity which shall be used by an LSE toward all components of its LSE Unforced Capacity Obligation for each Obligation Procurement Period immediately preceding the start of each Obligation Procurement Period. The exact date of the ICAP Spot Market Auction shall be established in the ISO Procedures. All LSEs shall participate in the ICAP Spot Market Auction. In the ICAP Spot Market Auction, the ISO shall submit monthly bids on behalf of all LSEs at a level per MW determined by the ICAP Demand Curves established in accordance with this Tariff and the ISO

Procedures. The ICAP Spot Market Auction will set the LSE Unforced Capacity Obligation for each NYCA LSE in accordance with the ISO Procedures.

The ICAP Spot Market Auction will be conducted and solved simultaneously for Unforced Capacity that may be used by an LSE towards all components of its LSE Unforced Capacity Obligation for that Obligation Procurement Period using the applicable ICAP Demand Curves, as established in accordance with the ISO Procedures. LSEs that are awarded Unforced Capacity in the ICAP Spot Market Auction shall pay to the ISO the Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction using the applicable ICAP Demand Curve. The ISO shall pay each Installed Capacity Supplier that is selected to provide Unforced Capacity the Market-Clearing Price determined in the ICAP Spot Market Auction using the ICAP Demand Curve applicable to its offer.

5.14.1.2 Demand Curve and Adjustments

ICAP Demand Curves will be established to determine (a) the locational component of LSE Unforced Capacity Obligations for each Locality (b) the locational component of LSE Unforced Capacity Obligations for any New Capacity Zone, and (c) the total LSE Unforced Capacity Obligations for all LSEs. The ICAP Demand Curves for the 2013/2014, 2014/2015, 2015/2016, and 2016/2017 Capability Years shall be established at the following points:

Capability Year	5/1/2013 to 4/30/2014	5/1/2014 to 4/30/2015	5/1/2015 to 4/30/2016	5/1/2016 to 4/30/2017
NYCA	Max @ \$15.48 \$9.15 @ 100% \$0.00 @ 112%	Max @ \$13.50 \$8.84 @ 100% \$0.00 @ 112%	Max @ \$13.79 \$9.03 @ 100% \$0.00 @ 112 %	Max @ \$14.10 \$9.23 @ 100% \$0.00 @ 112%
NYC	Max @ \$36.04 \$19.85 @ 100% \$0.00 @ 118%	Max @ \$26.14 \$18.55 @ 100% \$0.00 @ 118%	Max @ \$26.72 \$ 18.95 @ 100% \$0.00 @ 118%	Max @ \$27.31 \$19.37 @ 100% \$0.00 @ 118%

LI	Max @ \$32.42 \$10.32 @ 100% \$0.00 @ 118%	Max @ \$20.88 \$7.96 @ 100% \$0.00 @ 118%	Max @ \$21.34 \$ 8.12 @ 100% \$0.00 @ 118%	Max @ \$21.81 \$8.30 @ 100% \$0.00 @ 118%
G-J		Max @ \$18.80 \$12.14 @ 100% \$0.00 @ 115%	Max @ \$19.22 \$12.41 @ 100% \$0.00 @ 115%	Max @ \$19.64 \$12.68 @ 100% \$0.00 @ 115%

NOTE: All dollar figures are in terms of \$/kW-month of ICAP and all percentages are in terms of the applicable NYCA Minimum Installed Capacity Requirement and Locational Minimum Installed Capacity Requirement. The defined points describe a line segment with a negative slope that will result in higher values for percentages less than 100% of the NYCA Minimum Installed Capacity Requirement or the Locational Installed Capacity Requirement (“reference point”) with the maximum value for each ICAP Demand Curve established at 1.5 times the estimated localized levelized cost per kW-month to develop a new peaking unit in each Locality or in Rest of State, as applicable.

In subsequent years, the costs assigned by the ICAP Demand Curves to the NYCA Minimum Installed Capacity Requirement, the Locational Minimum Installed Capacity Requirement, and any Indicative NCZ Minimum Installed Capacity Requirement, will be defined by the results of the independent review conducted pursuant to this section. The ICAP Demand Curves will be translated into Unforced Capacity terms in accordance with the ISO Procedures.

5.14.1.2.1 Periodic Reviews of ICAP Demand Curves Applicable Prior to the 2017/2018 Capability Year

For ICAP Demand Curves applicable prior to the 2017/2018 Capability Year, a periodic review of the ICAP Demand Curves shall be performed every three (3) years in accordance with the ISO Procedures to determine the parameters of the ICAP Demand Curves for the next three Capability Years. The periodic review shall assess: (i) the current localized levelized embedded cost of a peaking plant in each NYCA Locality, the Rest of State, and any New Capacity Zone, to meet minimum capacity requirements, and (ii) the likely projected annual Energy and Ancillary Services revenues of the peaking plant over the period covered by the adjusted ICAP Demand Curves, net of the costs of producing such Energy and Ancillary Services. The cost and

revenues of the peaking plant used to set the reference point and maximum value for each ICAP Demand Curve shall be determined under conditions in which the available capacity is equal to the sum of (a) the minimum Installed Capacity requirement and (b) the peaking plant's capacity equal to the number of MW specified in the periodic review and used to determine all costs and revenues. The minimum Installed Capacity requirement for each Locality shall be equal to the Locational Minimum Installed Capacity Requirement in effect for the year in which the independent consultant's final report (referenced below in Section 5.14.1.2.1.6) is issued; for the NYCA, equal to the NYCA Minimum Installed Capacity Requirement based on the Installed Reserve Margin accepted by the Commission and applicable to the Capability Year which begins in the Capability Year in which the independent consultant's final report is issued; and for any New Capacity Zone, equal to the Indicative NCZ Locational Minimum Installed Capacity Requirement determined by the ISO in accordance with Section 5.16.3. The periodic review shall also assess (i) the appropriate shape and slope of the ICAP Demand Curves, and the associated point at which the dollar value of the ICAP Demand Curves should decline to zero; (ii) the appropriate translation of the annual net revenue requirement of the peaking plant determined from the factors specified above, into monthly values that take into account seasonal differences in the amount of capacity available in the ICAP Spot Market Auctions; and (iii) the escalation factor and inflation component of the escalation factor applied to the ICAP Demand Curves. For purposes of this periodic review, a peaking unit is defined as the unit with technology that results in the lowest fixed costs and highest variable costs among all other units' technology that are economically viable, and a peaking plant is defined as the number of units (whether one or more) that constitute the scale identified in the periodic review.

The periodic review shall be conducted in accordance with the schedule and procedures specified in the ISO Procedures. A proposed schedule will be reviewed with the stakeholders not later than May 30 of the year prior to the year of the filing specified in Section 5.14.1.2.1.11.

The schedule and procedures shall provide for:

- 5.14.1.2.1.1 ISO development, with stakeholder review and comment, of a request for proposals to provide independent consulting services to determine recommended values for the factors specified above, and appropriate methodologies for such determination;
- 5.14.1.2.1.2 Selection of an independent consultant in accordance with the request for proposals;
- 5.14.1.2.1.3 Submission to the ISO and the stakeholders of a draft report from the independent consultant on the independent consultant's determination of recommended values for the factors specified above;
- 5.14.1.2.1.4 Stakeholder review of and comment on the data, assumptions and conclusions in the independent consultant's draft report, with participation by the responsible person or persons providing the consulting services;
- 5.14.1.2.1.5 An opportunity for the Market Monitoring Unit to review and comment on the draft request for proposals, the independent consultant's report, and the ISO's proposed ICAP Demand Curves (the responsibilities of the Market Monitoring Unit that are addressed in this section of the Services Tariff are also addressed in Section 30.4.6.3.1 of Attachment O);
- 5.14.1.2.1.6 Issuance by the independent consultant of a final report;

- 5.14.1.2.1.7 Issuance of a draft of the ISO's recommended adjustments to the ICAP Demand Curves for stakeholder review and comment;
- 5.14.1.2.1.8 Issuance of the ISO's proposed ICAP Demand Curves, taking into account the report of the independent consultant, the recommendations of the Market Monitoring Unit, and the views of the stakeholders together with the rationale for accepting or rejecting any such inputs;
- 5.14.1.2.1.9 Submission of stakeholder requests for the ISO Board of Directors to review and adjust the ISO's proposed ICAP Demand Curves;
- 5.14.1.2.1.10 Presentations to the ISO Board of Directors of stakeholder views on the ISO's proposed ICAP Demand Curves; and
- 5.14.1.2.1.11 Filing with the Commission of ICAP Demand Curves as approved by the ISO Board of Directors incorporating the results of the periodic review, such filing to be made not later than November 30 of the year prior to the year that includes the beginning of the first Capability Year to which such ICAP Demand Curves would be applied. The filing shall specify ICAP Demand Curves for a period of three Capability Years and the inflation rate component of the escalation factor applied to the ICAP Demand Curves.

Upon FERC approval, the ICAP Demand Curves will be translated into Unforced Capacity terms in accordance with the ISO Procedures; provided that nothing in this Tariff shall be construed to limit the ability of the ISO or its Market Participants to propose and adopt alternative provisions to this Tariff through established governance procedures.

5.14.1.2.2 Periodic Reviews of ICAP Demand Curves Applicable Beginning with the 2017/2018 Capability Year

Beginning with the ICAP Demand Curves applicable for the 2017/2018 Capability Year, a periodic review of the ICAP Demand Curves shall be performed every four (4) years in accordance with the ISO Procedures to: (i) identify the methodologies and inputs used for determining the ICAP Demand Curves for the four Capability Years covered by the periodic review; and (ii) establish the ICAP Demand Curves for the first Capability Year covered by the periodic review.

The periodic review shall assess: (i) the current localized levelized embedded cost of a peaking plant in each NYCA Locality, the Rest of State, and any New Capacity Zone, to meet minimum capacity requirements (for purposes of this Section 5.14.1.2.2 hereinafter referred to as the “peaking plant gross cost”); and (ii) the likely projected annual Energy and Ancillary Services revenues of the peaking plant for the first Capability Year covered by the periodic review, net of the costs of producing such Energy and Ancillary Services (for purposes of this Section 5.14.1.2.2 hereinafter referred to as the “net Energy and Ancillary Services revenue offset”), including the methodology and inputs for determining such projections for the four Capability Years covered by the periodic review. The cost and revenues of the peaking plant used to set the reference point and maximum value for each ICAP Demand Curve shall be determined under conditions in which the available capacity is equal to the sum of (a) the minimum Installed Capacity requirement and (b) the peaking plant’s capacity equal to the number of MW specified in the periodic review and used to determine all costs and revenues (for purposes of this Section 5.14.1.2.2 hereinafter referred to as the “prescribed level of excess”). The minimum Installed Capacity requirement for each Locality shall be equal to the Locational Minimum Installed Capacity Requirement in effect for the year in which the independent consultant’s final report (referenced below in Section 5.14.1.2.2.4.6) is issued; for the NYCA,

equal to the NYCA Minimum Installed Capacity Requirement based on the Installed Reserve Margin accepted by the Commission and applicable to the Capability Year which begins in the Capability Year in which the independent consultant's final report is issued; and for any New Capacity Zone, equal to the Indicative NCZ Locational Minimum Installed Capacity Requirement determined by the NYISO in accordance with Section 5.16.3. The periodic review shall also assess (i) the appropriate shape and slope of the ICAP Demand Curves, and the associated point at which the dollar value of the ICAP Demand Curves should decline to zero; (ii) the appropriate translation of the annual net revenue requirement of the peaking plant determined from the factors specified above, into monthly values that take into account seasonal differences in the amount of capacity available in the ICAP Spot Market Auctions in accordance with the methodology set forth in Section 5.14.1.2.2.3; and (iii) the escalation factor and inflation component of the escalation factor applied to the peaking plant gross cost, including the methodology and inputs for determining such values. For purposes of this periodic review, a peaking unit is defined as the unit with technology that results in the lowest fixed costs and highest variable costs among all other units' technology that are economically viable, and a peaking plant is defined as the number of units (whether one or more) that constitute the scale identified in the periodic review.

In the filing referenced in Section 5.14.1.2.2.4.11 below, the ISO will: (i) identify the methodologies and inputs used for determining the ICAP Demand Curves for the four Capability Years covered by the periodic review; and (ii) propose the ICAP Demand Curves for the first Capability Year covered by the periodic review. For the subsequent three Capability Years covered by the periodic review, the ISO will establish the ICAP Demand Curves for each such Capability Year by updating the following factors in advance of each such subsequent Capability

Year: (i) the peaking plant gross cost in accordance with Section 5.14.1.2.2.1; (ii) the net Energy and Ancillary Services revenue offset in accordance with Section 5.14.1.2.2.2; and (iii) the winter-to-summer ratio, as such term is defined in Section 5.14.1.2.2.3, in accordance with Section 5.14.1.2.2.3. The ISO will post the updated ICAP Demand Curves for each subsequent Capability Year covered by the periodic review on or before November 30th of the calendar year immediately preceding the calendar year that includes the start of the Capability Year for which the updated ICAP Demand Curves will apply.

5.14.1.2.2.1 Annual Updates for Peaking Plant Gross Cost

For purposes of the annual updates to the ICAP Demand Curves, the ISO shall determine updated values for the peaking plant gross cost for each peaking plant. Updated values for the peaking plant gross cost shall be determined by application of an escalation factor to the peaking plant gross cost values underlying the then currently effective ICAP Demand Curves. The escalation factor shall consist of the following four components: (i) changes in construction material costs (“materials component”); (ii) changes in turbine generator costs (“turbine component”); (iii) changes in labor costs (“labor component”); and (iv) changes in the general cost of goods and services (“general component”). The escalation factor shall be equal to the sum of the: (i) the twelve month percentage change in the applicable index for the materials component, multiplied by the applicable weighting factor for such component; (ii) the twelve month percentage change in the applicable index for the turbine component, multiplied by the applicable weighting factor for such component; (iii) the twelve month percentage change in the applicable index for the labor component, multiplied by the applicable weighting factor for such component; and (iv) the twelve month percentage change in the applicable index for the general component, multiplied by the applicable weighting factor for such component. For purposes of

determining the twelve month percentage change for each component, the values utilized from each applicable index shall be as follows: (i) for indices that publish annual values, the most recently available annual value and the annual value for the calendar year immediately preceding thereto; (ii) for indices that publish monthly values, the average value of the three most recently available monthly values and the average value of values for the same three months from the calendar year immediately preceding thereto; and (iii) for indices that publish quarterly values, the value of the most recently available calendar quarter and the value for the same calendar quarter from the calendar year immediately preceding thereto. The applicable values to be used by the ISO shall be the available finalized values established by the publisher for each index as of October 1st of the same calendar year as the applicable November 30th deadline for posting the updated ICAP Demand Curves. The ISO shall not use any preliminary values published by an index in determining the applicable twelve month percentage change for any component of the escalation factor. The weighting factors applied to each component shall be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review. The specified index for each component shall likewise be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review, unless an index is eliminated, replaced or otherwise terminated by the publisher thereof during the period covered by the periodic review. In such circumstance, the ISO shall utilize the replacement or successor index established by the publisher, if any, or, in the absence of a replacement or successor index, shall select as a replacement a substantially similar index.

5.14.1.2.2.2 Annual Updates for Net Energy and Ancillary Revenue Offset

For purposes of the annual updates to the ICAP Demand Curves, the ISO shall also determine updated values for the net Energy and Ancillary Services revenue offset associated with each peaking plant. Updated values for the net Energy and Ancillary Services revenue offset shall, in part, be determined using a net revenue model that will be developed as part of the periodic review and made available to stakeholders. The model will, at a minimum, determine whether each peaking plant could earn positive net revenue by producing Energy in each hour based on historical prices and the variable costs for each peaking plant over the prior 36 month period ending August 31st of the same calendar year as the applicable November 30th deadline for posting the updated ICAP Demand Curves, as well as the physical operating characteristics of each peaking plant and any operating hours constraints necessary to address any applicable environmental requirements and/or fuel availability. The commitment and dispatch logic and data sources and/or inputs used by the model, as well as the manner in which the model accounts for net Ancillary Services revenues earned by each peaking plant, the physical operating characteristics of each peaking plant and any operating hours constraints applicable to each peaking plant that are necessary to address any applicable environmental requirements and/or fuel availability, will be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review, subject to annual updating of certain data inputs used by the model as described herein.

The model will determine whether each peaking plant could earn positive net revenue by producing Energy in each hour of the period encompassed by the model in a manner consistent with the following equation:

$$Net\ Energy\ revenue_{z,t} = \max([Output_{z,t} * (LOE_{z,t} * LBMP_{z,t})] - MC_{z,t}, 0)$$

where:

$Output_{z,t}$ = the quantity of Energy produced by the peaking plant for Load Zone z in hour t ;

$LOE_{z,t}$ = the applicable adjustment factor for Load Zone z and hour t used to adjust for the prescribed level of excess. The adjustment factors shall be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review;

$LBMP_{z,t}$ = the Day-Ahead zonal LBMP or time-weighted/integrated zonal RTD LBMP, as applicable, for Load Zone z and hour t ;

$MC_{z,t}$ = variable (or short-run marginal) cost of the peaking plant for Load Zone z to produce Energy in hour t , calculated as follows:

$$MC_{z,t} = [(HR_{z,t} * Fuel_{z,t}) + VOM_{z,t} + ASC_{z,t} + EC_{z,t} + RSI_{z,t}] * Output_{z,t}$$

where:

$HR_{z,t}$ = the heat rate of the peaking plant for Load Zone z and hour t . The heat rate for the peaking plant shall be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review;

$Fuel_{z,t}$ = the applicable fuel cost for the peaking plant for Load Zone z and hour t , which shall be the lesser of the primary fuel cost and the backup fuel cost, if any, for the peaking plant for Load Zone z . The primary fuel and any backup fuel for the peaking plant for Load Zone z shall be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review. The applicable fuel cost will be based on the applicable daily spot price for Load Zone z published in the specified data source determined as part of the periodic review (unless such data source is revised for the reasons described below), plus an adder to account for any applicable transportation and delivery costs and any applicable fuel taxes, which adder shall be determined

as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review. For real-time evaluations only, the otherwise applicable fuel cost shall be increased by the applicable real-time fuel premium adder for Load Zone z and hour t , which adder shall be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review. The data sources used for determining the applicable daily spot fuel prices shall be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review, unless the specified data source is eliminated, replaced or otherwise terminated by the publisher thereof during the period covered by the periodic review. In such circumstance, the ISO shall utilize the replacement or successor data source established by the publisher, if any, or, in the absence of a replacement or successor data source, shall select as a replacement a substantially similar data source;

$VOM_{z,t}$ = variable operating and maintenance cost of the peaking plant for Load Zone z and hour t , which cost shall be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review;

$ASC_{z,t}$ = amortized start-up cost for the peaking plant for Load Zone z and hour t . The model will ensure that the total value of this cost is recovered over the number of consecutive hours for which the model determines that the peaking plant should be committed or dispatched to produce Energy following each start of the peaking plant in the same market (Day-Ahead or real-time); provided, however, that in real-time, start-up costs must be recovered over a period of no more than two consecutive hours following the time at which the model determines that the peaking plant should be dispatched to produce Energy;

$EC_{z,t}$ = the sum of CO₂, NO_x and SO₂ emissions allowance costs for the peaking plant for Load

Zone z and hour t , which shall be calculated as follows:

$$EC_{z,t} = (CO_2 \text{ emissions rate}_{z,t} * CO_2 \text{ allowance price}_{z,t}) + (NO_x \text{ emissions rate}_{z,t} * NO_x \text{ allowance price}_{z,t}) + (SO_2 \text{ emissions rate}_{z,t} * SO_2 \text{ allowance price}_{z,t})$$

where:

The applicable emissions rates for the peaking plant for Load Zone z and hour t shall be

determined as part of the periodic review, identified in the filing required by Section

5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review. The

applicable allowance price for each emissions type shall be the price reported by the specified

data source for each emissions type determined as part of the periodic review (unless such data

source is revised for the reasons described below). The data sources for allowance prices shall

be determined as part of the periodic review, identified in the filing required by Section

5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review, unless a

specified data source is eliminated, replaced or otherwise terminated by the publisher thereof

during the period covered by the periodic review. In such circumstance, the ISO shall utilize the

replacement or successor data source established by the publisher, if any, or, in the absence of a

replacement or successor data source, shall select as a replacement a substantially similar data

source; and

$RS1_{z,t}$ = the applicable charges for the ISO annual budget and the annual FERC fee assessed to

Injection Billing Units for Load Zone z and hour t in accordance with Rate Schedule 1 of the ISO

OATT.

The results of the model will be used to determine an average annual net revenue value

earned by each peaking plant over the period encompassed by the model. Such value will be

increased by an adder to account for the estimated annual value of any applicable net Ancillary

Services revenue for each peaking plant that is not determined by the model, which adder shall be determined as part of the periodic review, identified in the filing required by Section 5.14.1.2.2.4.11 and remain fixed for the entire period covered by the periodic review. The resulting value for each peaking plant shall be the updated net Energy and Ancillary Services revenue offset value to be used in establishing the ICAP Demand Curves for the applicable Capability Year.

5.14.1.2.2.3 Annual Updates for ICAP Demand Curve Parameters

The ISO shall use the updated peaking plant gross cost and the updated net Energy and Ancillary Services revenue offset values in determining the parameters of the ICAP Demand Curves for the applicable Capability Year. The maximum value for each ICAP Demand Curve shall be established at 1.5 times the monthly value of the applicable updated peaking plant gross cost. The reference point for each ICAP Demand Curve shall be determined in accordance with ISO Procedures; provided, however, that the ratio of the amount of capacity available in the ICAP Spot Market Auctions in the Winter Capability Period to the amount of capacity available in the ICAP Spot Market Auctions in the Summer Capability Period used in calculating the reference point (the “winter-to-summer ratio”) shall be updated annually based on the average amount of capacity available in the ICAP Spot Market Auctions for the Summer Capability Period months and Winter Capability Period months in each 12-month period (measured from September through the following August) encompassed by the same historical period utilized by the net revenue model. The values used in determining the amount of capacity available in the ICAP Spot Market Auctions shall be the available Unforced Capacity values reported by the ISO and posted on its website for the relevant months, translated to Installed Capacity values based on the applicable translation factors reported by the ISO and posted on its website for each such

month. For Resources other than Special Case Resources, the values posted by the ISO shall include the following adjustments to account for ICAP market entry and exit under certain circumstances: (i) if within any of the three 12-month periods (*i.e.*, September through the following August) encompassed by the data used in calculating an updated winter-to-summer ratio value, a Resource (other than a Resource returning to participate in the ICAP market from an Inactive Reserves state) begins to qualify as eligible to participate in the ICAP market in any month encompassed by such 12-month period and remains eligible to participate in the ICAP market for the subsequent months encompassed by that period, the ISO shall adjust the values for all months of that 12-month period to include the Resource's applicable available capacity; and (ii) if within any of the three 12-month periods (*i.e.*, September through the following August) encompassed by the data used in calculating an updated winter-to-summer ratio value, a Resource is Retired or enters a Mothball Outage or ICAP Ineligible Forced Outage state during any month encompassed by such 12-month period and remains ineligible to participate in the ICAP market for the subsequent months encompassed by that period, the ISO shall adjust the values for all months of that 12-month period to exclude the Resource's applicable available capacity. The applicable capacity ratings for each peaking plant utilized in calculating the reference point and the point on each ICAP Demand Curve at which the price of ICAP declines to zero shall be determined as part of the periodic review and shall remain fixed for the entire period covered by the periodic review.

Notwithstanding anything to the contrary herein, for purposes of the annual updates for the 2018/2019, 2019/2020 and 2020/2021 Capability Years, the reference point for each ICAP Demand Curve shall not be permitted to increase by an amount greater than twelve percent (12%) or decrease by an amount greater than eight percent (8%) from one Capability Year to the

next, compared to the then currently effective reference point for the relevant ICAP Demand Curve. If the reference point value for an ICAP Demand Curve, as calculated by the ISO pursuant to the annual update procedures, for one of the affected Capability Years exceeds the maximum allowable percentage increase or decrease, the reference point established by the ISO for that ICAP Demand Curve for the relevant Capability Year shall be an amount equal to the price that represents the applicable maximum allowable percentage increase or decrease. If an adjusted reference point value is applied to an ICAP Demand Curve for a Capability Year, the maximum allowable percentage increase or decrease for the next Capability Year shall be determined using the adjusted reference point value. As part of the required posting to establish the updated ICAP Demand Curves for each of the affected Capability Years, the ISO will provide the reference point values calculated by the ISO pursuant to the annual update procedures, as well the adjusted reference point values, if any, that result from the application of the limitation described herein. The limitation described above regarding the allowable annual change to the reference point values calculated by the ISO pursuant to the annual update procedures shall not be applied to the reference point values for any ICAP Demand Curve after the 2020/2021 Capability Year.

The peaking plant gross cost and net Energy and Ancillary Services revenue offset values utilized in determining the parameters of the ICAP Demand Curves for the 2017/2018 Capability Year are as follows:

	Peaking Plant Gross Cost (\$ per kW-year)	Net Energy and Ancillary Services Revenue Offset (\$ per kW-year)
NYCA		
G-J		
NYC		
LI		

5.14.1.2.2.4 Periodic Review Procedures

The periodic review shall be conducted in accordance with the schedule and procedures specified in the ISO Procedures. A proposed schedule will be reviewed with the stakeholders not later than May 30th of the year prior to the year of the filing specified in Section 5.14.1.2(b).11.

The schedule and procedures shall provide for:

5.14.1.2.2.4.1 ISO development, with stakeholder review and comment, of a request for proposals to provide independent consulting services to determine recommended values for the factors specified above, and appropriate methodologies and inputs for such determination;

5.14.1.2.2.4.2 Selection of an independent consultant in accordance with the request for proposals;

5.14.1.2.2.4.3 Submission to the ISO and the stakeholders of a draft report from the independent consultant on the independent consultant's determination of recommended values for the factors specified above, including, as applicable, the methodologies and inputs for determining such values;

5.14.1.2.2.4.4 Stakeholder review of and comment on the data, assumptions and conclusions in the independent consultant's draft report, with participation by the responsible person or persons providing the consulting services;

5.14.1.2.2.4.5 An opportunity for the Market Monitoring Unit to review and comment on the draft request for proposals, the independent consultant's report, and the ISO's proposed: (i) methodologies and inputs used for determining the ICAP Demand Curves for the four Capability Years covered by the periodic review; and (ii) ICAP Demand Curves for the first Capability Year covered by the periodic

review. The responsibilities of the Market Monitoring Unit that are addressed in this section of the Services Tariff are also addressed in Section 30.4.6.3.1 of Attachment O;

5.14.1.2.2.4.6 Issuance by the independent consultant of a final report;

5.14.1.2.2.4.7 Issuance of a draft of the ISO's recommended: (i) methodologies and inputs used for determining the ICAP Demand Curves for the four Capability Years covered by the periodic review; and (ii) ICAP Demand Curves for the first Capability Year covered by the periodic review, for stakeholder review and comment;

5.14.1.2.2.4.8 Issuance of the ISO's proposed: (i) methodologies and inputs used for determining the ICAP Demand Curves for the four Capability Years covered by the periodic review; and (ii) ICAP Demand Curves for the first Capability Year covered by the periodic review, taking into account the report of the independent consultant, the recommendations of the Market Monitoring Unit, and the views of the stakeholders together with the rationale for accepting or rejecting any such inputs;

5.14.1.2.2.4.9 Submission of stakeholder requests for the ISO Board of Directors to review and adjust the ISO's proposed: (i) methodologies and inputs used for determining the ICAP Demand Curves for the four Capability Years covered by the periodic review; and (ii) ICAP Demand Curves for the first Capability Year covered by the periodic review;

5.14.1.2.2.4.10 Presentations to the ISO Board of Directors of stakeholder views on the ISO's proposed: (i) methodologies and inputs used for determining the

ICAP Demand Curves for the four Capability Years covered by the periodic review; and (ii) ICAP Demand Curves for the first Capability Year covered by the periodic review; and

5.14.1.2.2.4.11 Filing with the Commission of: (i) a description of the methodologies and inputs used for determining the ICAP Demand Curves for the four Capability Years covered by the periodic review; and (ii) the ICAP Demand Curves for the first Capability Year covered by the periodic review, as approved by the ISO Board of Directors incorporating the results of the periodic review. Such filing will be made not later than November 30th of the year prior to the year that includes the beginning of the first Capability Year covered by the periodic review. The filing will also specify the inflation rate that would have been used to calculate the general component of the escalation factor as if the escalation factor were applicable to the first Capability Year covered by the periodic review. Such inflation rate shall be equal to the twelve month percentage change in the applicable index for the general component, as determined in accordance with Section 5.14.1.2.2.1 utilizing the applicable values of the index as of October 1st in the same calendar year as the November 30th filing deadline specified above. For each of the subsequent three Capability Years encompassed by the periodic review, the value of this inflation rate shall be the twelve month percentage change in the applicable index for the general component of the escalation factor for the applicable Capability Year, as determined pursuant to Section 5.14.1.2.2.1.

The ICAP Demand Curves will be translated into Unforced Capacity terms in accordance with the ISO Procedures; provided that nothing in this Tariff shall be construed to limit the

ability of the ISO or its Market Participants to propose and adopt alternative provisions to this Tariff through established governance procedures.

5.14.1.3 Supplemental Supply Fee

Any LSE that has not met its share of the NYCA Minimum Installed Capacity Requirement or its share of the Locational Minimum Installed Capacity Requirement after the completion of an ICAP Spot Market Auction, shall be assessed a supplemental supply fee equal to the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction multiplied by the number of MWs the LSE needs to meet its share of the NYCA Minimum Installed Capacity Requirement or its share of the Locational Minimum Installed Capacity Requirement.

The ISO will attempt to use these supplemental supply fees to procure Unforced Capacity at a price less than or equal to the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction from Installed Capacity Suppliers that are capable of supplying Unforced Capacity including: (1) Installed Capacity Suppliers that were not qualified to supply Capacity prior to the ICAP Spot Market Auction; (2) Installed Capacity Suppliers that offered Unforced Capacity at levels above the ICAP Spot Market Auction Market-Clearing Price; and (3) Installed Capacity suppliers that did not offer Unforced Capacity in the ICAP Spot Market Auction. In the event that different Installed Capacity Suppliers offer the same price, the ISO will give preference to Installed Capacity Suppliers that were not qualified to supply capacity prior to the ICAP Spot Market Auction.

Offers from Installed Capacity Suppliers are subject to review pursuant to the Market Monitoring Plan that is set forth in Attachment O to the Services Tariff, and the Market Mitigation Measures that are set forth in Attachment H to the Services Tariff. Installed Capacity

Suppliers selected by the ISO to provide capacity after the ICAP Spot Market Auction will be paid a negotiated price, subject to the standards, procedures and remedies in the Market

Mitigation Measures.

The ISO will not pay an Installed Capacity Supplier more than the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction per MW of Unforced Capacity, or, in the case of In-City generation that is subject to capacity market mitigation measures, the annual mitigated price cap per MW of Unforced Capacity, whichever is less, pro-rated to reflect the portion of the Obligation Procurement Period for which the Installed Capacity Supplier provides Unforced Capacity. Any remaining monies collected by the ISO pursuant to this section will be applied in accordance with Section 5.14.3 of the Services Tariff.

5.14.2 Installed Capacity Supplier Shortfalls and Deficiency Charges

5.14.2.1 General Provisions

In the event that an Installed Capacity Supplier sells in the Capability Period Auctions, in the Monthly Auctions, or through Bilateral Transactions more Unforced Capacity than it is qualified to sell in any specific month due to a de-rating or other cause, the Installed Capacity Supplier shall be deemed to have a shortfall for that month. To cover this shortfall, the Installed Capacity Supplier shall purchase sufficient Unforced Capacity in the relevant Monthly Auction or through Bilateral Transactions, and certify to the ISO consistent with the ISO Procedures that it has covered such shortfall. If the Installed Capacity Supplier does not cover such shortfall or if it does not certify to the ISO in a timely manner, the ISO shall, to the extent the ISO is aware of the shortfall, prospectively purchase Unforced Capacity on behalf of that Installed Capacity Supplier in the appropriate ICAP Spot Market Auction or through post ICAP Spot Market Auction Unforced Capacity purchases to cover the shortfall.

The ISO shall submit a Bid, calculated pursuant to Section 5.14.1 of this Tariff, in the appropriate ICAP Spot Market Auction on behalf of an Installed Capacity Supplier deemed to have a shortfall as if the Installed Capacity Supplier were an LSE. Such Installed Capacity Supplier shall be required to pay to the ISO the applicable Market-Clearing Price of Unforced Capacity established in that ICAP Spot Market Auction. Immediately following the ICAP Spot Market Auction, the ISO may suspend the Installed Capacity Supplier's privileges to sell or purchase Unforced Capacity in ISO-administered Installed Capacity auctions or to submit Bilateral Transactions to the NYISO. Once the Installed Capacity Supplier pays for or secures the payment obligation that it incurred in the ICAP Spot Market Auction, the ISO shall reinstate the Installed Capacity Supplier's privileges to participate in the ICAP markets.

In the event that the ICAP Spot Market Auction clears below the NYCA Minimum Installed Capacity Requirement or the Locational Minimum Installed Capacity Requirement, whichever is applicable to the Installed Capacity Supplier, and the Installed Capacity Supplier is deemed to have a shortfall, the Installed Capacity Supplier shall be assessed the applicable deficiency charge equal to the applicable Market-Clearing Price of Unforced Capacity determined using the applicable ICAP Demand Curve for that ICAP Spot Market Auction, times the amount of its shortfall.

If an Installed Capacity Supplier is found, at any point during a Capability Period, to have had a shortfall for that Capability Period, *e.g.*, when the amount of Unforced Capacity that it supplies is found to be less than the amount it was committed to supply, the Installed Capacity Supplier shall be retrospectively liable to pay the ISO the monthly deficiency charge equal to one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined using the applicable ICAP Demand Curve for that ICAP Spot Market Auction times the amount of its

shortfall for each month the Installed Capacity Supplier is deemed to have a shortfall. If the Installed Capacity Supplier is a RIP, it may experience a shortfall when, among other reasons, it sells ineligible or unavailable capacity MW associated with a properly or improperly enrolled SCR.

The ISO, when evaluating whether an Installed Capacity Supplier has a shortfall, may use either Unforced Capacity data or Installed Capacity data; provided, however, that the ISO shall convert any shortfall MWs based on Installed Capacity data to its Unforced Capacity equivalent prior to calculating the amount of any deficiency charge. All shortfalls shall be measured in MWs in increments of 0.1 MW.

Any remaining monies collected by the ISO pursuant to Section 5.14.1 and 5.14.2 will be applied as specified in Section 5.14.3.

5.14.2.2 Additional Provisions Applicable to External Installed Capacity Suppliers

In addition to the general provisions set forth in Section 5.14.2.1 above that are applicable to External Installed Capacity Suppliers as Installed Capacity Suppliers, the following provisions shall also apply to External Installed Capacity Suppliers.

In the event that an External Installed Capacity Supplier fails to deliver to the NYCA the Energy associated with the Unforced Capacity it committed to the NYCA due to a failure to obtain appropriate transmission service or rights, the External Installed Capacity Supplier shall be deemed to have a shortfall from the last time the External Installed Capacity Supplier “demonstrated” delivery of its Installed Capacity Equivalent (“ICE”), or any part thereof, until it next delivers its ICE or the end of the term for which it certified the applicable block of Unforced Capacity, whichever occurs first, subject to the limitation that any prior lack of demonstrated delivery will not precede the beginning of the period for which the Unforced Capacity was

certified. An External Installed Capacity Supplier deemed to have a shortfall shall be required to pay to the ISO a deficiency charge equal to one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction for the applicable month, prorated for the number of hours in the month that External Installed Capacity Supplier is deemed to have a shortfall (i.e., $((\text{deficiency charge} \div 12 \text{ months}) \div \text{total number of hours in month when shortfall occurred}) * \text{number of hours the shortfall lasted}) * \text{number of MWs of shortfall}$).

5.14.2.3 Additional Provisions Applicable to RIPs

In addition to the general provisions set forth in Section 5.14.2.1 above that are applicable to RIPs as Installed Capacity Suppliers, this Section 5.14.2.3 establishes the following four specific shortfalls applicable to RIPs: 1. shortfall for Provisional ACL; 2. shortfall for Incremental ACL; 3. shortfall for SCR Change of Status; and 4. shortfall for RIP portfolio performance. The deficiency charge for any such shortfall shall be equal to the Unforced Capacity equivalent of the shortfall multiplied by one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined using the applicable ICAP Demand Curve for the ICAP Spot Market Auction for each month the RIP is deemed to have a shortfall.

There are three distinct measures of shortfall that are applicable to a RIP, described in this Section 5.14.2.3, where individual SCRs that have been enrolled with a Provisional ACL or an Incremental ACL, or that experience a SCR Change of Status may result in a shortfall. When a RIP is subject to multiple deficiency charges for the same SCR for the same Capability Period, the ISO shall assess to the RIP only the greatest deficiency charge related to such SCR. In addition, if the shortfall results in a reduction in the performance of a SCR, the ISO may recover from the RIP any energy payments for which the SCR was ineligible to receive.

5.14.2.3.1 Shortfall for Provisional ACL

Prior to the Summer 2014 Capability Period if the Installed Capacity Supplier is a Responsible Interface Party, after each Special Case Resource with a Provisional Average Coincident Load has its Average Coincident Load determined for the Capability Period in which it had a Provisional Average Coincident Load (such determination in accordance with ISO Procedures and without regard to whether the resource was registered to the same Responsible Interface Party at the time of the ACL determination), the ISO shall determine if there is a shortfall due to the Provisional Average Coincident Load being higher than the Average Coincident Load. This shortfall will be equal to the value, if positive, of (x) the sum of (i) the amount of UCAP a Responsible Interface Party sold in an Monthly or an ICAP Spot Market Auction or certified Bilateral Transactions for a Special Case Resource and (ii) the Special Case Resource's actual metered demand for the month in accordance with ISO Procedures, minus (y) the Special Case Resource's Average Coincident Load. If the ISO does not receive data to determine the Average Coincident Load in accordance with ISO Procedures, for each Capability Period a Special Case Resource had a Provisional Average Coincident Load, for purposes of determining the shortfall, the Average Coincident Load shall equal zero.

Beginning with the Summer of 2014 Capability Period if the Installed Capacity Supplier is a Responsible Interface Party, after each SCR with a Provisional ACL has its Verified ACL determined for the Capability Period in which it had a Provisional ACL (such determination in accordance with Section 5.12.11.1 and ISO Procedures) the ISO shall determine if there is a shortfall due to the Provisional ACL being greater than the Verified ACL. This shortfall shall be equal to the value, if positive, of (x) the Provisional ACL of the SCR, minus (y) the Verified ACL of the SCR. The shortfall calculated for the SCR for a month shall not exceed the amount of Installed Capacity associated with the SCR that was sold for that month. If the ISO does not

receive data to determine the SCR's Verified ACL for the Capability Period for which the SCR was enrolled with a Provisional ACL the Verified ACL shall equal zero.

5.14.2.3.2 Shortfall for Incremental ACL

If the Installed Capacity Supplier is a RIP that reported an Incremental ACL, the ISO shall determine there is a shortfall when the Net ACL is greater than the Verified ACL. This shortfall shall be equal to the value, if positive, of (x) the enrolled Net ACL of the SCR, minus (y) the Verified ACL of the SCR for each month in which the RIP sold the SCR's Installed Capacity. The shortfall calculated for the SCR for a month shall not exceed the amount of Installed Capacity associated with the SCR that was sold for that month. If the ISO does not receive data to determine the Verified ACL for each month within the Capability Period that the SCR was enrolled with an Incremental ACL, the Monthly ACL for each unreported month shall equal zero (0) and be used in the calculation of the Verified ACL in accordance with Section 5.12.11.1.5.

5.14.2.3.3 Shortfall for SCR Change of Status

If the Installed Capacity Supplier is a RIP, and a SCR Change of Status occurs, the ISO shall determine if a shortfall exists, based on the RIP's reporting of the SCR Change of Status.

When a SCR Change of Status is reported by the RIP in advance and no Installed Capacity associated with the SCR has been sold, a shortfall has not occurred. If the SCR Change of Status is reported by the RIP, but the Installed Capacity associated with the SCR has already been sold for one or more months a shortfall exists for these months, the shortfall shall be equal to the reduction to the ACL reported in the SCR Change of Status, but shall not exceed the amount of Installed Capacity sold for each month.

When the RIP fails to report the SCR Change of Status during the Capability Period, for each month in which the SCR's Installed Capacity was sold and the SCR Change of Status was in effect, the ISO shall determine the shortfall MW using the maximum one hour metered Load for the month. The shortfall amount for each month in which the SCR Change of Status was in effect shall equal the value of SCR ACL minus the maximum one hour metered Load for the month, but shall not exceed the SCR's Installed Capacity sold for the month.

5.14.2.3.4 Shortfall for RIP Portfolio Performance

In addition to the shortfall evaluations based on individual SCRs, a RIP is subject to a shortfall evaluation, by Load Zone, for its entire SCR portfolio. In this evaluation the shortfall shall be determined for each Load Zone separately. A shortfall will occur if the total of the amount of UCAP sold by the RIP for a month in a Capability Period Auction or a Monthly Auction and certified prior to that month's ICAP Spot Market Auction, the UCAP sold in that month's ICAP Spot Market Auction, and the UCAP sold as a Bilateral Transaction and certified prior to that month's ICAP Spot Market Auction is greater than the greatest quantity MW reduction achieved during a single hour in a test or event called by the ISO in the Capability Period as confirmed by data by the ISO in accordance with ISO Procedures (or the value of zero if data is not received by the ISO in accordance with such procedures).

5.14.3 Application of Installed Capacity Supplier Deficiency Charges

Any remaining monies collected by the ISO through supplemental supply fees or Installed Capacity Supplier deficiency charges pursuant to Section 5.14.1 but not used to procure Unforced Capacity on behalf of LSEs or Installed Capacity suppliers deemed to have a shortfall shall be applied as provided in this Section 5.14.3.

5.14.3.1 General Application of Deficiency Charges

Except as provided in Section 5.14.3.2, remaining monies will be applied to reduce the Rate Schedule 1 charge in the following month.

5.14.3.2 Installed Capacity Rebates

(i) New York City

If an Unforced Capacity shortfall exists during any month, the ISO shall rebate any remaining unspent deficiency charges or supplemental supply fees collected for that month for the New York City Locality allocated among all LSEs in that Locality in proportion to their share of the applicable Locational Minimum Installed Capacity Requirement. Rebates shall include interest accrued between the time payments were collected and the time that rebates are paid.

(ii) Long Island

If an Unforced Capacity shortfall exists during any month, the ISO shall rebate any remaining unspent deficiency charges or supplemental supply fees collected for that month for the Long Island Locality, allocated among all LSEs in that Locality in proportion to their share of the applicable Locational Minimum Installed Capacity Requirement. Rebates shall include interest accrued between the time payments were collected and the time that rebates are paid.

(iii) G-J

If an Unforced Capacity shortfall exists during any month, the ISO shall rebate any remaining unspent deficiency charges or supplemental supply fees collected for that month for the G-J Locality, allocated among all LSEs in that Locality in proportion to their share of the applicable Locational Minimum Installed Capacity Requirement. Rebates shall include interest accrued between the time payments were collected and the time that rebates are paid.

(iv) Rest of State

If an Unforced Capacity shortfall exists during any month, the ISO shall rebate any remaining unspent deficiency charges or supplemental supply fees collected for that month for the Rest of State requirements, allocated among all LSEs in each of the Localities and in Rest of State, in proportion to each LSE's share of the NYCA Minimum Installed Capacity Requirement less that LSE's Locational Minimum Installed Capacity Requirement. Rebates shall include interests accrued between the time payments were collected and the time that rebates are paid.

5.15 Payment and Allocation of Installed Capacity Auction Rebates

The ISO shall rebate to all LSEs with Locational Minimum Installed Capacity Requirements in the New York City Locality, except NYPA, any Excess Amount that remains after the completion of an auction. Such rebates shall be allocated among all New York City LSEs, except NYPA, in proportion to their share of the Locational New York City Installed Capacity Requirement, regardless of whether they actually took part in the Capability Period Auctions or Monthly Auctions. The ISO shall allocate such rebates among In-City LSEs except NYPA on a monthly basis. Rebates shall include interest accrued between the time they were collected and the time that they are paid.

5.16 New Capacity Zone Study and Procedures

Capitalized terms used in this Section 5.16 and not defined in this Services Tariff shall have the meaning set forth in the Open Access Transmission Tariff.

The ISO shall conduct the New Capacity Zone study in accordance with this Section (“NCZ Study”) and provide a written report of the results to stakeholders on or before January 15 in each ICAP Demand Curve Reset Filing Year.

5.16.1 NCZ Study Methodology.

5.16.1.1 The NCZ Study, developed in accordance with ISO Procedures, will test, under summer peak system conditions, using the following assumptions and methodology:

5.16.1.1.1 The following assumptions will be applied: (i) transmission facilities (other than existing merchant transmission projects) identified as existing in the ISO’s Load and Capacity Data report most recently published prior to the NCZ Study Start Date; (ii) all firm plans for changes to transmission facilities by Transmission Owners in the ISO’s Load and Capacity Data report most recently published prior to the NCZ Study Start Date scheduled to be in-service prior to the NCZ Study Capability Period; (iii) planned generation projects or Merchant Transmission Facilities that have accepted either (a) Deliverable MW or (b) a System Deliverability Upgrade cost allocation and provided cash or posted required security pursuant to OATT Attachment S, which for (a) and (b) is from a Class Year Final Decision Round that occurs prior to the NCZ Study Start Date (subject to Section 5.16.1.1.2); (iv) System Upgrade Facilities and System Deliverability Upgrades associated with planned projects identified in (iii) above,

except that System Deliverability Upgrades where construction of the System Deliverability Upgrade has been deferred pursuant to OATT Attachment S Sections 25.7.12.2 and 25.7.12.3 will only be included if construction of the System Deliverability Upgrades has been triggered under OATT Attachment S Section 25.7.12.3; (v) all transmission retirements and derates identified in the ISO's Load and Capacity Data report most recently published prior to the NCZ Study Start Date and scheduled to occur prior to the NCZ Study Capability Period; (vi) all existing Generators with CRIS identified in, and all projects with Unforced Capacity Deliverability Rights on the date of, the ISO's Load and Capacity Data report most recently published prior to the NCZ Study Start Date; and all CRIS rights from resources considered "deactivated" as defined in OATT Attachment S Section 25.9.3.1 unless the ability to transfer those rights has expired without completing a transfer as permitted under OATT Attachment S Section 25.9.4 or 25.9.5 as of the NCZ Study Start Date; and (vii) any transfer of CRIS rights pursuant to OATT Attachment S not identified in the Load and Capacity Data report most recently published prior to the NCZ Study Start Date but is completed and the transferee is operational prior to the NCZ Study Start Date.

5.16.1.1.2 Planned generation and Merchant Transmission Facilities identified pursuant to Section 5.16.1.1.1 will be excluded and not recognized in the NCZ Study if (a) the Commission has accepted the cancellation or termination of a rate schedule consisting of an Interconnection Agreement (absent the filing of another Interconnection Agreement for the project), or (b) for projects that either do not

have an executed Interconnection Agreement or have an executed Interconnection Agreement that is (i) not required to be filed with the Commission or (ii) is required to be filed but has not yet been filed, the ISO receives written notice from the project that it is withdrawing from the interconnection queue and/or a Notice of Termination under the interconnection agreement.

5.16.1.1.3 The Load forecast used will be the NCZ Study Capability Period peak demand forecast contained in the ISO's Load and Capacity Data report most recently published prior to the NCZ Study Start Date.

5.16.1.1.4 The base case conditioning steps contained in OATT Attachment S Sections 25.7.8.2.3 (excluding and not recognizing MW of CRIS requested by Developers other than CRIS identified in Section 5.16.1.1.1 (iii)), 25.7.8.2.4, 25.7.8.2.5, 25.7.8.2.10, and 25.7.8.2.11, will be applied to the above inputs and assumptions.

5.16.1.1.5 The ISO will perform the NCZ Study by applying to the above inputs and assumptions the methodology contained in OATT Attachment S Sections 25.7.8.2.6, 25.7.8.2.7, 25.7.8.2.8, 25.7.8.2.9, 25.7.8.2.12, and 25.7.8.2.13 to Highways. Deliverability will be determined through a shift from generation to generation within each Capacity Region that contains Highways. Each such Capacity Region will be tested on an individual basis.

5.16.1.2 On or before October 1 of the year prior to an ICAP Demand Curve Reset Filing Year, the ISO will review the inputs and assumptions for the NCZ Study with stakeholders and provide an opportunity for stakeholders to comment.

5.16.1.3 The ISO shall provide an opportunity for the Market Monitoring Unit to review and comment on the NCZ Study consistent with Services Tariff Attachment O Section 30.4.6.3.2.

5.16.2 New Capacity Zone Boundary

The ISO shall identify the boundary of a New Capacity Zone if there is a constrained Highway interface into one or more Load Zones. The boundary of the New Capacity Zone may encompass a single constrained Load Zone or group of Load Zones including one or more constrained Load Zones on the constrained side of the Highway. In determining the New Capacity Zone boundary, the ISO shall consider the extent to which incremental Capacity in individual constrained Load Zones could impact the reliability and security of constrained Load Zones, taking into account interface capability between constrained Load Zones.

5.16.3 Indicative NCZ Locational Minimum Installed Capacity Requirement

For each Load Zone or groups of Load Zones identified in the NCZ Study as having a constrained Highway Interface, on or before March 1 of each ICAP Demand Curve Reset Filing Year, the ISO shall determine Indicative NCZ Locational Minimum Installed Capacity Requirement. The ISO shall provide an opportunity to stakeholders to review and comment on the Indicative NCZ Locational Minimum Installed Capacity Requirement. This Indicative NCZ Locational Minimum Installed Capacity Requirement will be used solely for establishing revised ICAP Demand Curves in accordance with 5.14.1.2.

5.16.4 NCZ Report

On or before March 31 of an ICAP Demand Curve Reset Filing Year,

- (a) If the NCZ Study identifies a constrained Highway Interface, the ISO shall file for Commission review proposed tariff revisions necessary to establish and recognize the New Capacity Zone or Zones, and shall include in the filing a report of the results of the NCZ Study. If the ISO proposes that a New Capacity Zone that is comprised of a group of Load Zones instead of a single Load Zone, the ISO shall include in the filing the basis for its determination, consistent with Section 5.16.2.
- (b) If the NCZ Study does not identify a constrained Highway interface, the ISO shall file with the Commission the ISO's determination that the NCZ Study did not indicate that any New Capacity Zone is required pursuant to this process, along with a report of the results of the NCZ Study.

The ISO shall provide an opportunity for the Market Monitoring Unit to review and comment on the NCZ Study and any proposed tariff revisions, consistent with Services Tariff Attachment O Section 30.4.6.3.2.

5.17 Expedited Dispute Resolution Procedures

5.17.1 Five-Day Consultation Period

Parties to a dispute involving a matter that is subject to the procedures of this section must immediately confer and attempt to resolve the dispute on an informal basis. If the parties are unable to resolve the dispute within five (5) calendar days by mutual agreement, the dispute shall be immediately submitted to the ISO's Dispute Resolution Administrator ("DRA").

5.17.2 Written Submissions

Immediately upon conclusion of the five-day consultation period, the party requesting the dispute resolution shall submit to the DRA and all other parties to the dispute, a concise written statement specifying that expedited dispute resolution under this section is requested and describing the nature of the dispute, the issues to be resolved and the specific award requested. The party opposing the requested relief shall then have five (5) calendar days to submit to the DRA and the party requesting the dispute resolution, a concise written response which shall include a proposed disposition of the dispute.

5.17.3 Appointment of the Arbitrator

The DRA shall keep at all times a list of ten (10) qualified arbitrators for matters which may be subject to the procedures of this section. Within five (5) calendar days of receipt of a request for dispute resolution under this section, the DRA shall appoint one arbitrator from that list to preside over the dispute. The arbitrator shall be selected by the DRA by randomly drawing names from the list until an available arbitrator is found. If none of the arbitrators on the list is available, the DRA shall appoint a qualified arbitrator to preside over the dispute. No person shall be eligible to act as an arbitrator who is a past or present officer, employee of, or

consultant to any of the disputing parties, or of an entity related to or affiliated with any of the disputing parties, or is otherwise interested in the matter to be arbitrated except upon the express written consent of the parties. Any individual appointed as an arbitrator shall make known to the disputing parties any such disqualifying relationship or interest and a new arbitrator shall be appointed by the DRA, unless express written consent is provided by each party.

5.17.4 Arbitration Proceeding

There shall be no right to discovery between the parties, including, but not limited to, depositions, interrogatories or other information requests. The arbitrator may request, and the parties shall produce, any information in addition to the written statements that is deemed by the arbitrator to be relevant to the issues presented. The arbitrator shall resolve the arbitration matter solely on the basis of the written statements and evidence submitted by the parties unless, in the sole discretion of the arbitrator, a hearing is deemed necessary. Any such hearing shall be limited to one (1) day and conducted in accordance with the procedures determined by the arbitrator. Absent agreement to the contrary by all parties to the dispute, no person or entity shall be permitted to intervene. Except as otherwise set forth in this section, the arbitrator will follow the Commercial Arbitration Rules of the American Arbitration Association and the expedited procedures contained therein.

5.17.5 Arbitration Award

Within fifteen (15) calendar days of the appointment of the arbitrator, the arbitrator shall select as an arbitration award the award proposed by one of the parties in their written submission (except that, in disputes concerning the development of regional Load growth factors pursuant to Section 5.10 of this Tariff, the arbitration award shall be either the forecast developed by the Transmission Owner or by the ISO) and shall render a concise written decision

including findings of fact and the basis for the decision. All costs associated with the time, expenses, and other charges of the arbitrator shall be borne by the unsuccessful party. Each party shall bear its own costs, including attorney and expert fees, if any. No award shall be deemed to be precedential in any other arbitration related to a different dispute.

5.17.6 Limited Appeal

The decision of the arbitrator shall be final and binding upon the parties, except that, within one year of the arbitration decision, a party may request that any federal, state regulatory or judicial authority (in the State of New York) having jurisdiction take such action as may be appropriate with respect to any arbitration decision that is based on fraudulent conduct or demonstrable bias of the arbitrator.

5.18 Generator Outages and Generator Obligations While in These Outages

This Section 5.18 shall apply to a Generator in any outage state that started on or after May 1, 2015.

A Market Participant with a Generator in the NYCA that is in any outage state shall report this status to the ISO pursuant to ISO Procedures.

5.18.1 Forced Outages and Commenced Repair Determinations

5.18.1.1 A Market Participant with a Generator in a Forced Outage shall keep the ISO informed as to progress of its Generator's repairs pursuant to ISO Procedures. A Market Participant may keep its Generator in a Forced Outage beyond the last day of the month which contains the 180th day of its Forced Outage only if it has Commenced Repair of its Generator. A Market Participant that anticipates its Generator will not be able to return to the Energy market before the last day of the month which contains the 180th day of its Forced Outage and which desires to remain eligible to be in the Installed Capacity market beyond the 180th day shall provide a Repair Plan to the ISO by the 120th day of the Forced Outage.

5.18.1.2 A Repair Plan shall include a work plan, with milestones, or set of necessary actions, and shall provide the time it is expected to take to complete each task and describe the repair of the Generator's equipment related to electric production, fuel or station power supply or transmission interconnection, as appropriate, that was either affected by the Forced Outage or otherwise makes the unit available for the Energy market. The Repair Plan's milestones shall include, in appropriate circumstances: damage assessments, engineering assessments,

initial cost estimates, purchase orders, inspection reports, initial safety assessments, hazardous material abatement plans, and labor mobilization plans.

The Repair Plan shall include the date the Market Participant expects the Generator to be repaired and available for the Energy market (return date) which return date: i) shall be reasonable, ii) may be provided as a good faith estimate, and iii) shall be updated to the extent new information becomes available. The return date or good faith estimate of a return date that a Market Participant provides for its Generator shall be reasonable if it is comparable to the return date that would be included in a Credible Repair Plan pursuant to Section 5.18.1.4 of this Services Tariff.

5.18.1.3 Market Participants requesting that the NYISO determine, pursuant to Services Tariff Section 23.4.5.6.2, that their Generator has experienced a Catastrophic Failure, or that Exceptional Circumstances will delay the submission of data necessary for the ISO to perform an audit and review pursuant to Section 23.4.5.6.2, shall submit their requests, with necessary supporting data, to the NYISO by the 120th day of the Forced Outage if they desire the determination to be issued by the 160th day of the Forced Outage of their Generator.

5.18.1.4 A Market Participant has Commenced Repair of its Generator if it: i) has decided to pursue the repair of its Generator, and based on the ISO's technical/engineering evaluation, ii) has a Repair Plan for the Generator that is consistent with a Credible Repair Plan, and iii) has made appropriate progress in pursuing the repair of its Generator when measured against the milestones of a Credible Repair Plan.

5.18.1.5 For purposes of the determinations required by Section 5.18.1.3(ii) and (iii), and 5.18.1.6 of this Services Tariff, a Credible Repair Plan is the Repair Plan that would be expected from a supplier: i) with a generating facility that is reasonably the same as or similar to the type and vintage of the Generator; ii) intending to return its generating facility to service. A Credible Repair Plan for a Generator that suffered a Forced Outage is a Repair Plan that would also be expected from a supplier with a generating facility that suffered a forced outage that was reasonably the same as or comparable to the Forced Outage suffered by the Generator and which forced outage occurred under the same, or reasonably similar, circumstances as the Generator's. A Credible Repair Plan for a Generator in a Mothball Outage is a Repair Plan that would also be expected from a supplier pursuing a repair to its generating facility which repair is reasonably the same as or comparable to the repair being pursued by the Generator.

5.18.1.6 The determination that a Market Participant has Commenced Repair of its Generator in a Forced Outage shall be made by the ISO by the 160th day of the Forced Outage. If the Market Participant provides updated information after the 120th day of the Forced Outage and before the 180th day of its Generator's Forced Outage, the ISO will, as applicable, take such information into consideration to make its determination or it will update its previously issued determination to the extent practicable.

The determination that a Market Participant has Commenced Repair of its Generator in an ICAP Ineligible Forced Outage, which Market Participant has been determined by the ISO to have one or more Exceptional Circumstances that

delay the acquisition of necessary data for an audit and review for economic justification pursuant to Section 23.4.5.6.2 of this Services Tariff, shall be made by the ISO as soon as practicable following receipt of necessary data.

The determination that a Market Participant has Commenced Repair of its Generator in an ICAP Ineligible Forced Outage or Mothball Outage, which Market Participant is seeking to toll expiration of its outage and CRIS rights pursuant to Sections 5.18.2.3.2 or 5.18.3.3.2 of this Services Tariff, will be made by the ISO as soon as practicable following receipt of the necessary data.

5.18.1.7 If a Market Participant has not Commenced Repair of its Generator by the last day of the month which contains the 180th day of the Forced Outage, the Generator's Forced Outage shall expire on the last day of the month which contains the 180th day of the Forced Outage. The Forced Outage of a Generator that Commenced Repair but ceased or unreasonably delayed the Generator's repair shall terminate on the last day of the month containing the date that the Market Participant ceased or unreasonably delayed the repair. The ISO will determine a Market Participant has unreasonably delayed the repair of its Generator if such delay would not have been included in a Credible Repair Plan from a supplier experiencing the situation which caused the Market Participant to delay the repair of its Generator.

5.18.1.8 Upon the expiration or termination of a Generator's Forced Outage, the Generator shall be in an ICAP Ineligible Forced Outage unless the Generator has been Retired by the Market Participant.

5.18.2 ICAP Ineligible Forced Outage

5.18.2.1 A Market Participant may voluntarily reclassify its Generator from a Forced Outage to an ICAP Ineligible Forced Outage only if the Generator has been in a Forced Outage for at least sixty (60) days. A Generator that has been voluntarily reclassified from a Forced Outage to an ICAP Ineligible Forced Outage shall begin its ICAP Ineligible Forced Outage on the first day of the month following the month in which it was voluntarily reclassified to an ICAP Ineligible Forced Outage.

A Generator in an ICAP Ineligible Forced Outage as a result of the expiration or termination of its Forced Outage pursuant to Section 5.18.1.6 of this Services Tariff, shall begin its ICAP Ineligible Forced Outage on the day following the day the Generator's Forced Outage expired or terminated.

A Generator in an ICAP Ineligible Forced Outage as a result of substantial actions that have been taken, such as dismantling or disabling essential equipment, which actions are inconsistent with an intention to operate the Generator in the Energy market shall begin its ICAP Ineligible Forced Outage on the day following the day such actions began.

5.18.2.2 A Generator in an ICAP Ineligible Forced Outage is not eligible to participate in the Installed Capacity market and shall automatically cease to qualify to participate in the Installed Capacity market beginning with the first day of its ICAP Ineligible Forced Outage. The Generator shall no longer be ineligible to participate in the Installed Capacity market, by virtue of its ICAP Ineligible Forced Outage, as of the first day the Generator returns to operation and offers its Energy into the Day-Ahead Market without declaring an outage. The month for

which the Generator will first be eligible to participate in the Installed Capacity market will be based on the date the Generator returns to operation and offers its Energy into the Day-Ahead Market without declaring an outage and ISO Procedures.

5.18.2.3 ICAP Ineligible Force Outage Expiration

5.18.2.3.1 Except as provided in Section 5.18.2.3.2, a Generator's ICAP Ineligible Forced Outage shall expire if: i) its CRIS rights have expired; or ii) it did not have CRIS rights and has been in the ICAP Ineligible Forced Outage for 36 consecutive months. A Generator shall be Retired if its ICAP Ineligible Forced Outage expires.

5.18.2.3.2 If a Market Participant with a Generator in an ICAP Ineligible Forced Outage has Commenced Repair prior to when the ICAP Ineligible Forced Outage would expire pursuant to Section 5.18.2.3.1 and has provided a reasonable return date as that term is described in Section 5.18.1.2 of this Services Tariff that occurs after such expiration date, then the outage and the Generator's CRIS rights will be tolled until, and the ICAP Ineligible Forced Outage will expire on, the earlier of:

- i) 120 days from when the outage would have expired under Section 5.18.2.3.1; or
- ii) an ISO determination that the Market Participant has ceased or unreasonably delayed the repair of its Generator. The ISO will determine if a Market Participant has unreasonably delayed the repair of its Generator if such delay would not have been included in a Credible Repair Plan from a supplier experiencing the situation which caused the Market Participant to delay the repair of its Generator. The tolling of CRIS rights occurs under this Section 5.18.2.3.2 notwithstanding the

three year period in which deactivated facilities may maintain CRIS rights pursuant to Section 25.9.3.1 of Attachment S to the OATT; provided, however, the expiration period for transfers of CRIS rights provided in Section 25.9.3.1 of Attachment S to the OATT shall not be tolled. A Market Participant seeking to toll its outage and CRIS rights pursuant to this Section 5.18.2.3.2 must submit a Repair Plan no later than 60 days prior to when the ICAP Ineligible Forced Outage would expire under Section 5.18.2.3.1.

5.18.2.4 A Market Participant with a Generator in an ICAP Ineligible Forced Outage that is notified by a Transmission Owner or the ISO that the return to service of its Generator could address a reliability issue shall provide an updated good faith estimate of the Generator's return date. A Market Participant with a Generator in an ICAP Ineligible Forced Outage shall make a timely return to service to resolve a reliability issue, in accordance with Section 5.18.4, as the term "timely return" is described in Section 5.18.4.2 of this Services Tariff. A Market Participant with a Generator in an ICAP Ineligible Forced Outage shall provide temporary use of its Generator's interconnection point in accordance with Section 5.18.5 of this Services Tariff when a transmission solution using the Generator's interconnection point has been selected as either the Gap Solution or to resolve a reliability issue arising on a non-New York State Bulk Power Transmission Facility during its outage. The Transmission Owner shall provide that power to the station remains available notwithstanding its temporary use of the Generator's interconnection point.

5.18.3 Mothball Outage

5.18.3.1 A Generator in a Mothball Outage is not eligible to participate in the Installed Capacity market and shall automatically cease to qualify to participate in the Installed Capacity market beginning with the date the Generator begins its Mothball Outage. The Generator shall no longer be ineligible to participate in the Installed Capacity market, by virtue of its Mothball Outage, as of the first day the Generator returns to operation and offers its Energy into the Day-Ahead Market without declaring an outage. The month for which the Generator will first be eligible to participate in the Installed Capacity market will be based on the date the Generator returns to operation and offers its Energy into the Day-Ahead Market without declaring an outage and ISO Procedures.

5.18.3.2 No later than 60 days before starting the Mothball Outage of its Generator, a Market Participant shall notify the ISO whether its Generator will be physically able to return within 180 days to resolve a reliability issue or it has good cause for an alternate period of time, stated in days, to return its Generator to service to resolve a reliability issue. The Market Participant shall establish good cause, to the satisfaction of the ISO, by providing empirical evidence demonstrating the need for the alternate period of time to return its Generator to service to resolve a reliability issue. The number of days within which a Generator in a Mothball Outage can be returned to service to resolve a reliability issue will be shared with the applicable Transmission Owner(s).

5.18.3.3 Mothball Outage Expiration

5.18.3.3.1 Except as provided in Section 5.18.3.3.2, a Generator's Mothball Outage

shall expire if: i) its CRIS rights have expired; or ii) it did not have CRIS rights and has been in the Mothball Outage for 36 consecutive months. A Generator shall be Retired if its Mothball Outage expires.

5.18.3.3.2 If a Market Participant with a Generator in a Mothball Outage has Commenced Repair prior to when the Mothball Outage would expire pursuant to Section 5.18.3.3.1 and has provided a reasonable return date as that term is described in Section 5.18.1.2 of this Services Tariff that occurs after such expiration date, then the outage and the Generator's CRIS rights will be tolled until, and the Mothball Outage will expire on, the earlier of: i) 120 days from when the outage would have expired under Section 5.18.3.3.1; or ii) an ISO determination that the Market Participant has ceased or unreasonably delayed the repair of its Generator. The ISO will determine if a Market Participant has unreasonably delayed the repair of its Generator if such delay would not have been included in a Credible Repair Plan from a supplier experiencing the situation which caused the Market Participant to delay the repair of its Generator. The tolling of CRIS rights occurs under this Section 5.18.3.3.2 notwithstanding the three year period in which deactivated facilities may maintain CRIS rights pursuant to Section 25.9.3.1 of Attachment S to the OATT; provided, however, the expiration period for transfers of CRIS rights provided in Section 25.9.3.1 of Attachment S to the OATT shall not be tolled. A Market Participant seeking to toll its outage and CRIS rights pursuant to this Section 5.18.3.3.2 must submit a Repair Plan no later than 60 days prior to when the Mothball Outage would expire under Section 5.18.3.3.1.

5.18.3.4 A Market Participant with a Generator in a Mothball Outage shall timely return the Generator to service to resolve a reliability issue, in accordance with Section 5.18.4, as the term ‘timely return’ is described in Section 5.18.4.2 of this Services Tariff. A Market Participant with a Generator in a Mothball Outage shall provide temporary use of its Generator’s interconnection point, in accordance with Section 5.18.5 of this Services Tariff, when a transmission solution using the Generator’s interconnection point has been selected as either the Gap Solution or to resolve a reliability issue on a non-New York State Bulk Power Transmission Facility arising during the Generator’s outage. The Transmission Owner shall provide that power to the station remains available notwithstanding its temporary use of the Generator’s interconnection point.

5.18.4 Return to Service of Generators in a Mothball Outage or an ICAP Ineligible Forced Outage to Resolve a Reliability Issue

5.18.4.1 Following: i) notification to a Market Participant that the return to service of its Generator in a Mothball Outage or an ICAP Ineligible Forced Outage for a specified minimum time period has been selected as either a Gap Solution or to resolve a reliability issue on a non-New York State Bulk Power Transmission Facility arising during the Generator’s outage; ii) negotiations with the applicable Transmission Owner to effectuate such return; and iii) an order establishing compensation for such return from the Federal Energy Regulatory Commission (“Compensation Order”), the Market Participant shall timely return the Generator to service, as the term “timely return” is defined in Section 5.18.4.2 of this Services Tariff.

5.18.4.1.1 Within 30 days of a determination by the ISO and the Market Participant that

negotiations on compensation for the return to service of the Market Participant's Generator are at an impasse, the Market Participant may submit a filing to the Federal Energy Regulatory Commission under Section 205 of the Federal Power Act for compensation. No later than ten days after such filing is made, the ISO shall file with the Federal Energy Regulatory Commission an unexecuted compensation agreement that includes the non-rate terms and conditions for the return to service of the Market Participant's Generator.

5.18.4.2 A Market Participant's return to service of its Generator in a Mothball Outage to resolve a reliability issue shall be deemed to be a timely return if such return to service was i) within 180 days from the date of the Compensation Order, ii) within the alternate period of time following the date of the Compensation Order pursuant to Section 5.18.3.2, or iii) by such other date agreed to by the parties.

A Market Participant's return to service of its Generator in an ICAP Ineligible Forced Outage to resolve a reliability issue shall be deemed to be a timely return if it is returned to service following the date of the Compensation Order; provided, however, the Market Participant will not be required to return the Generator to service before its estimated return date unless otherwise agreed.

5.18.4.2.1 A Generator's return to service shall not be untimely if the Generator provided the Transmission Owner with access to its interconnection point and is available for a timely return, and the Transmission Owner is unable to reconnect the Generator within the timeframes provided for a timely return to service, pursuant to Section 5.18.4.2 of this Services Tariff.

5.18.5 Temporary Use of Interconnection Point to Resolve a Reliability Issue

5.18.5.1 A Market Participant shall provide a Transmission Owner with temporary use of the interconnection point of its Generator in a Mothball Outage or ICAP Ineligible Forced Outage when a transmission solution using the Generator's interconnection point has been selected as either the Gap Solution or to resolve a reliability issue arising on a non-New York State Bulk Power Transmission Facility during its outage.

5.18.5.2 A Market Participant that provided temporary use of the interconnection point of its Generator in a Mothball Outage or ICAP Ineligible Forced Outage pursuant to Section 5.18.5.1 of this Services Tariff shall be permitted to reconnect its Generator to the transmission system by submitting to the ISO a Notice of Intent to Return that provides the date it intends to return to service which submission shall be provided no later than six months before the expiration of its outage, unless otherwise agreed. A Market Participant that submitted a Notice of Intent to Return and that was not requested to return its Generator to service to resolve a reliability issue pursuant to Section 5.18.4.1 of this Services Tariff during its immediately previous Mothball Outage or ICAP Ineligible Forced Outage, shall be permitted to reconnect at no cost.

The Transmission Owner shall reconnect the Generator on or before the indicated return date using efforts that are timely, consistent with Good Utility Practice and that are otherwise substantially equivalent to those the Transmission Owner would use for its own purposes. The Transmission Owner shall report

periodically to the ISO and the Generator on the progress of reconnecting such Generator and shall advise the ISO and the Generator promptly if it expects it will not be able to complete the reconnection of the Generator before its indicated return date.

If the Generator returning to service pursuant to this Section 5.18.5.2 of the Services Tariff is available to return but the Transmission Owner is unable to reconnect the Generator before its outage expires, the outage expiration, and expiration of its CRIS rights, where applicable, will be tolled until the date the Transmission Owner reconnects the Generator notwithstanding the three year period in which deactivated facilities may maintain CRIS rights pursuant to Section 25.9.3.1 of Attachment S to the OATT; provided, however, the expiration period for transfers of CRIS rights provided in Section 25.9.3.1 of Attachment S to the OATT shall not be tolled.

5.18.6 Retired and Termination of Existing Interconnection Agreements

The classification of a Generator with an interconnection agreement other than an Small Generator Interconnection Agreement (SGIA) or Standard Large Generator Interconnection Agreement (LGIA) as Retired may be grounds for the termination of the interconnection agreement depending on the terms and conditions of the applicable agreement. Any termination of such an interconnection agreement will be effective on the filing with the Federal Energy Regulatory Commission of a notice of termination, which notice and proposed effective date have been accepted by the Federal Energy Regulatory Commission. Either party to the interconnection agreement may file the notice of termination,

as appropriate. If and when termination of the interconnection agreement is effective, access to the Point of Interconnection of the Generator will be available on a non-discriminatory basis pursuant to the NYISO's applicable interconnection and transmission expansion processes and procedures. If the existing interconnection agreement is not terminated, the Retired Generator would retain its right to the specific point of interconnection as provided for in the interconnection agreement and access to this point would not be available for new projects.

The impact on a Generator with a LGIA or SGIA that has been classified as Retired is described in OATT Sections 30 and 32 respectively.